RADIO AMATEURS' JOURNAL





## CQ, The Radio Amateurs' Journal

#### Wayne Green, W2NSD Editor

Jim Morrissett, K2OLK Art Brothers, W7NVY/2 R. C. Spenceley, KV4AA Walt Burdine, W8ZCV Sam Harris, W1FZJ Associate Editor Associate Editor DX Editor Novice Editor VHF Editor George Jacobs, W3ASK Propagation Editor Byron Kretzman, W2JTP RTTY Editor Louisa B. Sando, W5RZJ YL Editor William I. Orr, W6SAI Contributing Editor Bob Adams, K2DW SSB Editor

#### Feature Articles

6-Meter 'TV' Antenna	Pete Maloney, K6HBY	19
Emergency A-C Generators	Lt. C. E. Donaldson, W4VXD/1	20
Sunspot Cycle 19: Part II	George Jacobs, W3ASK	24
GDO as Crystal Oscillator	Robert Ropes, W9PAP	30
75-Meter "Shorty" Ground Plane	Norm McLaughlin, W6GEG	31
2 on Two	Bert Green, W2LPC	33
Mobile Reference-Shift Modulator	Dale Hileman, K6DDV	36
Mobile Reference-Shift Modulator Frequency-Shift Converter	Arthur A. Usner, W5QHB	40
Good Day at Starved Rock	Jim Morrissett, K2OLK	46
YL Marine Radio Operators	Louisa B. Sando, W5RZJ	48
The Dayton Hamvention	Ed Bonnet, W8OVG	54
The Dayton Hamvention  Antennas are Easy	Wayne Green, W2NSD	53
Signal Separation	Guy Slaughter K9A7G	60
Windblowers VHF Society	Wayne Green, W2NSD	81
21-Mc Preamplifier	Henry McPeak, W2SHT	92

#### Departments

Propagation Special	24	VHF	70
55B	4/	Propagation	14
YL	48	RTTY	78
DX	62	Novice	82

#### Miscellaneous

Scratchi6	New Books 45
de W2NSD10	QSL Contest77
Letters to the Editor14	CQ World Atlas106
CQ World Globe	112

SR	Cowan				Publisher
J. S	stillman .		 	Advertising	Representative
Jack	N. Schne	ider	 	Advertising	Representative
R A	Cowan		 	Advertising	Representative

Branch Advertising Offices

Ted E. Schell, 2700 West 3rd St., Los Angeles 5, Calif. DUnkirk 2-4889
James D. Summers, 400 N. Michigan Ave., Chicago 1, III. SUperior 7-1641

Foreign Subscriptions
England: RSGB, New Ruskin House, Little Russell St.,

London WC 1. Australia: Technical Book Co., 297 Swanston St., Melbourne Cl, Victoria, Australia.

									Production Manager
									. Circulation Manager
									Draftsman
C.	W. Gardi	ner, Jr.		. 6		, ,	 ٠.		. Editorial Production

CQ—(title Reg. U.S. Post Office)—is published monthly by Cowan Publishing Corp. Executive and Editorial offices, 67 West 44th Street, New York 36, N. Y. Phone MUrray Hill 7-2080. 2nd Class Mail privileges authorized at New York, N. Y. Subscription rates in U.S.A., Possessions, APO PPO, Canada & Mexico. 1 year \$4.00; 2 years \$10.00. Pan-American and Foreign, 1 year \$6.00; 2 years \$10.00; 3 years \$16.00. Single copies 50 cents. Printed in U.S.A. Entire contents copyright 1956 by Cowan Publishing Corp. CQ does not assume responsibility for unsolicited manuscripts.

POSTMASTER: SEND FORM 3579 to CQ, 67 WEST 44th ST., NEW YORK, 36, N. Y.



FEATURES

Design proven through actual signal reports.

Only top-quality components used throughout.

5-point TVI suppression, and pi network output to match 50 to 600 ohms.

> Detailed construction manual for simplified assembly.

100 watts output on 160, 80, 40, 20, 15, 11, and 10 meters.

> Attractive and functional physical design.

The Heathkit Model DX-100 Transmitter is rapidly coming the "standard" ham rig in its power class. T high quality and outstanding performance it offers can matched only in equipment costing many dollars more features a built-in VFO, modulator, and power suppli and is bandswitching for phone or CW operation on 1 80, 40, 20, 15, 11, and 10 meters. The kit includes a tailed construction manual, the cabinet, all tubes, p wound coils, and all other parts necessary for construction

Push-pull 1625 tubes are used to modulate paral 6164 tubes for RF output in excess of 100 watts on photo and 120 watts on CW. May be excited from the built VFO or from crystals. Features pi network output circu illuminated VFO dial and meter face, and 5-point T suppression. High grade, well-rated parts supplied. Sch matic diagram and technical specifications on request.



MODEL DX-100

Shpg. Wt. 107 Lb

Shipped Motor Freight unless otherwise specifie \$50.00 deposit required on all C.O.D. orders.

#### antenna coupler

KIT

MODEL AC-1

Shpg. Wt. 4 Lbs.

In addition to matching a low power transmitter to an end-fed long wire antenna, this antenna coupler incorporates a 3-section low-pass filter, to attenuate output above 36 mc and reduce TVI. Handles up to 75 watts, 10 through 80 meters. 52 ohm coaxial input-tapped inductor and variable capacitor-neon RF indicator. Ideal for use with the Heathkit AT-1 Trans-



A Subsidiary of Daystrom, Inc.

BENTON HARBOR 12, MICHIGAN

grid dip meter KIT

The Model GD-1B is a time-proven instrument. It will enable you to accomplish literally hundreds of jobs on all types of equipment. Frequency range is from 2 mc to 250 mc. A 500 ua meter is employed for indication, and a sensitivity control and headphone jack are provided. Includes pre-wound coils and rack. Indispensable for the ham, serviceman, and engineer. Extra coils available to extend frequency down to 350 kc.



MODEL GD-1B Shpg. Wt. 4 Lbs.

......

HEATHKIT

## antenna impedance meter KIT

MODEL AM-1

Shpg. Wt. 2 Lbs.

Used with an RF signal source, the AM-1 will enable you to match your antenna-receiver-transmitter system for optimum operation. Will double as a phone monitor or relative field strength meter. Uses 100 ua meter, and covers 0 to 600 ohms. Frequency to 150 mc.

## HEATHKIT communications-type all band receiver KIT

Slide-rule dial -electrical andspread-ham bands marked. Slug-tuned coils and efficient IF transformers for good sensitivity and

selectivity. Transformeroperated power supply for safety ind high efficiency.



The Model AR-3 receiver features new high-Q slug-tuned coils, new layout, and new-type IF transformers. The result is high sensitivity and selectivity and better image rejection on all bands.

Transformer-type power supply, electrical bandspread, RF and AF gain controls, an-

tenna trimmer, AGC, BFO, headphone jacks, socket for Q multiplier, 5½" PM speaker and illuminated dial.

#### SPECIFICATIONS:

Frequency Range-550 kc to 30

mc on four bands.
Tube Complement—1—12BE6 os-Tube Complement—1—12BE6 os-cillator and mixer • 1—12BA6 IF amplifier • 1—12BA6 second detec-tor, AVC, first audio amplifier and reflex BFO • 1—12A6 beam power output • 1—5Y3 full wave rectifier



95 (Less Cabinet) MODEL AR-3 Shpg. Wt. 12 Lbs.

CABINET: Fabric-covered cabinet available. Includes aluminum panel, speaker grille, and protective rubber feet. Measures 124" W. x 64" H. x 74" D. No. 91-15, Shpg. Wt. 5 Lbs. \$4.50.

#### HEATHKIT CW amateur transmitter KIT Single-knob

bandswitching for 80, 40, 20, 15, 11, and 10 meters. anel meter monitors

final grid or plate current.

Plate power input 25-30 watts.

Best dollar-perwatt buy on the

6AU6 electron-

coupled Clapp

oscillator.

Copper plated chassis-aluminum

case—profuse

shielding—cer-amic coil forms,

switch wafers.



The AT-1 is complete with its own power supply, and covers 80, 40, 20, 15, 11, and 10 meters with single-knob bandswitching. Designed for crystal or external VFO excitation. Incorporates key-click filter, line filter, copper plated chassis, pre-wound coils, 52-ohm coaxial output, panel meter, and high quality components throughout. Easy to build, even for the beginner. Employs 6AG7 oscillator and 6L6 final. Up to 30 watts power input.



Shpg. Wt. 15 Lbs.

SPECIFICATIONS: RF Amplifier Power Input. . . 25-30 watts Output Connection 52 ohms Band Coverage 80, 40, 20, Tube Complement: 15, 11, 10 Meters Tube Complement:

5U4G. Rectifier 6AG7 Oscillator—Multiplier 6L6 Amplifier—Doubler

OA2 voltage regulator tube for stability.

overs 160-80-40-0-15-11-10 meters.

Smooth-acting, uminated and precalibrated dial.



The Model VF-1 features illuminated and pre-calibrated dial scale. Cable and plug provided to fit the crystal socket of any modern transmitter. Covers 160-80-40-20-15-11 and 10 meters with 3 basic oscillator frequencies. Better than 10 volt average RF output on fundamentals. Derives operating power from transmitter power supply. Has VR tube for stability. Go VFO for more operating enjoyment.

ORDER DIRECT FROM THIS AD . . . OR WRITE FOR FREE CATALOG. Describes more than 65 interesting "build-it-yourself" projects. Amateur equipment, hi fi amplifiers, and the complete Heathkit line of test instruments. Get yours today!



SPECIFICATIONS;


Output Frequencies — 1750-2000 kc, 7000-7425 kc, 6740-6808 kc. Calibrated Bands—160-80-40-20-15-11-10 meters. Tube Compliment—6AU6 Oscillator OA2 Voltage Regulator. Power Requirements—250-350 VDC @ 15-20 ma. and 6.3 VAC @ .45 A.



A Subsidiary of Daystrom, Inc.

BENTON HARBOR 12, MICHIGAN

Designed for Application



#### The No. 10000 WORM DRIVE UNIT

One of our original Designed For Application products, tried and proven over the years. Rugged cast aluminum frame may be panel or base mounted. Spring loaded nickel plated cut brass gears work with polished stainless steel worm to provide low back lash. ¼" diameter stainless steel drive and driven shafts. Available in two ratios, 16:1 and 48:1. Specify ratio in ordering.

MFG. CO., INC.

MAIN OFFICE AND FACTORY

MALDEN

MASSACHUSETTS





Feenix, An

Deer Hon. Ed:

Cupple weeks ago Scratchi are opening I mouth and putting Hon. Foots in it. Natcl ourally I are sorry that I not coming out top, but also hole thing are making me a lit sad. It are reely the story of the O.T. vers the Y.F.—the Old Timer versus the Yu Fellers.

It all getting started one evening at amchoclub meeting. Scratchi been sitting there, taki it all in. Heering talk from some brite yu geenyus from local communicayshun lab watelling how Hon. Tran Sisters going to maki it easy to having Arizona Kilowhat rigs in ve pocket.

Also having yung feller there from university who explaneing all abouts new developments in reseever designs, and according him, in another few yeers anybuddys can asseeving any kind signals from almost anywheres.

Next item of busyness are discussion How to Getting More Answers to Our Cand How to Working More Dee-X. This a point where Scratchi desiding that enuf a enuf, so I asking for floor.

Boy oh boys, are I telling them. I pointing out that yung amchoors these days aren't is trusted in knowing how to working mostayshuns, even the they saying they are. A these yung fellers doing is trying to add even newfangled idea that coming along to the rigs and reseevers.

Everytime sumbuddy riting artickle on ho to getting another two-tenths dee-b better noisingyour on reseever, they ripping out reseever front ends and re-wiring reseever sircut. I teling them that if they spending less times trying to re-bild there equipment, and more time trying to lerning how to being good operator then they having good chance to getting moranswers to there calls, and much better chancalso to working more dee-x.

I even going so far as to telling them the a reel good amchoor operator could takin old-time amchoor geer and running ring around the average yung amchoor with all his fancy cromeplated reseevers and sooper-doop er xmitters. It are at this point that all the

## NOW... MODEL SX-100 SELECTABLE SIDE BAND RECEIVER

#### **BUILT TO THE SPECIFICATIONS** OF 1.000.000 FIELD EXPERTS

See it at Your Jobber-only \$29500

Hallicrafters 22 years of production know-how, the engineering experience of developing over 100 different major receiver designs, plus the advice of over 1,000,000 field experts operating Hallicrafters receivers all are combined to bring you this outstanding new receiver—the SX-100! Hallicrafters alone, long recognized as the leading designer and manufacturer of quality communications equipment, can offer you the dependability and performance of this great new SX-100 at the amazingly low price of just \$295.00.

Look at these features you enjoy with the SX-100... before, they were available only on receivers costing a great deal more!

1. SELECTABLE SIDE BAND OPERATION.
2. "TEE-NOTCH" FILTER—This new development provides a stable non-regenerative system for the rejection of unwanted hetrodyne. The "Tee-Notch" also produces an effective steepening of the already excellent 50 KC i.f. pass band (made famous in the SX-96) and further increases the effectiveness of the advanced exalted carrier type reception.

3. NOTCH DEPTH CONTROL for maximum null adjustment.

4. ANTENNA TRIMMER.

5. PLUG IN LABORATORY TYPE EVACUATED 100 KC QUARTZ

CRYSTAL CALIBRATOR—included in price.
6. LOGGING DIALS FOR BOTH TUNING CONTROLS.
7. FULL PRECISION GEAR DRIVE DIAL SYSTEM.

8. SECOND CONVERSION OSCILLATOR CRYSTAL CON-TROLLED-greater stability through crystal control and additional temperature compensation of high frequency oscillator

#### Controls

Pitch Control Reception Standby Phone Jack Response control (upper and lower side band selector) Antenna Trimmer Notch Frequency Notch depth Calibrator on/off Sensitivity **Band Selector** Volume Tuning AVC on/off Noise limiter on/off Bandspread Selectivity

# hallicrafters

CHICAGO 24, ILLINOIS

Model SX-100. Amateur Net \$295.00 Matching R-46B Speaker \$17.95 Frequency Range 538kc-1580 kc 1720 kc-34 mc





Tells how thousands of brand-new, better paying radio-TV-electronics jobs are now open to FCC License Holders.

TELLS HOW .

An FCC License Can

Be Your Guarantee of Success in

Electronics

- Tells how we guarantee to train and coach you until you get your FCC License.
- Tells how our amazing Job-Finding Service helps you get the better paying job our training prepares you to hold.



CLEVELAND INSTITUTE OF RADIO ELECTRONICS Desk CQ-16, 4900 Euclid Bldg., Cleveland 3, Ohio (Address to Desk No. to avoid delay)

I want to know how I can get my FCC ticket in a minimum of time. Send me your FREE booklet, "How to Pass FCC License Examinations" (does not cover exams for Amateur License), as well as a Sample FCC-type lesson and the amazing new booklet, "Money-Making FCC License Information." Be sure to tell me about your Television Engineering Course.

Bincoring Course.	
Name Age	
Address	
City Zone State  FOR PROMPT RESULTS SEND AIR MAIL  Special tuition refer to members of the U.S. Armed The	

Electronic Training also available to Canadian Residents

yung fellers are jumping on me. They telling me that they will taking me up on my state

So. I find myself appointed as champeen of the old-time operator. Are having to bild old time amchoor stayshun and then having contest with new amchoor using all the lates geer. Not one to be outdone by a bunch of yung fellers, Scratchi are starting off in high speerits.

First thing I doing is digging deep into junk-pile and unerthing old favorite see-w reseever of mine. Hon, Ed., are you recalling old FB-7 reseever. Man, some of sweetest see-w signals I ever heering coming out of that reseever. I getting it all cleaned up, dusting off plug-in coils, testing toobs to make sure they

good, and putting it together.

The xmitter and antenna are harder. I having to bild them. The rig are copy of one I having long time ago. It are crisstal-controlled, though. Using tipe 53 ossilator and dobbler, with first triode secshun as ossilator. It are driving a tipe 76 newtralized buffer, which are driving pair push-pull 42's, also newtralized. Remembering how we twisting wires together, then snipping them off, a little at a time, to newtralizing? Well, that's how I doing it.

Hole rig are mounted on piece of wood, with cathode meter and key jack and all tooning condensers mounted on little brackets. After spending one hole evening tooning it up, it putting out reel slicky signal.

For antenna I deciding to using a Zepp. In case you not remembering it, Hon. Ed., you just have to looking it up in book. Only trubble having are finding six-inch long insulators, but finally making them from wood and boiling them in parrafeen. That weekend I getting shorting bar on feeder and tapping above it with a-c line, which bringing into shack and cuppling to link on final coil. Seeming to load up hunky-dunky.

Contest are starting next day, on Munday, from 7 p.m. until midnites every nite for a week. First nite I doing pretty good, and not paying much attenshun to other fellow I working aganst. I using cupple diffrunt crisstals, and moving around band, working peeples in one spot, and then another. After working one spot awhile, howsumever, I finding that can't working amchoors more than few kay-

cees away from that spot.

It are middle of next nite I reelizing that the jig are up. It are when I heering the yung feller with his sooper-dooper VFO moving up and down band, working stayshuns like crazy. It weren't that he were particqyoularly a good operator. It were just that he could putting signal where other amchoor was listening. When I getting chance I braking in on him and telling him he can stop using up the am-

[continued on page 127]


1956

## PLYTUBULAR BEAMS

THE GREATEST ADVANCE IN ROTARY BEAM DESIGN OF THE PAST 20 YEARS

PLYTUBULAR CONSTRUCTION is a process developed by TENNALAB where by close tolerance 61ST aluminum tubing of telescoping sizes are fabricated together note booms and elements having multi-ply walls for greater strength, less vibration and smaller size.

- GREATER STRENGTH
- LESS WEIGHT
- LESS VIBRATION
- D LESS ICE LOADING
- LESS WIND DRAG D UNITY MATCH (72 or 52 OHM)
- HIGH GAIN
- HIGH FRONT TO BACK
- SHARP PATTERN



#### PRICES, WEIGHTS, BOOM LENGTHS

Full Size
Beams
for
Full Size
Signals!

*(Other Specings Custom Built)			
SINGLE BAND— With One No. 20G Reactance Tuned Coax Gamma Boom* Length	Actual Weight Lbs.	Shipping Weight Lbs.	AMATEUR NET
No. 2L-20RG-2 Element 14 megacycle beam	27	38	\$ 67.50
No. 3L-6RG -3 Element 50 megacycle beam		17	37.50
No. 3L-10RG-3 Element 28 megacycle beam	18	22	55.00
No. 3L-15RG-3 Element 21 megacycle beam	- 24	35	65.00
No. 3L-20RG-3 Element 14 megacycle beam	43	55	107.50
No. 5L-6RG -5 Element 50 megacycle beam 8'-634	17	23	65.00
No. 5L-10RG-5 Element 28 megacycle beam	29	40	107.50
No. 5L-15RG-5 Element 21 megacycle beam		58	157.50
No. 5L-20RG-5 Element 14 megacycle beam	82	100	225.00
TWO BAND—Interlaced On One Boom With Two No. 20G Reactance Tuned Coax Gammas			
No. 6L-1015RG-6 Element Beam-3/28 mc - 3/21 mc11'-51/2"	34	50	105.00
No. 6L-1090RG-6 Element Beam-3/28 mc - 3/14 mc17'-1/2"	54	72	157.50
No. 6L-1520RG-6 Element Beam-3/21 mc - 3/14 mc - 17,-1/2"	57	75	165 00
THREE BAND—Interlaced On One Boom With Three No. 20G Reactance Tuned Coax Gammas	40		
No. 9L-101520RG-9 Element Beam 3/28 mc - 3/21 mc - 3/14 mc _ 17'-1/2"	67	86	217.50
No 20G—Reactance Tuned Coax Gamma With Insulator and Universal Element Clamp	2	4	14.95
(Specify Band as No. 20G-14, No. 20G-21, No. 20G-28 or No.	20G-50)		

#### PLYTUBULAR BEAMS ARE ALSO AVAILABLE FOR COMMUNITY SYSTEM TV AND OTHER COMMUNICATION SERVICES

AIN—F/B—PATTERN—When properly installed results as shown alow may be expected at the average installation varying slightly with eight above ground, surrounding objects, etc.:

F/B 15 db PATTERN ELEMENTS GAIN 5 db 8 db 24 db 28 db 12 db

nterlaced models for 2-band and 3-band operation will differ slightly om these figures but interaction will be less than if separate beams ere installed on separate towers on an average city lot.

IBRATION—More beams are weakened by vibration than from any other cause. The dampening effect of PLYTUBULAR CONRUCTION reduces vibration and the resultant crystallization to a

inimum

MR—ALL TYPE RG TENNALAB PLYTUBULAR BEAMS are uipped with the No. 20G Reactance Tuned Gamma for unity matcheg of coax line to powers up to 1 kw phone.—See above if No. 20G is sired separately for your present beam. Tuner is sealed in cast uminum weatherproof case, complete with insulator and universal mma to element clamp. Either \$5 ohm or 72 ohm coax may be ed but 72 ohm line is recommended.

UNING—No element tuning is required. The half wave elements le factory tuned for operation over the entire band. PLYTUBULAR EAMS are finished products. Just set the match, adjust the react-ace tuner and QSO!

#### TENNAKITS

COMPLETE WITH T/GAMMA FOR 300, 72 or 52 OHM MATCH

Although TENNALAB'S principal function is the building of com-plete antennas of the very highest quality, we also desire to be of service to the amateur who desires to build his own beam.

In capable hands a TENNAKIT can be finished into a fine Standard quality beam excelled only by TENNALAB'S PLYTUBULAR CONSTRUCTION.

TENNAKITS are complete with aluminum castings, bolts, nuts, insulator, etc. No cutting - - - just telescope to length, drill, fasten and assemble.

		NET
	2 Meter	
	2 Meter	
	6 Meter	
	6 Meter	
	10 Meter	
	10 Meter	
	15 Meter	
	15 Meter	
	20 Meter	
No. 320 3 Element	20 Meter	74.50

.058 61ST6 telescoping tubing 1 1/4" to 1/2"-in stock, prices upon request.

A COMPLETE LINE OF VERTICAL'S READY SOON!

SEE YOUR DISTRIBUTOR OR WRITE

## **TENNALAB - QUINCY, ILLINOIS**

## ... de W2NSD

NEVER SAY DIE

#### July Behemoth CQ

Since July is normally a rather slack month, what better time to put out a monster December issue of CQ? While this whim may in some degree stem from a natural tendency to grab people by the short hair whenever they are at a disadvantage, it also will get me out from under quite a load of manuscripts that are backing up for publication. You've had your warning, at any rate. Get that soldering iron in hand and open up the parts box for you have only thirty days left to get prepared for the massive jumbo behemoth gigantic 128-page July CQ (wow!)

#### Slave Laborers Needed

Hardly a week goes by that some sort of project doesn't raise its ugly head and require the services of a development engineer. If there happen to be any experienced hams reading this obscure paragraph, and they




John Fulmer, W4HAV, corners Bill Halligan, W9AC, during the Dayton SSB Dinner.

happen to live within walking distance of New York I might be able to steer a few rasbuckniks their way plus all sorts of fame and recognition (A reference to your latest article in *CQ* makes a terrific conversational opening). We have all sorts of dirty work available, from the testing of new products to the construction of absurd gadgets. Who will be the first to run tests on the new Heath do-it-yourself Electric Chair kit?

#### The Dayton Hamvention

Hamfest managers and convention planners had best drop everything and get in touch with the Dayton group. The yearly gathering in this Ohio town of about 300,000 pop. runs to about 2000, making it one of the biggest



Walt, W8ZCV, with his ten and twenty meter rotary beams.

conventions in the country hamwise.

Doings started Friday afternoon with arrival of *CQ's* first line shock troops, J and myself, to spellbound weakwilled countboys into long-term subscriptions to *CQ*. J as the last stages of starvation were weakening sales pitch the SSB Dinner set in. To natural ringing in my ears demodulates tupper sideband just fine so I was able to tawith a few of the twenty-meter gang. Seatifor the dinner was apparently arranged with the important people in the middle, the wind known further out, and the rest of us in the fringe area.

Most everything happened on Saturda There were technical talks, hidden transmitthunts, demonstrations of new equipment, a prizes (neither Jim nor I won any prize thereby maintaining our excellent past recoin this matter). The *Drake* six-meter filter gets.



W2NSD high pressuring for subscriptions.



A Big Signal

## The Easy Way...

Eimac 4-125A Radial Beam Power Tetrode TYPICAL OPERATING CONDITIONS

CW AM SSB
'late Voltage 2500v 2500v 3000v
'riving Power 3.8w 3.3w 0w
'ower Input 500w 380w 315w

It takes a big signal to get out consistently. At 500 watts CW, an Eimac 4-125A handles the kind of power required to stay in there when the going gets rough.

No need for special or tricky circuits. If you prefer a transmitter stripped of ornaments, an oscillator will drive an Eimac 4-125A in one of the easiest and simplest amplifiers that can be built. And, your Eimac 4-125A will reward you with more watt-hours per dollar — year after year.

If you're having trouble cutting through the big signals, there's only one thing to do — don't fight 'em, join 'em. Buy an Eimac 4-125A.

For more information on the 4-125A, see your distributor or write to our Amateurs' Service Bureau.

Be sure to visit the ARRL National Convention at San Francisco, July 6-7-8.



#### EITEL-MCCULLOUGH, INC.

SAN BRUNO, CALIFORNIA
The World's Largest Manufacturer of Transmitting Tubes

me all excited and looks like the answer to our 6M TVI miseries. W4HHK gave an interesting talk and showed slides of some of the fancier VHF antennas around the country. W1FZJ managed to get himself banged up a bit while plowing out his driveway (about ½ mile long) and had to stay home. W1RUD subbed for him and explained what is in the wind as far as moon bounce two-meter work is concerned. Read the VHF column for more on that.

The climax of the meet was the Banquet. Imagine 1000 hams all eating soup at one time! Afterward there were the usual veddy formal speeches, with a sparkling and humorous keynoter by John Reinartz. I get stage fright when I talk to any number over six people so you can imagine how paralyzed I was when I was called upon for a few (please keep it short) words.

On Sunday Jim and I drove down to Waynesville to visit Walt Burdine, W8ZCV, our Novice Editor. When we arrived Six Meters was wide open with stations pouring in from all over the east coast, a really fantastic opening. I've heard and worked a lot of six-meter openings, but I've never heard anything like that before. By the time I got back home to Brooklyn that night there was nothing left but a few locals bragging about all the DX they had worked. Wonder if Six will ever do that again?

#### CO VHF Contest

With high hopes and trepidations I waited our first try at running a VHF contest. Would the fellows support it? Would our new scoring system work out? Would we have good conditions? And a thousand other worries. If only we could have had that six-meter band opening one week later! When the contest finally got started I was surprised and pleased to observe all the heated activity. By the time the contest was over, several of the gang around the New York area had run up remarkable scores, some with over 200 contacts. This was particularly remarkable since band conditions were absolutely terrible. With even a slight band opening we normally hear Hartford and Rhode Island. Not a peep!

The one great saving event was several hours of pretty good aurora. Using this great umbrella I was able to work Maine, Vermont, Massachusetts, Rhode Island (Sam-portable) Maryland, Western New York, Ontario, Ohio, Michigan, and Illinois. Some of the gang with better equipment hooked Wisconsin and Indiana too. This was my first brush with aurora on Two Meters and I found it very exciting. I imagine that a lot of the fellows out in the midwest managed to work more than my 46 counties; we shall see.

[continued on page 127]



## DX-35 phone and cw transmitter

- · Built-in modulator for phone operation.
- Bandswitching on 80, 40, 20, 15, 11 and 10 meters. Pi network output coupling.
- Switch selection of three crystals—provision for external VFO excitation.
- Attractive and functional physical design.

This brand new transmitter model provides phone and CW operation tion on 80, 40, 20, 15, 11, and 10 meters. Plate power input to 6 watts on CW and controlled carrier modulation peaks to 50 watt on phone. Completely bandswitching.

Employs two-stage 12AX7 speech amplifier, 12AU7 modulator 12BY7 oscillator, 12BY7 buffer, and 6146 final. The buffer stage assures plenty of drive to the final on all bands. Pi network outpu coupling employed for easy antenna loading. Switch selection o crystals. Crystals changed without removing transmitter cabiner Husky power transformer and choke are potted, and the circui is well shielded. Meter indicates final grid or plate current.

Truly a remarkable transmitter package for the price. Ideal both for the novice and for the more experienced operator.



## multiplier KIT

Provides extra selectivity for separating signals, or will reject one signal to eliminate heterodyne. Effective Q of 4,000 for sharp "peak" or "null." Tunes any signal within receiver IF. Operates with 450 to 460 kc IF. Will not function with MODEL QF-1 AC-DC type receivers. Requires 6.3 VAC at 300 ma, and 150-250 VDC at 2 ma.



## Small, highly efficient

## MOBILE RECEIVER

-full fledged, 12 tube, all-band, mobile or fixed station



Power Packs Available:

6-12 VDC

12 VDC

110 VAC

\* (includes speaker and "S" meter all in one matching package)

#### KE-93

now delivering 5" High, 6" Wide, 9" Deep

- Field performance fully comparable to big table models.
- 7-band turret, 10 meters thru broadcast.
- New, advanced noise elimination circuits.
- Dual conversion, crystal controlled.
- Pulls in and holds weak stations.
- 3 KC selectivity, under 1 microvolt sensitivity.

## You asked for it . . . here it is:

New MARS frequency coverage on all standard amateur modelsat no additional cost

Band #1 550 -1650 KC

Band #2 1650 -3500 KC

4030 KC Band #3 3500 -

7310 KC Band #4 6990 -

Band #5 13970 - 14360 KC

Band #6 20990 - 21450 KC

Band #7 27950 - 30000 KC

Watch for announcement of our

new matching transmitter - REVO-

**LUTIONARY!!** 

## PIERSON-HOLT ELECTRONICS

2308 West Washington Blvd., Venice, California

Write for literature



## BUD PRODUCTS with EXCLUSIVE FEATURES

When you're selecting equipment or components to give your rig extra utility or flexibility always choose Bud products. Only Bud products have the extra features that insure satisfactory operation and yet they are priced no higher than ordinary products.



CODE PRACTICE **OSCILLATOR** AND MONITOR CPO-128-A **Amateur Net** \$17.25

THE ONLY OSCILLATOR WITH BUILT-IN MONITOR WHERE NO MODIFICA-TION IS NEEDED TO CHANGE FROM OSCILLATOR TO MONITOR AND BACK AGAIN. It has 2 tubes and a built-in 4" dynamic speaker. A volume and pitch control are included. Operates on 110 V AC or DC. Also available in earphone model CPO 130-A at \$15.60.

FREQUENCY CALIBRATOR FCC 90-A **Amateur Net** \$19.20



THE ONLY SELF-POWERED MODEL. Permits accurate checking of transmitter frequency on all bands to 30 mg. Has 100 kc crystal. Uses 2 tubes and plugs into 110 V receptacle. Provided with on-off and standby switch.

> See these and other Bud Products at your Distributors



## BUD RADIO, Inc.

Dept. C

2118 East 55th St.

Cleveland 3, Ohio

## Letters . . to the editor

#### Novice Q'5er

Sirs:

 $_{
m My}^{
m SIRS}$ : My introduction to CQ Magazine was through that ticle on building a Q'5er, by Donald L. Stoner, i your January issue.

This type of article I want—so here's a subscription

for 2 years.

The Q'5er article contained an error\* which cause The Q'ser article contained an error\* which cause me to do some studying and inquiring before I wound uy with a really fine receiver. This is good for me becaus I learned more about radio from this one thing that from any other activity so far. This Q'ser is ever better than you claim!!

Now if I can overcome the stage fright whenever someone answers my CQ I'll have it made, hi.

A Green New Ham M. C. Robinson

\*March '56, p. 36.

Dear Ed:

Dear Ed:
I recently completed the Novice Q5'er (CQ January 1956) and would like to pass along an idea that may help others interested in this converter.
As this xtal converter was described by W6TNS an RF stage and a Mixer were fed into a BC-453 to make a very stable receiver for 80 and 40 Meters. Separate crystals were used for each band. I discovered that by using an active 3500-kc crystal that I could cover the phone portions of not only 80 and 40 but 20 Meters awell. To accomplish this the RF and Mixer coils were hand wound and grid dipped so that 20 Meters tuned at minimum capacity of the variable condenser. 40 Meters will be found at about half capacity and 80 Meters at approximately full capacity. The coils used here were wound on ½" forms of old IF transformers and comprised 20 turns of 26 wire. The crystal evidently doubles to 7000 kc for 40 Meters and quadruples to 14000 kc for 20 Meters. 20 Meters.

The frequencies covered by my conversion are as fol-

3500 plus 190— 3690 kc plus 550— 4050 kc } for 80 3500 3500 x 2 plus 190— 7190 kc } for 40 7000  $3500 \times 4$ 14000 plus 190—14190 kc for 20 14000

As you can see I am interested in only the phone bands. An antenna condenser of 100  $\mu\mu{\rm fd}$  (Variable) was connected in series with the grounded end of the antenna

Thus we have a 3-band receiver without a band switch Thus we have a 3-band receiver without a band switch and with stability that will enable single-sideband reception on even the 20-meter band. In the conversion here, AVC, Audio control and RF controls were added to the BC-453. Not only is this a fine receiving set up for the fixed station but an excellent receiver for mobile use,

Fred Nazar, W8RNA

14424 Camden, Detroit 13, Mich.

#### Separate Power-Supply Fusing

Dear Mr. Green:

This is being sent in the desire to help others avoid the troubles encountered in regard to the following experience.

experience. This information particularly should be a real service to the thousands of owners of Viking I, II and DX-100's. The transmitter of a friend of mine and my own went up in smoke within six days of each other. Although both were different makes they met their demise though, strangely enough, through the same chain of circumstances. A fore-warning can save others of a similar fate. Believe me, that seeing your favorite piece of gear go up in smoke is no fun. Briefly, here is the reason for the trouble and a simple and inexpensive way of preventing it.

way of preventing it.

Both transmitters are adequately fused during the actual time on the air, however, during standby periods,

[continued on page 16]

# Introducing another NEW Viking transmitter the ... "Valiant"

landswitching 160 through 10 neters...275 watts input CW and SSB\*...200 watts AM!


with auxiliary SSB exciter

ERE'S EXCITING NEWS! Another new Viking ... the Valiant." This compact transmitter gives you outstanding flexibility and performance ... power to punch arough terrific QRM! The "Valiant" may be operated y built-in VFO or crystal control ... VFO is temperture compensated and extremely stable — operates in the 1.75 to 2.0 mc and 7.0 to 7.45 mc ranges.

High efficiency pi-network tank circuit matches anenna loads from 50 to 600 ohms... tunes out large mounts of reactance — final tank coil is silver plated. Therefeatures: complete TVI suppression; timed sevence (grid block) keying; high gain push-to-talk udio system; low level audio clipping; built-in low ass audio filter; self-contained power supplies and ngle control mode switching.

As an exciter, the "Valiant" will drive any of the opular kilowatt level tubes and will provide a high uality speech driver system for high power modulators. A nine pin receptacle on the rear of the transmitter permits the "Valiant" to be used as a filament and plate power source, and also as a modulator for uxiliary equipment such as a VHF transmitter.

he Viking "Valiant" is available completely wired nd tested or as an easy-to-assemble kit. Cabinet is finished in attractive maroon and grey with green omenclature. Complete kit includes assembly instructions, tubes and all necessary hardware. Dimensions: 15" x 21%" x 17%". Shipping weight: 83 lbs.



Cat. No. 240-104 — Viking "Valiant" Kit with tubes, less crystals, key and microphone.

\$34950 Amateur Net

Cat. No. 240-104-2 — Viking "Valiant" wired and tested with tubes, less crystals, key and microphone. \$439.50 Amateur Net



### E.F. Johnson Company


2929 SECOND AVENUE SOUTHWEST . WASECA, MINNESOTA

Capacitors • Inductors • Knobs • Dials • Sockets • Insulators • Plugs • Jacks • Pilot Lights

## See your distributor

Johnson Amateur Equipment is sold only through Authorized Johnson Distributors—most offer convenient time payment plans. For complete information see your distributor.





for TEN

MOSLEY Super Ten

Rotary Beam

HIGH GAIN! LOW COST!

Here's a 3 element 10 meter beam with design features that assure Top Performance-consistent DX Results!

The all new Mosley "Super Ten" has full length parasitic reflector and director elements teamed with a driven element shortened to permit use of loading coil and link which provides a perfect match to 52 ohm coax line and an exceptionally efficient and convenient coupling.

The "Super Ten" is built to the same high standards of quality that have made Mosley Rotary Beams the choice of Hams around the world . . . yet priced so low every Ham can now enjoy the thrill of Beam Operation!

Performance Data and Specifications



• 20 db. front-to-back • 1.2/1 SWR at resonant freq. • 17'3" max. el. length • 8'4" boom

• Wt., 20 lbs. • Pre-tuned

Model S-103. Super Ten Beam, with hardware & instructions, Less mast & rotor.

\$39,50 Amateur Net

ORDER FROM YOUR HAM SUPPLIER

OSIEY Electronics, Inc.

8622 ST. CHARLES ROCK ROAD, ST. LOUIS 14, MISSOURF

which ordinarily run many times greater than on-the-air times, you will find that they are still a tected by the same fuse while drawing 150 watts when fully loaded on phone and drawing up to 500 watts!!! This can sure lead to some very me

work.

The usual chain of events consists of a low voltisupply input filter condenser developing enough leaks
to overload the 5V4 rectifier to the point of short,
and thus placing a real overload on the low voltage #
filament supply transformer. Once the rectifier sho
only a few seconds are necessary to really cook
transformer. Three of us were in the shack at the til
and all power was removed within seconds after a few and all power was removed within seconds. only a few seconds are necessary to feath, cook transformer. Three of us were in the shack at the ti and all power was removed within seconds after a factor of burning varnish was noticed. Although power transformer was checked and no apparent ow heating considered existent, less than ten minutes lathe transformer was again checked and found too to handle. In the meantime varnish had boiled through the wiring harness, tube sockets, etc., exthough no more power had been on it.

Get busy before it is too late and install a suita fusing system. It will be considerably more economit than replacing a fairly expensive power transform 5V4 rectifier tube, filter condenser and then puttin the new system of fusing. A 2-amp fuse shotake care of the low voltage and filament supply, a 3-am for the high voltage supply. Look over the diagra-

for the high voltage supply. Look over the diagrafor your transmitter and check the method of fusi the primaries of these two transformers. situation before it is too late. Correct

George S. Woods, W2SW Rome, New Yc

This is the first report we have had of this trout and our experience with the Viking and the DX-indicate that both use components of high quality the circuits mentioned. This idea of separate fuse for power supply circuits is a good one, and the vestment in an extra fuse and a few minutes' wo is cheap enough insurance against the sorrowful currence above described.

#### **Visual Comparison Wattmeter**

Dear Mr. Green:

I am writing to you to offer a few comments an article which appeared in the January issure CQ; French, A Visual Comparison Wattmeter, page 4

1) The possible accuracy of the balance of the two light-bulb-luminosities may be increased by means simple comparison devices known as photo-meters—to Count Rumford, Bunsen, and Lummer-Brodhun phot meters being described in most Sophomore Colleg Physics books. (Perkins, College Physics, Prentice-Ha contains a discussion of the theory of operation these devices). All that is needed for the Bunsamethod is a piece of thick paper with a grease spat the center and two pieces of mirror placed in a "V to one side of the paper so as to enable the viewir Dear Mr. Green: at the center and two pieces of mirror placed in a "Vito one side of the paper so as to enable the viewir of both sides of the paper without obstructing the light. If the paper is placed at the midpoint between the two lamps—the lamps being set up as in the Frencarticle—and the two lamps are operating at identical conditions are operating under otherwise identical conditions then, the brightness will be the same on both sides of the paper as seen in the mirror reflections.

2) The "visual comparison method" is of little valuation was found to be as much as 30% in error at 100 Mcc and at higher frequencies a sort of gas discharge was observed to take place within the bulb. At 1,000 Mcs for example, it is possible to burn out a 500-watt bul with as little as 100 watts of R. F. power—due, apparently, to the occurrence of "hot-spots" on the bul filament.

Richard F. Burns, W9OBU/W9NV Beloit Research and Development Compan Beloit, Wisconsin

#### Poof! Poly Tubing

Dear W2 Not So Dumb:

Dear w2 Not So Dump:

Mighty nice magazine you are turning out these days son. Keep it up! I like your style!

Here's a little wee nugget of thrift for the build-it-yourself clan—if you ever have need for 4½" of polyethelene insulating tubing about 3/16" in diameter just take a hacksaw and cut open a discarded spraynet or deodorizing container and there it is—for free! I knew there must be something worthwhile inside those cans!

Harry H. Heinrich, W9KPG

#### That February Cover

Dear Wayne:

I receive my CQ a bit later than some people, of course —boat mail, you know—but I cannot resist enquiring how many other subscribers opened their February copy, muttered something profane about careless wrapping, and scratched at the edge of the "torn" cover to see what was underneath?
73 from the land of coffee, bananas and "senoritas

bonitas.

Ted, TI2BX San Jose, Costa Rica

#### Sam's Identity Revealed

Dear Ed:

Your F. S. Harris was introduced some months ago by picture of a beavered character, together with a more a picture of a beavered character, together with a more benign and harmless looking one—with no caption as to which was which. And so for months I had to worry about what this man Harris looked like. Woke me up in the middle of the night, sometimes. All I know yet is that he writes real purty. And finally I have got him tagged as W1HOY's husband, and that's good enough identity for me.

Glad to hear you dropped in to see how KV4AA pushes traffic. Always nice to have a phone man see what a REAL operator can do.

Fred C. Hall, W1MZE SS Archers Hope, KCQG Off Cape Hatteras

#### V V V

Gentlemen:

Gentlemen:

We enjoy CQ very much. My husband and I are both novices, KN6PXB and KN6QCS.

We are wondering if a precautionary word could be said regarding those people who, in order to obtain the air, resort to test, V V V or hold their thumbs on the key for 20 to 25 minutes at a stretch. This is done without identification. There seems to be a great deal of this going on in our area and it is very wearying particularly when you have Hawaii or Alaska or the Virgin Islands and cannot complete the call. Thank you.

Mr. & Mrs. Mahurin

Long Reach, Calif.

Long Beach, Calif.

#### Code Signal Source

Dear Sir:

Wanting to get some code practice for myself and my oldest son, I found I had no tubes on hand to make an oscillator (battery type) so I hit on the idea of using my Heath Signal Generator as a signal source, the modulation being about 400 cycles. I hooked a pair of phones, key and plug in series and then plugged into the output for AF and found that it worked quite satisfactorily. Also found that by converting this satisfactorily. Also found that by connecting this arrangement into my signal tracer it will give a much louder signal, amplified by the tracer so as to use the speaker.

George B. Martin, W2JHL Campbell Hall, N. Y.

#### **How Many Ham Ministers?**

Dear Sirs:

I have talked to three other hams who are ministers. I would like to know just how many ministers in the U.S. are hams. Could you ask all ministers who are hams to notify your magazine? This would be of great interest

I would like to tell you just how much CQ has meant to me since taking up our great hobby. I anxiously await its arrival each month and get much pleasure and help from all the articles.

Since getting on the air in December I have had over 250 QSOs on 40 Meters, using only one crystal. To date I have worked 32 states.

Thanks again for your wonderful contribution to our

James M. Demott, KN5DED Chaplain, USAF

#### Missouri Hamfest

At Sedalia, Mo., June the 10th, the Central Missouri ARC sponsors a real midwest style hamfest at the Missouri State Fair Grounds. Admission \$1. Basket lunch, free hot coffee and cold soft drinks. Swap Shop, drawings for OM's, XYL's, YL's. Write Mrs. Jessie M. Goist, WØNUY, 108 W. 5th St., Sedalia, Missouri.



for 15&20 meter 3x

Here's the 2-Band 'V-P' Beam You Asked For!

The VPA 1520

Want to work 15 and 20? The new MOSLEY Model VPA-1520 is just the Rotary Beam for that job!

Two 3 element beams, mounted on one boom and fed with just one coax line, give you True Beam Performance on both bands . . . and to change beams, you just change bands-at the transmitter!


Here's a space saver and a money saver . . . but don't let the low cost and compact size fool you. There's performance aplenty in the Proven MOSLEY "Vest Pocket" Design!

#### SPECIFICATIONS and DATA

- Forward Gain, 71/2db. (each band)
- F/B, 20db., or better.
- SWR, 1.2/1, or better, at resonant freq.
- PRETUNED: to 14, 14.1, 14.2, 21, 21.2 & 21.3 Mcs.
- Boom, 12' long, 11/2" OD 61ST6 Alum.
- Elements, 61ST6 Alum. Max. Lath. 221/2.
- Weight, 58 lbs., assembled,
- Wind Surface Area, 11.9 sq. ft.
- Wind Load, 238 lbs.

Model VPA-1520, with coils, hardware and instructions. Ham Net, \$129.90

ATTENTION VPA20-3 OWNERS! Convert to a VPA-1520 with Conversion Kit. Model VPA 20-1520 Amateur Net \$63.54



8622 ST. CHARLES ROCK ROAD, ST. LOUIS 14, MISSOURI







G-77
MOBILE
TRANSMITTER

G-66 MOBILE RECEIVER

Gonset's new Mobile Twins, G-66 Receiver and G-77 transmitter, represent the perfect mobile combination. Outstanding multi-band performance—beauty of appearance—finger-tip control—6 and 12 volt operation—compactness without compromise! Typical Gonset dollar-for-dollar value—real "owner satisfaction".

#### G-66 RECEIVER



6 BANDS: 540-2000 kcs. 3500-4000 kcs. 7000-7300 kcs. 14,000,14,350 kcs. 21,000-21,450 kcs. 28,000-29,700 kcs.

AM, CW, SSB RECEPTION. Highly stabilized HF and BF oscillators and xtl controlled 2nd conversion oscillator.

STEEP SKIRT SELECTIVITY: 265 kc 2nd 1.F. 8 high Q tuned circuits, 3.5 kc 1.F. bandwidth at 6 db down.

DOUBLE CONVERSION ALL BANDS: 2050 kc ist 1.F. Double input tuning (3 tuned circuits) on high bands for high image rejection.

AVC—Noise limiter—Panel S meter—antenna trimmer—BFO pitch—Audio-RF gain control—slide rule dial—3 watts audio.

G66 RECEIVER...(less power supply).......(#3046).....net 169.50
"3 way" (6V-12V-115V AC) Universal power supply/speaker..net 39.95

#### G-77 TRANSMITTER




FREQUENCY RANGE: 80-40-20-15-10 meters. VFO or xtal, switchable. Highly stable VFO, each band spread over most of slide rule dial.

FULL BANDSWITCHING: Exciter ganged with VFO, pi network output.

POWER INPUT: 50-60 watts, modulated. CW provisions, 6146 tube in output. New modulator has integral speech clipping. High gain speech for PA-type dynamic, reluctance,ceramic or xtl mikes.

POWER SUPPLY: Heavy-duty, vibrator, 6 and 12V DC. Output voltage 500-600V full load, Selenium rectifier, low drain both on standby and transmit. Power supply is a separate compact unit.

GONSET CO. BOI-SOUTH MAIN STREET, BURBANK, CALIF.



## Using a TV Antenna for Six Meters

Pete Maloney, K6HBY 1427 Guadalajara Place Claremont, California

When Six opened for Technician operation and activity started perking up I decided to get in there too. The age old argument of horizontal vs vertical came out vertical for me when I considered that my main interests were local rag chewing and working mobiles.

The next point was to get that vertical up there with a minimum of expense. It sounded like too much work to start with the raw materials and make the whole thing. Besides that, a completely finished TV antenna doesn't cost much more than the same amount of aluminum bought retail. The TV conical antennas cost less than \$5.00 and can be simply worked into a fine six meter vertical.

My method is to use the TV boom for the radiator and use the TV reflectors for a ground plane. This means that you will have to extend the boom a bit and make it about 55" long to resonate low in the six meter band. This can be done by fitting a 24" to 30" piece of tubing on the end of the boom to extend it after sawing off the reflector end of the boom. The extension can be the same size as the boom if a short smaller piece is used inside to make a rigid and conductive joint. A smaller or larger piece of tubing could also be used, but keep in mind that good electrical contact is important. I used a 12" tube inside and bolted the works together with eight screws.

The ground plane radial elements are the TV reflectors (the longer tubing) and are fastened in the insulator in the normal way. A piece of braid (from coax cable) is used to bond the four radials together. This will connect to the braid on the coax from the transmitter.

A hole is drilled in the insulator so the coax center conductor can pass through and connect to the end of the boom.

A mounting bracket can be made from a piece of steel bent to fasten to the bolts holding the radials and arranged to clamp to the mast with "U" bolts. Do it any way you want, but leave the boom alone.

#### Tuning

A small loop of wire between the radials and the driven element will enable you to couple in a grid dip meter. You can then adjust the length of the driven element to the frequency you desire. The loading of this antenna is quite broad due to the large diameter of the driven element. Remove the wire loop and connect the RG-8/U to the shack.

This ground plane will give you a good signal report all over town and the whole thing costs less than five dollars. See you on Six?

38 Toppa Blvd., Newport, R. I.

a few field-tested emergency-power schemes well worth perusing: on noise reduction, using motors as generators, methods of regulation-

#### for Outdoorsmen:

## for Emergencies:

## **A-C** Generators

With the approach of another summer season, the thoughts of many hams turn to outdoor operation of their rigs, encompassing among other incentives the annual Field Day contest and the hurricane season (Heaven forbid that we will need to operate under such conditions again, but we must always be

prepared).

Operation under these conditions involves one common denominator about which much is taken for granted—the small, electric power generator in any of several forms, as an independent source of power. This is not intended to be a college-level lecture in the mysteries of electric machinery, but rather an explanation of a few fundamentals of generator operation plus some practical suggestions for improved or novel generating schemes, utilizing these fundamentals.

#### Eminently Useful Data

First, let's stow just a small portion of elementary theory under our belts so that we may share a few common terms. We all know that an electric current is generated whenever a magnetic field "cuts" a conductor, or vice versa. This means that if a simple straight wire is placed in the field between the poles of a simple horseshoe magnet, then moved rapidly out of the field, a feeble electric current will be generated in the wire. Here we have the rudiments of an electric generator.

#### Generators Basically A-C

All we need do to make a practical producer of usable power is to rearrange both the magnetic element and the conductor for maximum efficiency and connect the beast to a gasoline engine, or, to use the general term, a prime

It should be noted that the simplest gel erator is a loop of wire rotating within a ma netic field, producing an alternating currel output. It is necessary to provide a means f connecting the two ends of our movable willoop to the "load." In smaller machines, sa 10,000 watts or less in capacity, the magne or field is generally fixed, while the wire looor armature is rotated within it, the rotating member being fitted with slip rings, each which is connected to one end of the windin and upon which ride stationary brushes collect the current.

#### **D-C-ing Schemes**

Now, to produce a d-c, or direct-current output, we must rectify the a.c. This can b done with selenium or vacuum-tube rectifier or as is commonly done, by the use of the commutator, which is nothing but a mechani cal rectifier. Here is a fundamental princip to bear in mind: except for one notable case the current generated within the armature of all ordinary generators is a.c. If the machin is a d-c machine, the commutator mechanical rectifies this generated a.c. and the output a the machine terminals is d.c. A more detaile: discussion of electrical machinery may b found in an electrical handbook, or in an standard electrical engineering textbook.

#### **Practical A-C Machines**

Since most of our radio equipment is aoperated, any operation of equipment designed for other than mobile use presupposes a suit able supply of 115-volt, 60-cycle a.c. For Field Day and emergency operation, this "house current" is usually obtained from gasoling

<sup>1.</sup> The homopolar, or unipolar, d-c generator actuall generates true d.c. internally.

ngine-driven generators in various sizes up o about 10 kw. These generators are almost without exception of the tapped d-c armature

ariety.

Recall that the current generated within the rmature of all ordinary generators is a.c. All ve have to do is get this a.c. out of the armature without rectifying it, and we are in business. Thus, the tapped d-c armature generator





Fig. 1a.

s simply an ordinary d-c generator, complete vith shunt field coils and an armature with commutator, plus two slip-rings for picking off the a-c power. Brushes are provided to ride on the commutator to provide d.c. to excite the field coils, and another set of brushes rides the blip rings to collect the a.c. for delivery to the shoad. These slip rings are simply connected to the total two directly opposite commutator segments. Figure 1-a illustrates this construction of three slip rings were provided, connected to commutator segments 120° apart, three-phase h.c. would be the resulting output.

#### Drawbacks

These machines perform very well, with hese exceptions: They do not produce a very pure sine wave of voltage (inconsequential in nost applications). But they are usually profific r-f noise generators, to which any Field Day advocate will readily attest! Most of the noise is generated by the brushes riding across he many make-and-break contacts on the commutator, and it covers the majority of the r-f spectrum. It happens that very little noise is produced by the other brushes riding on the notest slip rings (continuous contact). But the



noise produced at the commutator is passed on the load through the slip rings, and though his noise responds to treatment, such as the use of *Hypass* coaxial capacitors, it is usually lifficult or impossible to eliminate or even to reduce to negligible proportions.

#### Removing Commutator Noise

One obvious means of eliminating this noise is simply to lift the brushes off the commutator and discard them, thus eliminating the source of the noise. If the shunt field, now without excitation, is disconnected from the unused brush holders and reconnected to a suitable selenium rectifier, as shown in Fig. 1-b, it will be found that the generator will satisfactorily excite itself from the a-c or slip-ring terminals, and the electrical noise problem will be nearly licked. We still have the problem of ignition noise in the gasoline engine, but judicious use of shielding is usually successful here.

Thus all we have done is to substitute a selenium rectifier for our efficient but noisy mechanical rectifier, the commutator. A full-wave or bridge rectifier should be used, as the half-wave arrangement will not give sufficient excitation. The selenium rectifier rating may be computed using Ohm's law: Measure the resistance of the generator shunt field with the commutator brushes lifted. Divide this into 120, which is the assumed field voltage rating,




Fig. 2. Bridge rectified generator with current transformer.

and this gives the normal, full-load current rating of the field. Noting that the r-m-s voltage being handled will not exceed 135 volts, and that in a bridge rectifier, each rectifier handles half the load current, selenium rectifiers with ratings in the range of 135 volts at 500 milliamperes will probably be found to suffice.

#### **Voltage Control**

The addition of the capacitor and rheostat as shown will provide a wide range of voltage adjustment. Like any self-excited, shunt-wound machine, this type of generator, whether excited from brushes and commutator or from external rectifiers, will have a drooping voltage characteristic. That is, as the load increases, the terminal voltage will gradually drop, so that with changing load, adjustments must be made in the field rheostat setting to maintain near-constant voltage at the terminals.

#### "Compounding"

As a d-c generator may be "compounded" to give it a flat voltage characteristic, so may this type of a-c generator be compounded. If a current transformer is inserted with its primary in series with the load and its secondary in series with the a.c. to the field rectifier leads, the effects of compounding are realized. Note that as the load increases, so does the secondary voltage of the current transformer, and this secondary voltage adds to the generator



Fig. 3a. "Induction" generator.

terminal voltage to give an increased voltage on the field—just the regulating effect we needed to counteract our voltage drop. If the voltage drops severely with the addition of the current transformer, simply reverse the leads to either the secondary winding or the primary (not both).

#### The Current Transformer

Current transformers are relatively unavailable in the average ham junk box, but a very satisfactory one may be built from materials at hand. A stack of transformer laminations must be available. A large, burned-out receiver type power transformer with an original high voltage winding of perhaps 360-0-360 volts at 120 milliamperes will yield a laminated stack or core of large enough dimensions for our purposes.

Generally the easiest way to disassemble such a transformer is to grasp one of the outer laminations with long nose pliers and firmly pull it out of the winding. Then, if the additional laminations are carefully separated with




Fig. 3b. -with "ufd amplifier"

a knife, they may be removed one at a time. Take care to note the way in which they are stacked, as we should duplicate this arrangement when we restack the core in our current transformer.

Now the cross-sectional area of the core is measured by measuring the dimensions of the open space in the center of the winding left by removal of the iron. A winding form of the same size as this is made by folding a layer of cardboard, or heavy paper to the dimension of this inner "window." This form is coate with a couple of coats of shellac to give a stiffness.

Now we are ready to wind the current transformer, and for lack of more specific windin instructions, we will find that about 15 turn will be adequate for the primary. This wir should be large enough to carry safely the ful rated current of our generator as stamped on the nameplate. The usual rule of thumb is to allow about 1,000 circular mils of wire for each ampere of current. If our generator is 1-kw. unit rated at about 9 amperes, we should wind the primary of our current transformer with wire of at least 9,000 circular mils cross section, or 10-gage B & S wire size, which has a cross section of 10,380 circular mils. The extra size will give a slight factor of safety Regular magnet wire, coated with ename (Formvar or Formex) should be used, and the winding should be wound directly on the cardboard form.

Over this simple primary winding the secondary is wound directly. It should have 10 times as many turns. For flexibility of final




Fig. 3c. -alternate method.

adjustment, we may tap it at 100, 110, 120, 130, and 140 turns, but this is not mandatory. Use of wire smaller than number 18 B & S gage should be avoided, as it will introduce too much resistance in the field circuit. Within the limitations imposed by the core window area, we should use the largest wire size feasible.

After the windings have been secured on the cardboard form with a bit of strong twine, the entire winding may be dipped in shellac and hung up to dry. Actually, commercial practice is to dip such winding in electrical baking varnish and then to bake the winding until the varnish dries. However, the shellac treatment will work quite satisfactorily. When the winding is dry, we carefully reinsert the laminations, bring out the leads and replace the transformer case. The leads are connected as shown in Fig. 2. Caution: Do not leave the primary of the current transformer connected in series with the load without leaving the secondary connected to some sort of load, or else short-circuited.

If for any reason the secondary is to be disconnected from the remainder of the field cir-

cuit, the primary should first either be disconnected or shorted out. If the primary terminals are not shorted, the secondary terminals should be shorted. If the secondary is ever entirely disconnected, the voltage can, under certain conditions, rise to a maximum value of about 10 times generator terminal voltage, or about 1,200 volts. That this could be dangerous is obvious, particularly when we consider that the 1,200 volts would appear where least expected. Actually the current transformer is quite safe to use . . . just obey the cardinal rule: Either have some definite, closed circuit connected across its secondary, or short-circuit the secondary. A shorting switch across the secondary provides a convenient means for accomplishing this. Short-circuiting it won't hurt it at all because its primary is in series with the load, and not tied across the line.

#### The "Sears & Roebuck" Special

Next we come to an interesting little generator which can be used to advantage for powering ham gear, lights, and other loads which do not draw current at a lagging power factor. Many of us have heard that any electric motor becomes a generator if driven by a prime mover, but few of us ever thought of the handy little half-horsepower induction motor down in the cellar driving the local bench saw for the "do-it-yourself" contingent of the family.

Just as the synchronous a-c generator (by far the most common variety—this includes our tapped d-c armature type) is excited by means of a d-c electromagnetic field, the induction generator is excited by capacitors. Figure 3-a illustrates the utter simplicity of the basic circuit. If a capacitor of sufficient size is connected directly to the terminals of the plain, garden variety squirrel-cage induction motor, and the motor shaft turned by an engine at a few r.p.m. faster than the name-plate rating, it will generate a.c. that is of the finest sinusoidal waveshape, utterly devoid of electrical noise, since there are no sliding brushes of any kind.

#### No Motors, Please

There are, of course, drawbacks to this system which are serious but not insurmountable.

The principal reasons for its lack of popularity are these: It will not run electric motors. The voltage regulation is relatively inflexible. It requires a rather large capacitor for excitation per kw. delivered.

Immediately following the great hurricane of 1954, however, when commercial power was out for several days, the author, for lack of a better generator successfully operated half the lights in the house, the TV set and the large ham station receiver by using a half-horsepower induction motor as a generator,

driven by one rear wheel of the family car. But as soon as an attempt is made to start an electric motor on this system, the generator voltage decreases radically and erratically, and continues in this unsteady state until the motor is disconnected from the system.

This unfortunate characteristic of the simple induction generator limits its popularity. However, it will successfully operate radio equipment and lights, and so should be of immediate interest to the average ham. The problem of the capacitor is not too difficult to solve. Note that since we are handling a.c. we cannot use an electrolytic, or polarized capacitor, but must use a paper or oil-filled, non-polarized type. Experience has shown that for a 120-volt induction generator of ½-horsepower size, about 160  $\mu$ fd is required to cut the mustard. This figure may be up to 30 #fd or so in error either way, depending on the particular motor and the load. This is a rather large capacitor to expect from the average ham junk box, so we will not even consider it.

To solve this dilemma, we can cleverly employ another transformer. First we observe the equation for energy storage in a capacitor: Energy =  $\frac{1}{2}$  C V<sup>2</sup>, or, put another way, for a capacitor of given capacity, the energy storage is proportional to the voltage squared. Thus, if we double the voltage of the induction generator, we can get the same output with a capacitor of  $\frac{1}{4}$  the capacity required at 120 volts, so for 240-volt operation, we require a capacitor of only 40  $\mu$ fd.

Doubling the voltage again to 480, the capacitor required is \(\frac{1}{4}\) of 40 or 10 \(\mu \text{fd}\). This process can be continued as far as we like. Our formula for this particular case works out to be  $K = C V^2$  where K is 1,600,000, C is in μfd and V is in volts. Now suppose we connect a transformer across our generator terminals, and suppose the turns ratio is 4 to 1. If the low-voltage side is then rated at 120 volts and the high side at 480, we can connect a 10 µfd capacitor to the 480 volt side, and the transformer will effect a 16-to-1 impedance transfer to the generator terminals; that is, the generator will "see" the 10 µfd capacitor, through the transformer, as a 160 μfd capacitor at 120 volts, which is what we required in the first place. It all boils down to a matter of what have you.

The author happened to have an old surplus 1-kw. power transformer with a voltage rating of 450 to 115. This was used in conjunction with a 10  $\mu$ fd, 600-volt oil-filled capacitor to excite the half horsepower

[Continued on page 104]

<sup>2.</sup> Theoretical or ideal 60-cycle induction motor speeds are 3600, 1800, 1200, etc. rpm. Actual motor speeds are slightly less, e.g., 3450, 1725, 1150 rpm, etc. The induction generator, on the other hand, must be turned faster than the ideal, e.g., 3750 rpm for a motor of 3450 rpm rating, 1875 rpm for a motor of 1725 rpm rating, etc. This is accounted for by a phenomenon known as "slip."

## The Sunspot Story: Cycle 19

by George Jacobs, W3ASK

607 Beacon Road, Silver Springs, Md. Propagation Editor, CQ

Latest reports of sunspot activity continue to confirm the fact that the present sunspot cycle, cycle 19, is rising at an unprecedented rate. Because of the direct correlation between sunspot activity and ionospheric characteristics, shortwave radio conditions during the next few years may be better than they have ever been in the history of radio.

in the history of radio.

The origin of sunspots, the effects of solar radiation upon the ionosphere, and the trend of the present sunspot cycle have been discussed in Part 1 of this article appearing in the March issue of CQ. In Part 2 of this timely article, W3ASK, CQ's Radio Propagation Editor, discusses the effects of the rapid rise in sunspot activity upon ionospheric propagation conditions in each amateur high frequency band 10 through 160 meters as well as the possibility of once in a lifetime conditions on the 6 meter band. The effects of the rapid rise in sunspot activity upon ionospheric propagation conditions in the VHF spectrum, with the possibility of long distance reception of TV transmissions, and other phenomena believed to be associated with the sunspot cycle are also discussed.

#### PART 2

In the three months that have elapsed since the publication of Part 1 of this article, additional evidence from the Swiss Federal Solar Observatory at Zurich continues to confirm the fact that the present sunspot cycle will be one of outstanding intensity, reaching a maximum higher than any previously observed. Sunspot activity during the past three months has been greater than predicted a short time ago and the latest forecast of the Swiss Observatory is for the maximum of cycle 19 to occur as early as February, 1957, with a record breaking smoothed sunspot number of 170. Figure 1 shows the trend of cycle 19 compared to the previous cycle which reached a maximum smoothed sunspot number of 152 during June, 1947. The previous cycle was the highest recorded since 1778, and the present cycle is rising at even a faster rate.

The predicted smoothed sunspot numbers shown on Figure 1 are based upon empirical calculations taking into account the latest Swiss predictions as well as other statistical data. These predictions are slightly lower than the Swiss forecast and indicate that the peak of




Fig. 1. Progress of Present Sunspot Cycle (19)

cycle 19 can be expected between March and August of 1957, and that the highest smoothed sunspot number will exceed 165.

#### **Abnormal Ionospheric Variations**

Ultraviolet radiation from the sun is bclieved to be responsible for the formation of the regular electrified layers of the ionosphere. Normal ionospheric variations have been discussed at length in Part 1 of this article. To review briefly, these consist of daily variations, which are a result of the twenty-four hour rotation of the earth about its axis, seasonal variations as a result of the earth's relative angular position and distance with respect to the sun, and the sunspot cycle variation as a result of the approximate 11 year variation in sunspot activity on the face of the sun. There also occur, however, abnormal variations in the ionosphere that cannot be explained in accordance with known solar relationships. Among these abnormal characteristics of the ionosphere are ionospheric disturbances. auroral displays, and the formation of Sporadic-E layers. It is necessary to investigate the behavior of these abnormal characteristics of the ionophere as well as the normal variations since both play an important part in the overall propagation of a shortwave signal.

#### Ionospheric Disturbances

There are two distinctly different types of ionospheric disturbances. One is termed sudden ionospheric disturbance, usually abbreviated SID. SIDs occur suddenly, and generally last for short periods of time upwards to two hours or so. The other type of disturbance is the ionospheric storm which develops over a period of a day or so and generally continues for several days.

SIDs are believed to be produced by solar flares. A solar flare is a bright, visible eruption occurring from time to time on the face of the sun and is usually associated with a large group of sunspots. The flares rarely last more than an hour before burning out. Excessive ultraviolet radiation believed to be emitted from the flare penetrates the upper layers of the ionosphere and forms a region of heavy absorption

ist under the E-layer. This absorption region generally referred to as the D-layer of the nosphere and is enhanced almost instantaneusly with the visual observation of the flare. -layer absorption is greater on the lower equencies (i.e., 80, 40 and 20 meters) than 1 the higher frequencies (i.e., 15 and 10 eters). At times absorption is great enough prevent any high frequency wave from enetrating the D-layer, and therefore reflecon can not take place from the regular layers the ionosphere and a radio blackout occurs. the SID is of low intensity, a partial fadeout ill occur, and transmission will continue to possible on the higher frequencies less afcted by the absorption. Since the sudden




Fig. 2. Sudden Ionospheric Disturbances, Washington, D. C.

nospheric disturbance is caused by excessive traviolet radiation from the sun, SIDs influice only transmission paths completely or artially in daylight areas of the world. The ID ends as the solar flare dies out.

Figure 2 shows the correlation that exists at ween the number of occurrences of SIDs and the sunspot cycle. During the peak of the st cycle, 1947-48, 148 SIDs were reported by the National Bureau of Standards in a twelve onth period at Washington, D. C. During the minimum of the past cycle, 1953-54, a velve month total of 7 SIDs was reported. As the approach sunspot maximum again we can expect the occurrence rate of SIDs to increase pidly, and several very intense ones have ready been reported during early 1956.

The second type of ionospheric disturbance, le ionospheric storm, constitutes a more seriis problem to shortwave communication beause of its much greater duration. While the D lasts for an hour or so, most ionospheric orms last for several days. Ionospheric storms e believed to have their origin in the vicinity f certain types of sunspots which appear to associated with violent solar eruptions. hese sunspots are called active sunspots to istinguish them from the regular ones that e believed to be responsible for the normal traviolet radiation from the sun. The active inspots are believed to emit corpuscular idiation which travels at a slower speed and ontains a much higher energy level than ultra-

violet radiation. On reaching the earth's atmosphere the corpuscular radiation is influenced by the magnetic field that surrounds the earth and is directed towards the magnetic poles of the earth. As a result, the effects of this radiation are more intense in areas around the magnetic poles. The high energy particles contained in the corpuscular radiation saturate the ionosphere, considerably increasing ionospheric absorption thus resulting in weakerthan-normal signal strengths. This radiation also sets up a turbulence in the ionosphere, reducing the ionization density of the layers so that waves which are normally reflected begin to penetrate and do not return to earth. During storms, the highest frequency which the F-layer will reflect may be reduced by as much as 50% below normal, and excessive fading may also be present. Under extreme conditions, the combination of a weaker ionosphere and increased absorption results in a radio blackout during which times long distance shortwave communication to various parts of the world becomes impossible, especially on those circuits that pass near the magnetic poles.

Unlike SIDs, and because it is caused by corpuscular radiation rather than ultraviolet, the ionospheric storm affects circuits both in the daylight and dark parts of the world. The storm is world-wide in character, lasting for several days, and is most intense in areas near the earth's magnetic poles, becoming less in-

tense in more southern latitudes.




Fig. 3. Ionospheric Storminess at Washington, D.C.

Figure 3 shows the co-incidence that exists between the sunspot cycle and ionospheric storms. During the peak of the last cycle, over 1200 hours were reported as disturbed at Washington, D. C., in a twelve month period. During the minimum of the last cycle, 1953-54, less than 800 hours were reported as disturbed. As we approach the maximum of the present cycle, we can expect a considerable increase in the number of ionospheric storms. However, this is not as serious as it may seem since the effects of an ionospheric storm during sunspot maximum are not as drastic upon communications as during sunspot minimum. For example, if a serious storm lowers the MUF on

a trans-Atlantic circuit by 50%, this results in a reduction in MUF from 40 to 20 Mc during maximum sunspot activity, still leaving considerable spectrum space for communications. During the minimum of the sunspot cycle, when the normal MUF on the same circuit may be about 20 Mc, the 50% reduction reduces the MUF to 10 Mc leaving very little, if any usable spectrum space.

#### Aurora

Corpuscular radiation from the sun, responsible for producing the ionospheric storm, also bombards the atoms and molecules of the gases present in the rarified atmosphere at the extremities of the earth, causing them to

ignite forming an aurora.

Of all natural phenomena, the aurora is probably the most breathtaking and spectacular. Usually called "northern" or "southern" lights, the aurora arcs across the night time skies at the extremities of the earth as weird, yellowish-green, dancing ribbons, violently throbbing rays and as great draperies folding and unfolding. They occur at E level height in




Fig. 4. Sporadic-E Occurrence, Washington, D.C.

the ionosphere, about 60 miles above the earth's surface and can be seen obliquely for

distances up to 600 miles.

Observations made over the past hundred years have defined areas of the world where the auroras occur most frequently. The zone of maximum occurrence, where the aurora occurs for approximately 250 nights a year, is a belt about 23 degrees centered around the magnetic pole in each hemisphere. The earth's magnetic poles do not coincide with the geographic poles. In the Northern Hemisphere, the magnetic pole is located on the northwestern tip of Greenland, and the zone of maximum occurrence, called auroral the Northern Auroral Zone, swings across northern Alaska, central Canada, the southern tip of Greenland. Iceland, over the northern tip of Norway and off the northern coast of Russia and Siberia. Auroras are seen less frequently as one proceeds south of this zone. In the northern areas of the USA, auroras are seen between 10 and 40 nights per year, while in southern areas of the USA, several years may pass before an aurora is seen.

Visible aurora plays havoc with shortwa radio communication. The excessive ionization believed to exist in the Auroral Zones resu in severe absorption of any shortwave sign that passes through or near this region. Asresult, the Auroral Zones act as a scree shielding shortwave transmissions from passi: through. For this reason trans-polar commun cation from the United States is extreme difficult and unreliable. Besides excessive a sorption, the aurora contributes a unique fa ing component to signals passing through the region. The fading is usually referred to "flutter fading" and consists of a low frequenaudio component, between 20 and 200 cr superimposed on the carrier. The fading cor ponent is usually severe enough to rend modulation unintelligible.

Shortwave transmissions passing south the Northern Auroral Zone are not usually a fected by this excessive absorption or fadin However, as certain disturbances take place in the earth's magnetic field, usually associate with abnormal sunspot activity, the region excessive auroral absorption spreads out, an visible aurora will occur further south. Th greater the disturbance, the further south the influence of the aurora is felt, and shortway circuits generally not bothered by the auronow become seriously disrupted. There is tendency for auroras to spread southward du ing the spring and fall months, and more often in years of high sunspot activity. During 194 when solar activity was at a maximum, 2 overhead auroras were observed in norther N.Y. State. During 1953, when the sunspo cycle was at a minimum, 10 auroras were of served at the same location. We can expect a considerable increase in auroral activity the sunspot numbers continue to climb toward a maximum.

#### Sporadic-E

There frequently forms within the norma E-layer region of the ionosphere, "clouds" of "patches" of abnormally dense ionization which are capable of reflecting radio waves c frequencies much higher than those reflected by any of the regular layers. These patchet usually take the form of thinly ionized area covering a rather small geographical region They occur more or less at random and ar relatively short lived, nevertheless they do ap pear to display seasonal, and possibly sunsport cycle variation at any one particular geographil cal location. Because of the intermittent natural of this type ionization it is usually referred to as Sporadic-E ionization. Electronic clouds of this nature are capable of reflecting radio waves, at oblique incidence, on frequencies ex ceeding 30 Mc and on remote occasions extending up to, and possibly somewhat beyond 100 Mc. Exceptionally long distance propagation does not often occur by way of Sporadic-E because of the remote possibility of the clouds being present over such a large area necessary for multi-hop propagation. Occasionally two-hop Sporadic-E propagation will occur for distances up to about 2400 miles, and from time to time the combination of regular F-2 layer reflection and Sporadic-E reflection will result in communication being possible over long distances during periods of time when F-2 regular propagation alone could not be possible. For the most part however, Sporadic-E propagation is limited to a one-hop distance not exceeding 1400 miles, and for this reason it is often referred to as "short-skip" propagation.

The occurrence of Sporadic-E propagation has been studied for some time but its cause is still unknown. Since it occurs more often during the daylight hours, it appears that ultraviolet radiation from the sun might play a part in its formation. On the other hand, since it also occurs quite frequently at night, some other source of ionization must also be responsible for its formation and recent suggestions point towards ionization from meteor trails and from auroral displays as other

sources.

Figure 4 shows the number of hourly periods during which Sporadic-E exceeded a critical frequency of 6 Mc at Washington, D.C. This would support propagation at frequencies above 29 Mc over oblique path distances of approximately 1200 miles. The occurrence of Sporadic-E rises sharply during the late spring and summer months, and occurs very little during the late fall, winter and early spring months. It is interesting to note that Sporadic-E at Washington, D. C. occurred far less during sunspot maximum than during the minimum of the previous cycle, further indicating that its formation may be independent of ultraviolet radiation from the sun. As we approach another sunspot maximum we can expect a decrease in the occurrence of Sporadic-E in the United States.

#### **Propagation Analysis**

Both the normal and abnormal characteristics of the ionosphere are influenced by the variation in sunspot activity. As solar activity increases, there is a corresponding increase in the intensity of ionization of the regular reflecting layers, resulting in the reflection considerably higher frequencies somewhat increased ionospheric absorption. The occurrence rate of auroral displays, sudden ionospheric disturbances and ionospheric storms also increase with rising sunspot numbers. On the other hand the formation of Sporadic-E clouds in the ionosphere appears to decrease as solar activity increases. While these characteristics of the ionosphere are of direct concern to the upper atmosphere scientist, the radio engineer and communicator are also concerned with the effect of these characteristics upon shortwave transmission.

During the past twenty years or so, procedures have been developed for applying basic ionospheric data in the determination of shortwave transmission parameters\*. Figures 5-8 are examples of circuit analysis curves derived from this procedure. The upper contour on the circuit analysis curve is the Maximum Usable Frequency, or MUF. The MUF, discussed at some length in Part 1 of this article, is the highest frequency that will be reflected by the ionosphere on 50% of the days of the month at the time indicated. The lower contour on the circuit analysis curve is the Lowest Useful Frequency, or LUF. The LUF is the lower limiting frequency for communications for a particular circuit and takes into account the radiated power of the transmitter, ionospheric absorption, the signal strength of the transmission at the receiver, atmospheric noise, and the necessary signal to atmospheric noise ratio to maintain intelligible reception on at least 50% of the days of the month. The LUF, in




Fig. 5. Circuit Analysis Curve, East Coast USA-Western Europe. Winter, Sunspot Low (1953-54). Horizontal arrows indicate time particular amateur band is usable.

this particular study, is based upon a radiated power of 250 watts. In general the LUF will not vary more than a few megacycles up or down throughout the range of power permitted for amateur operation. The LUF contour in *Figures 5-8* indicates the lowest frequency that will enable a signal to atmospheric noise ratio of 3 to 1 to be maintained.

Between the limiting contours of the LUF and MUF lies the range of frequencies useful for communications on a particular circuit.

Frequencies above the MUF will pierce the

<sup>\*</sup>Ionospheric Radio Propagation, National Bureau of Standards Circular 462, Supt. of Documents, Washington 25, D.C.

ionosphere and will not be returned to earth, while frequencies below the LUF will be so weakened by ionospheric absorption that signals will be below the atmospheric noise level at the receiver.

By utilizing basic ionospheric data observed during the last sunspot cycle, modified to take into account the rapid rise of the present cycle, it is possible to construct circuit analysis curves for determining the range of frequencies that will probably be useful during the next few years of maximum sunspot activity. In preparation for this article, over three hundred such circuit analysis curves have been calculated for nearly fifty long distance circuits in all directions from the United States. Space does not permit the publication of each curve, but pertinent data has been summarized and will be discussed in reference to each amateur band in which ionospheric propagation takes place. Figures 5-8 are typical examples of circuit analysis curves and can be used for a comparison of the range of usable frequencies between sunspot minimum and sunspot maximum on winter circuits from the East Coast to Europe and from the West Coast to Australasia.

The period of maximum solar activity is assumed to take place when the smoothed sunspot numbers exceed 130. From data appearing in *Figure 1*, this period is expected to begin September 1956 and last through the spring

of 1958.

The following is a band by band summary of propagation conditions expected during the period of maximum solar activity, September 1956 through April 1958. The spectrum from 10 through 160 meters is discussed first, followed by a summary for 6 meters and the VHF




Fig. 6. Circuit Analysis Curve, East Coast USA-Western Europe. Winter, Sunspot High (1956-57)




Fig. 7. Circuit Analysis Curve, West Coast, USA-Australasia. Winter, Sunspot Low (1953-54). Horizontal arrows indicate time particular amateur band is usable.

range. All times referred to in the following summary are given in Local Standard Time.

#### 10 Meters:

The 10 meter band, practically in hibernation during the low sunspot years of 1952 through 1955, awoke during the fall of 1955 as the smoothed sunspot numbers passed 60. As the sunspot cycle continues to climb, long-distance propagation conditions are expected to improve considerably on 10 meters. Beginning with this coming September, and lasting at least through the early spring of 1958, propagation conditions are expected to be excellent from the United States to all areas of the world. During the fall, winter and spring months it should be possible to work all continents in a matter of a day, and more likely in a matter of just a few hours. Because of low ionospheric absorption in this frequency range, signals are expected to be exceptionally strong even with relatively low power transmitters. The band is expected to open from shortly after sunrise and remain open on most undisturbed days until early evening. Peak conditions should occur during the late afternoon and early evening hours. During the late spring and summer months, the normal seasonal trend of lower MUF's will result in fewer 10 meter openings than during other seasons, but propagation conditions are expected to be good enough to permit a considerable amount of world-wide  $\mathbf{D}\mathbf{X}$ almost daily through the summer months. During the summer months, conditions peak later in the day than during the other seasons, and propagation will favor northsouth paths. Except during ionospheric storms, auroral absorption is considerably less intense in this frequency range and trans-polar propagation to Asia and parts of Europe should be possible on a good number of days, especially during the early morning and early evening hours of the fall and spring months. A typical example of the improvement in 10 meter propagation conditions during the period of maximum solar activity can be seen from Figures 5-8. During the winter months of 1953-54, when the previous sunspot cycle was approaching a minimum, no 10 meter openings were possible between the United States and Europe, and only an occasional opening occurred between the West Coast and Australasia during a two hour period in the late afternoon. During this coming winter, the 10 meter band is expected to open to Europe almost daily between 6AM and 3 PM EST and between the West Coast and Australasia between 9 AM and 8 PM PST.

#### 15 Meters:

While world - wide propagation conditions were fairly good on the 15 meter band for at least a few hours a day on most days during the years of minimum solar activity, conditions on this band are expected to improve considerably during the next few years of maximum solar activity. Beginning with September, the band is expected to be open to all areas of the world between the hours of dawn and late evening. On many circuits, especially those to Central and South America, the band will remain open around the clock on many days. Daytime absorption will be somewhat higher, especially during the summer months, and signal strengths will dip during the late morning and




Fig. 8. Circuit Analysis Curve, West Coast, USA-Australasia, Sunspot Maximum (1956-57).

early afternoon hours. Peak propagation conditions will occur during the late afternoon and evening hours when ionospheric absorption decreases, and signal levels are expected to be exceptionally high, even for relatively low power transmitters. Transpolar propagation to Asia and parts of Europe should be possible on most undisturbed days, especially during the early morning and early evening hours of the fall and spring months.

#### 20 Meters:

While long distance propagation remains good on 20 meters throughout the sunspot cycle, the propagation pattern on this band changes considerably between the vears of minimum and maximum sunspot activity. During the years when sunspot activity is low the 20 meter band is predominately a daytime band, opening shortly after dawn, and remaining open until around sunset. As solar activity increases, the 20 meter band remains open for longer periods of time. Beginning with September, and lasting until at least the spring of 1958, the 20 meter band is expected to open from shortly after dawn and remain open to about midnight. For a high percentage of time, propagation conditions will be good enough to permit the band to remain open around the clock on many long distance circuits. Daytime absorption increases on 20 meters by about 6 DB, on the average, during sunspot maximum. This will cause signals to become considerably weaker during the late morning and early afternoon hours, especially during the summer months. Long circuits, especially those in a north-south direction, may fade out altogether during this period. Conditions on 20 meters can be expected to be optimum during

the late afternoon and evening hours when ionospheric absorption is minimum. During this period of optimum conditions signal levels are expected to be exceptionally strong, and it should be possible to work all Continents without much difficulty. QRM is expected to increase considerably on 20 meters since short-skip propagation conditions will also be optimum during much of the same time that the band will be open for DX. During the late [continued on page 107]

# G. D. O. doubles as Crystal Oscillator

Robert J. Ropes, W9PAP

The grid-dip oscillator has become a universal piece of equipment, and nearly every serious amateur and experimenter has one. Most experimenters do not realize, however, that by adding a simple adapter, they will have a fine crystal-controlled utility oscillator at almost no additional expense.

Most grid-dip oscillators, both "home-built" and commercial, use the basic Colpitts oscillator circuit. By making a simple adapter to

using a 5-prong steatite tube socket for the crystal socket, both the FT-243 and the standard 34" spaced crystals can be used with the same adapter. (Fig. 2). Use a short length of 114" plastic tubing to make a neat assembly of this adapter.

The signal radiated from the crystal is adequate for all receiver alignment purposes, and where it is necessary to couple an output voltage direct into a circuit or a standard capaci-




Figure 1.

allow the crystal to be connected across the coil terminals, the grid-dip oscillator now becomes a crystal-controlled oscillator, having more r-f output than is usually obtained with a high-Q coil (Fig. 1). The G.D.O. tuning capacitor can be used to slightly adjust the crystal frequency, in those cases where the oscillator is to be used for a secondary frequency standard, etc.

The crystal-controlled G.D.O. makes an excellent signal source for use in aligning receivers. Most G.D.O.'s will oscillate easily with any good crystal between the frequency ranges of 455 kc to 10 Mc.

When making the adapter, it is a good idea to use polystyrene instead of bakelite, etc. By



Figure 2. FT-243 type crystals plug in between pins #2 and #3 and standard crystals between pins #2 and #4.


tor, the voltage should be taken from the terminal of the crystal which is in the *plate* circuit of the G.D.O., through a 50 or 100  $\mu\mu$ fd. fixed capacitor.

Editors note: The Heathkit GD-1B works just fine as an xtal oscillator. Further, by turning up the sensitivity to maximum you can get a good indication of the activity of the crystal by the reading on the meter. A good crystal will put the meter off scale. Any reading from half scale up should be satisfactory, but lower readings point to a need for cleaning of the crystal.

#### orman R. McLaughlin, W6GEG

143 Muirfield Road 3 Angeles, 8, California

Fig. 1. The Top Loaded Ground Plane for 75 Meters stands 35 feet. 10 foot sections of thinwall conduit, a loading coil and a 6 foot whip make up the vertical radiator.



a "shorty" Ground Plane

## A Top Loaded Ground Plane Antenna for 75 Meters

Three ten foot sections of thin wall elecical conduit, a high Q loading coil and a six ot whip antenna can be easily made into a ry effective vertical radiator. When worked gainst an array of quarterwave radials it bemes an efficient ground plane antenna.

There are a number of advantages to vertical tennas and a number of disadvantages as




Fig. 2. A 6 turn coil shunted across the coaxial, cable assures proper termination at the antenna base. Coil is 3 inches in diameter, of 16 wire.

well. This configuration affords all of the advantages and eliminates one of the main disadvantages. While the advantages are well known they might be reviewed before getting into constructional details. They are:

1—Low angle of radiation with a substantial concentration of radiated signal equivalent to several db gain at an angle ap-

proximating 45°

2—Ease of feeding. Readily available coaxial cable need only be connected to the base as described later. No elaborate networks, balun coils or the like are required

3—Little space is required in which to erect

the antenna.

4—Excellent efficiency is possible. Broadcast station vertical antennas have demonstrated efficiencies in excess of 90%

The main disadvantage to a vertical radiator is that it must work against a good ground system if reasonable efficiency is to be expected. As a rule, this implies an elaborate radial ground system. The latter, in turn, usually means digging small trenches in the lawn, flower bed and tunnelling under sidewalks and driveways, all of which is nothing but hard

work. By use of ground plane radials, as described herein, a good ground system is ob-

tained with a very minimum of effort.

Figure I tells the story of the vertical radiator itself. A base section made of 1" thin wall electrical conduit supports a  $\frac{3}{4}$ " section which in turn supports a  $\frac{1}{2}$ " section. Each section is telescoped into the other, 12". Telescoped ends



Frame which holds the ground screen and base insulator, made of scrap lumber. 2x4's serve as feet which straddle the garage roof peak. Wood screws hold the ground screen on the frame.

are peened to the inside diameter of their lower section to reduce vibration in high

winds.

Atop the ½" section is mounted a coil normally used for loading mobile antennas. While waterproof reducers couple the section of conduit together, a ½" coupler that takes a standard ½" pipe connector is used to mount the coil onto the conduit. A standard ½" pipe plug is drilled to take a ¾ 24 bolt through its center. The connector is screwed onto the coupler. The ¾ 24 bolt is fed through the plug up into the base of the coil and then the plug



Ground screen, base insulator and frame, with 62 foot radials cut and rolled into coils await hoisting atop garage roof. Ground screen is scrap dural 20x24 inches.

is screwed into the pipe connector. The whip screws into the top of the loading coil to com-

plete the antenna.

At the base is connected a 1-1/4" reducer to which a standard 1-1/4" pipe connector is attached. A 1-1/4" standard pipe plug fits into the connector, after having been drilled through its center to take the 3/8 18 bolt that holds the antenna onto the base insulator.

While a porcelain insulator is shown, the

type of insulator used at the base is not creal. At even maximum legal power, voltage this point will be quite low. Ordinary ha wood impregnated with paraffin, coil dope other dielectric material to keep it dry will a good job.

Feeding the antenna is accomplished shown in the schematic of *Figure 2*. Fifty of coaxial cable shunted by a small coil connect to the base. The coil which consists of 6 to of No. 16 wire space wound three inchest diameter cancels the capacitive reactance the line and effectively keeps the line out

the antenna system.

The ground system consists of a ground screen and six quarterwave radials. Size of a ground screen is not too important. The consoler shown just happened to be 20 inches by inches, but obviously the larger the screen about the screen better. Radials were cut to measurement, however. Each one was pruned to a length of feet.

After radials were cut to length they we assembled on the ground screen. The latter supported by a frame (see photo), whi straddles the peak of the garage roof up




Fig. 3. This simple field strength meter consists of a germanium diode such as a 1N34, a .005 condenser and a 0-5 milliampere movement meter. More sensitive meters can be used, but since readings are only comparative, in this usage, a more common movement will suffice. Many surplus meters that read low DC voltages have 0-5 ma. movements and can be bought quite inexpensively.

which the radiating system has been erected. However, the radiator was 'rough tuned' before being hoisted to the garage as follow

1—Coax was connected to antenna as show

in Figure 2

2—The opposite end of the coax was teminated with a 50 ohm ½ w. carbdaresistor

3—The transmitter was set on the desire frequency and a random length of wir was attached to its antenna connection

- 4—A simple field strength meter, Figure was connected to the end of the coathat is terminated with the 50 ohm resistor
- 5—Input to the transmitter was then set the where about a quarter scale deflection appeared on the meter
- 6—Antenna was lowered and turns of the coil were shorted out a few at a time until optimum reading was achieved or the meter

The whole system was then hoisted to the

roof. The ground screen was put in place and radials were strung out as far as possible in straight lines and then bent around until they were extended to their full length. While it would be nice if radials could be laid out as though they were spokes of a wheel this is seldom practical for the amateur. Therefore it is necessary to string radials around in several directions. Even though radials might run through trees, shrubs, down sides of buildings and along fences, they are considerably better than no radials at all.

The antenna was then hoisted into position and guyed loosely. Impregnated rope serves as guys although that new plastic clothesline with the nylon tire cord core is even better. The latter does not stretch while the rope has stretched for several months, requiring frequent trips to the roof to take up slack.


With the antenna in position the same procedure as outlined previously was gone through. The coil was tapped down until optimum reading was obtained. This requires raising and lowering the antenna a number or times, but it is time well spent.

Since the meter is attached to the far end of the coax, it was brought up to the roof of the garage. There readings were available as fast as the antenna could be lowered and raised. As a result the coil pruning process took less time than it might first appear. The whole job was done by one man, but two makes life so much simpler!

At W6GEG this top loaded ground plane has worked out even better than expected. While rag chewing is preferred to DX, contacts have been made as far West as Midway Island, as far North as Kodiak, Alaska and up and down the East coast of the United States

with excellent reports.

The transmitter is a single sideband transmitter with a pair of grounded grid 6L6's in the output stage. Despite this modest tube array 50 db over S9 reports have been obtained from San Francisco, 30 db over S9 from Denver, Colorado and 40 db over S9 from Seattle during rag chews! No such reports were received before a conventional half wave dipole was replaced by the top loaded ground plane.



# 2 On Two

Bert Green, W2LPC Amperex Electronic Corporation 230 Duffy Avenue Hicksville, New York

Just a few years ago if one wanted to use crystal control on two-meters it would have meant a l.f. crystal and four or five doubler stages. In addition, the h.f. performance of the old high-inter-electrode capacity tubes would be poor. Now with the new harmonic-crystals, and h.f. tubes at low prices, a crystal-controlled two-meter transmitter can be constructed with just two Amperex 6360 miniature tubes. This transmitter will run 17 w. input on phone or 30 w. input on CW.

The Amperex 6360 is similar to its big brother, the Amperex 9903/5894, but is of the 9-pin miniature type and sells for about four dollars. The tube is a dual-tetrode with a com-

mon cathode, common screen and dual-filaments that can be used in parallel for 6 v. operation or in series for 12 v. operation. This allows the tube to be used for mobile work in either the older 6 v. cars or the newer 12 v. ones. The tube is designed with short leads and a button stem for full ratings up to 200 mc.

The transmitter is constructed on a 4" x 6" aluminum bottom plate in order that a Bud AC-430 4" x 6" x 3" aluminum chassis can be used for a base and cover. This small size makes the transmitter useful for mobile work since it can be clamped to the steering wheel post, or kept in the glove compartment.

From the picture of the top of the transmit-

ter, starting from the left is the crystal, 6360 harmonic crystal-oscillator and trippler (V1), L1 is in front of V1, C2, push-pull 6360 amplifier (V2), C3, coax output, and C4 in front

of coax output.

In the schematic diagram all leads are shown metered, but some of these meters could be eliminated or a single meter and switching arrangement used at the discretion of the builder. The schematic shows the transmitter set for phone operation: for *CW* operation the plate-voltage may be increased to 300 v.

The first section of V1 is a harmonic crystaloscillator and is used with a fifth harmonic crystal (48.666 Mc.). C5 and C6 form the feedback circuit. The amount of feedback is fairly critical. Making C5 smaller increases the feedback and making it larger decreases the feedback. With different make crystals the feedback may have to be adjusted. The feedback should be adjusted so that the crystal oscillates on its harmonic readily, but too much feedback will cause the oscillator to oscillate without the crystal plugged in. L1 should always be tuned for the harmonic frequency. (48.666 Mc.) because when LI is off resonance the circuit acts as a Pierce oscillator and oscillates on the crystal fundamental frequency.

The second half of V1 is a tripler to 146 mc. This feeds a balanced tank circuit to provide balanced drive to V2, the push-pull am-

plifier.

R6 and R7 in the screen circuit of V2 are

such as to provide the correct ratio of audit to appear on the screen for 100% plate modulation.

L3 is made up of two coils, each being turns of Air Dux #416T or B&W #3003\* co stock and spaced 1/4" apart to allow L4 t swing in and out.



Tiny modulator for the "2 on Two."


The meter readings are approximately as follows using a 200 v. power supply:

Osc. Plate—15 ma.
Trip. Grid—1 ma.
Trip. Plate—25 ma.
Amp. Grid—1.8 ma.
Amp. Plate—70-86 ma.

No trouble was experienced with parasitics or self-oscillation in the final due to the fact that these tubes are internally neutralized.

After building the transmitter I looked

\*16 Turns per inch, 1/2" diameter.



Schematic for the "2 on Two", with optional modulator shown



Bottom view of the "2 on Two" r-f chassis.

round for a modulator and decided to keep it mple and use the same tube, so that only one pare would have to be carried. I came up with unit that only used a 6360, a condenser, a fattery and two transformers. When completed fit into the palm of my hand. The modulator clivers about 7 w. of audio with 200 v. on the lates and screen, but this can be increased to 2 w. if the plate voltage is increased to 300 v. Looking at the picture of the top view, the 360 is at the rear left corner with the 22½ bias battery just in front. In the center is the odulation transformer. To the right rear is he power plug and just in front is the output lug. The jack on the front is for the single utton carbon mike.

Looking at the photograph of the bottom ew we see C14 and the mike transformer TI).

#### Parts List

C1-47 µµfd. tubular ceramic Erie C2, C3-8 µµfd. butterfly

Johnson 9MB11 C4 — 32 μμfd. variable

Johnson 30M8 C5-27 μμfd. tubular ce-

ufd. tubular ceramic Centralab

16—100 μfd. 6 v. electrolytic C.D. #BBR-100-6

R1. R2 — 100K ½ w. Ohmite

R3-10K 1/2 w. Ohmite R4, R5, R6 -33K ½ w. Ohmite

R7-12K 1/2 w. Ohmite RFC1-Ohmite Z-50 R.F.

RFC2-Ohmite Z144 R.F. choke

T1-High gain carbon mike trans. Triad A-

T2 - Multi-Tap modulation trans. Stancore A-3891

V1, V2, V3 — Amperex 6360

Xtal-48.666 Mc. International Crystal

Bat.-221/2 v. Eveready #412 L1-9½ turns


enam. wire on National XR91 coil form L2—2½ turns Air-Dux #416T or B&W #3003

tapped at center (16T/ in-½" dia.) L3—4 turns

Air-Dux #416T or B&W #3003 spacing at center L4-2 turns Air-Dux #416T or B&W #3003

In the schematic diagram it will be seen that the mike is in the cathode of V3. This eliminates the use of a mike-battery with its constant replacement problems. However, a 22½ v. battery is used for grid bias, but the life of this battery is practically equal to its shelf-life as no grid current is drawn since V3 is operated class AB1. T1 is a very high gain type in order to supply the necessary grid to grid voltage.

The modulator is built on the cover of a Premier PMC-1002 miniature aluminum case




Modulator, bottom view.

 $4'' \times 2\frac{1}{8}$ " x  $1\frac{5}{8}$ ". The mike jack is a closed circuit type in order to prevent the voltage across C14 from exceeding its voltage rating when the mike is removed from the jack. Since there is no mike-battery the mike may be left in the jack at all times.

For mobile use the 200 v. at 60 to 70 ma. for the modulator may be obtained from the car receiver by inserting a S.P.D.T. toggle switch in the B+ lead of the receiver.

## Mobile

## Reference-Shift Modulator



The author's referenceshift-modulated mobile rig. The modulator (right to left) uses a 12AX7, 12AU7, and 1614 (or 616) with modulation choke mounted inside the chassis. Input to final is 35 watts.

Dale L. Hileman, K6DC Ramo-Wooldridge Corp. Inglewood, Calif.

In the design of both mobile and fixedstation rigs, the modulation transformer is an eternal headache. Unless you pay extra for a multimatch transformer, you're limited to only one final-amplifier load impedance. This is especially notable in the case of the mobile rig which will seldom load according to your expectations.

To avoid the transformer problem you can use screen modulation (frequently used in mobile rigs), but this method provides a carrier efficiency of only about 30 per cent. No ordinary efficiency-modulation system can offer the psychological boost to be obtained from a plate-modulation carrier efficiency of 60—80 per cent.

One solution is Heising, or choke-coupled, plate modulation. With Heising plate modulation the final operates at the usual 60—80 per cent class-C efficiency. In this system an or-

dinary filter choke replaces the modulation transformer. A choke is a common junk-buitem; or, if you don't have a choke with surable characteristics, you can buy one at hat the cost of a comparable modulation transformer.

However, the class-A<sub>1</sub> amplifier used in conventional Heising modulator has two serous shortcomings: First, since the maximum modulator plate dissipation occurs with naudio input the permissible modulator plate power input is therefore limited to the rate plate dissipation of the tube even though the actual plate dissipation drops below this value with audio input. In other words, you can take full advantage of the tube's capabilities Suppose, for example, you use a 6L6 in conventional class-A<sub>1</sub> modulator. The rate plate dissipation of this tube is about 20 watt therefore you're limited to 20 watts input the modulator. But with maximum audio input

# A transformerless plate modulator for a 35-watt mobile rig

36 • CQ • June, 1956

e actual plate dissipation drops to 13 watts less. This leaves 7 watts or more of potential

ite dissipation that goes unused.

:Second, the maximum plate-current swing severely limited; hence, maximum modulator ite efficiency is usually only about 30 per

Both of these objections can be overcome by circuit in which modulator plate current is duced in the absence of audio input. By this eans, the full plate-dissipation capability of tube can be utilized and the power input ereby increased. Also, the greater plate-curit swing increases efficiency. In fact, if linrity can be maintained, the theoretical maxium efficiency of 50 per cent can be obtained. Two systems which fulfill these requirements ve recently appeared in CQ: The first, and far the oldest, is bias-shift modulation, uvenated in 1950 by M. H. Kronenberg<sup>1</sup> d modernized in 1954 by Bill Orr<sup>2</sup>. In this stem, the modulator tube is operated classand control-grid bias is varied according the audio level. An increasing audio level creases the bias and consequently increases andulator plate current.

The other variable-plate-current Heising sysn is called "class-K" modulation and was veloped by the author<sup>3</sup>,<sup>4</sup> in 1953. In the iss-K system, the modulator (not the r-f (al) is fitted with an audio-controlled clamp be. An increasing audio level increases the dio-clamp-tube bias and thereby increases




Fig. 1. Basic reference-shift modulator. Choice of values is discussed in the text.

the modulator screen voltage. The modulator is operated at zero bias so that a high platecurrent swing can be obtained within a reasonable screen-voltage excursion.

Both systems provide a high modulation level, good efficiency, and excellent linearity. However, each has its drawbacks. The biasshift system requires the use of a fixed-bias supply and one or two bias-control tubes, which contribute to physical size, complexity, and cost. These factors are particularly important in the design of a mobile modulator.

The class-K system, while requiring no fixedbias supply, does use a power-consuming audio clamp tube. And because this modulator is operated at zero bias, it requires considerable driving power, which means that the driver consumes appreciable d-c input power. Powersupply drain is of course another important consideration in the mobile modulator.

Reference-shift plate modulation combines the better features of the bias-shift and class-K systems and avoids the disadvantages of both. No fixed-bias supply is needed, no unwieldy clamp tube is used, and the driver requires very little input power. This modulation system is therefore particularly well suited to the mobile rig.

#### Reference-Shift Modulation

Reference-shift plate modulation is basically bias-shift modulation with positive bias. Don't be alarmed: Positive bias has no ill effect since the modulator tube is operated as a zero-bias

The unique cathode-follower driver circuit which makes a practical reference-shift modulator possible was suggested to me by Henry S. Keen, W2CTK. Mr. Keen had devised a controlled-carrier screen-modulation system in which the d-c output level of the modulator is a function of the audio input voltage<sup>5</sup>. Mr. Keen suggested that his modulator might be an excellent driver for a variable-plate-current Heising plate modulator. He was quite right.

Detailed operation of the reference-shift plate modulator is described in the April issue of Radio & Television News6. However, here is a brief circuit analysis:

The basic reference-shift circuit is shown in Fig. 1. The output of cathode-follower driver V1 is an audio voltage impressed on a positive d-c voltage equal to the peak audio voltage. The average plate current of modulator V2 is therefore proportional to the audio input voltage.

Voltage divider R3 and R4 applies a fraction of the cathode voltage to the anode of rectifier CR1. Output from CR1 is filtered by C2 and applied as a positive d-c reference level to the grid through grid-return resistor R1.

M. H. Kronenberg, "Low Cost Modulator for the KW Final," CQ, Oct., 1950, p. 34.
Orr, "The Bias-Shift Modulator," CQ, April, 1954,

Hileman, "Class K Modulator," CQ, Oct., 1953, p. 37. Hileman, "Class K Mobile Modulator," CQ, Sept., 1954,

A similar system is described in CQ: Thomas E. Beling, "The Midget Budget Modulator," CQ, September, 1955, p. 45.
Hileman, "A Reference-Shift Modulator," Radio & Television News, April, 1955, p. 46.

Resistor R2 permits C2 to discharge at a syllabic rate but not an audio rate. The reference voltage is therefore a function of the

average audio level.

With no audio input, VI is biased by the voltage developed across R3. This voltage is high enough that the plate current of VI, and therefore the cathode voltage, is relatively low. But audio voltage applied to the grid through CI causes an audio voltage to be added to the already-existing d-c voltage at the junction of R3 and R4. The resulting increase in reference voltage increases the average cathode current, which in turn increases the d-c cathode level. The d-c output level of VI thus increases as its audio output level increases.

Modulator V2 is a zero-bias triode operated with positive bias; this bias is the d-c output level of V1. Since the d-c output level of V1 is a function of the audio level, the average plate current of V2 is also a function of the

audio level.

With no audio input, therefore, the plate current of V2 is at its minimum value. With maximum audio input, the plate current is at its maximum average value, swinging between cutoff and saturation. This plate-current swing provides a plate efficiency of 50 per cent or more.

Compared with the characteristics of a conventional class-A<sub>1</sub> modulator, the increased efficiency of a reference-shift plate modulator and the increase in permissible power input almost triple the obtainable power output. Thus where a 6L6 normally provides a power output of 7 watts, in a reference-shift circuit it delivers an output of almost 21 watts.

The 6L6 is of course not a zero-bias trice it is a tetrode. However, any tetrode can made to operate as a zero-bias triode, as plained later.

#### Choice of Values

Driver VI should have a relatively low place resistance so that a low source impedance presented to the grid of V2. And the maximated cathode-to-heater voltage of VI must high enough to permit a relatively high perpositive output voltage. Among the tubes to fulfill these requirements for low- or median power applications are the 6BF5 (triode connected), 6C4, 6S4, 12AU7, and 12BH7.

Resistors R3 and R4 should be equal value. The mathematical proof of this stament is somewhat involved; however, expe

mental evidence bears it out.

These resistors are simply a voltage divid loaded by a relatively high impedance, a should not present an appreciable load to compared to the grid-to-cathode resistance V2. The total resistance of R3 and R4 should be 5 to 10 times the load presented by the grid of V2.

Rectifier CR1 must have a maximum ratiback voltage equal to or higher than the maximum reference voltage. A 1N38 will tolera a back voltage of about 100 volts; for a high voltage, a thermionic rectifier (such as t. 6AL5) is most practical. Crystal diodes series are not recommended; two cost mothan one 6AL5 and cannot be depended on have equal back resistances.

The time constant of components in the cathode circuit of CRI is not at all critical be




Fig. 2. Complete schematic diagram for the mobile reference-shift modulator.

C1—0.001  $\mu$ fd., 500 v. C2—380  $\mu\mu$ fd., 500 v. C3—8  $\mu$ fd., 450 v. electrolytic C4—470  $\mu\mu$ fd., 500 v. C5--0.002 µfd., 500 v. C6-5 µfd., 450 v. elec-C7-0.005 µfd., 500 v. C8-500 µµfd., 1000 v. (see text) C9-0.002 µfd., 1000 v. (see text) CH1-5 henries, 200 ma CR1-1N38A diode J1-microphone jack, as required R1—1500 ohms,  $\frac{1}{2}$  w. R2, R3-100,000 ohms, I; W.

R4-500,000-ohm potenti-R5-5600 ohms, 1/2 w. R6-470,000 ohms, ½ w. R7, R11-1 meg., ½ w. R8, R10-10,000 ohms, R9-220,000 ohms, ½ w. R12, R13-47,000 ohms, ½ w. (5%) R14-22,000 ohms, 1 w. R15-10,000 ohms, 1 w. (see text) V1-12AX7 tube V2-12AU7 tube (do not V2-12AU7 tube (do not use 12AX7 for V2) V3-1614 or 6L6 tube (1614 preferred)

should be as small as will permit full reference voltage for the lowest audio frequencies involved. Experimental data indicate that a time constant of 0.005 to 0.05 sec is satisfactory.

The reactance of C2 at audio frequencies should be 2 to 5 times the resistance of R3 or R4 so that it charges quickly as the audio level increases. With a given value for C2, therefore, the time constant is determined primarily by the resistance across C2. So if CR1 is a thermionic rectifier having an almost infinite back resistance, the time constant is determined by the value of R2. But if CR1 is a crystal rectifier, then its back resistance may determine the time constant, making R2 unnecessary.

The resistance of RI is the normal gridreturn value for VI. Coupling capacitor CI, however, should be as small as practicable to that it has negligible effect on the time con-

stant.

I have referred to modulator V2 as a zerobias triode; actually a triode has probably never been used as a reference-shift modulator. Instead, tetrodes have been used. Modulator input voltage is applied directly to the screen grid and to the control grid through a current-limiting resistor, a method commonly used in class-B zero-bias modulators using tetrodes.

Experiments with several tetrodes indicate that a tetrode reference-shift modulator requires a maximum d-c screen-voltage input level equal to one-third the value necessary for

class-C operation.

The reactance of modulation choke *CH1* (at about 200 cps) should be equal to or higher than the power-amplifier plate impedance. Its current capacity should be about equal to the sum of the modulator and final plate currents. The lower its d-c resistance, the better.

For a high modulation level, the modulator must deliver an output power equal to half the input power to the final r-f amplifier. The maximum plate efficiency of a reference-shift moduator is 50 per cent; therefore, maximum

modulator power input is equal to final r-f amplifier power input. For the same reasons, the modulator should have a rated plate dissipation equal to at least half the final power input.

In a conventional class-A, Heising plate modulator, a d-c voltage-dropping network is required between the modulator plate and the final to produce 100 per cent modulation. However, in a reference-shift circuit, the modulator plate-current swing is great enough that a voltage-dropping network is unnecessary. This system provides a modulation level which for all practical purposes is equivalent to that of a conventional class-B modulator.

#### A Mobile Modulator

A schematic of the mobile reference-shift modulator is shown in *Fig. 2*. The speech amplifier uses three triode sections; *V1a*, *V1b*, and *V2a*. Section *V2b* is a cathode-follower driver for modulator *V2*.

Input amplifier V1a is a grounded-grid stage, eliminating the need for an expensive and bulky microphone transformer; sections V1b and V2a are conventional cascaded triodes. These three stages provide enough gain to make cathode-bypass capacitors unnecessary.

Frequency response of the modulator is determined by circuit constants in the speech amplifier. Low-frequency response is limited by the low values of coupling capacitors CI and C4; high-frequency response is limited by R3 and C2 in the grid circuit of VIb. Values for these components are so chosen that response is 1 db down at 500 cps and 2500 cps, limits customarily recommended for amateur modulators. However, many operators prefer more high-frequency response in a mobile rig. Therefore, to boost high frequencies, simply exclude R3 and C2.

Reserve gain is sacrificed to eliminate cathode-bypass capacitors. However, any of the speech-amplifier cathode resistors may be bypassed if more gain is needed.

Capacitors C3 and C6 and resistor R10 are a dynamotor hash filter. They are not necessary if the mobile-power-supply output is well

filtered.

Values in the driver circuit were chosen in accordance with the principles described under "Design Considerations." Rectifier *CR1* is a 1N38A; any diode having a rated back voltage of 100 volts or more and a nominal back resistance greater than 0.5 meg. is satisfactory. However, if you use a thermonic rectifier or a diode having a back resistance exceeding 3 meg., connect a 1.5-meg. resistor across *C7*.

A 6L6 operates satisfactorily for modulator V2. A 1614, however, is a better choice since it offers a higher plate-dissipation rating at no


increase in physical size.

Choke CH1 should have an inductance of [continued on page 100]

# New Radioteletype Frequency Shift Converter

Arthur A. Usner, W5QHB

4167 D Alabama Ave. Los Alamos, New Mexico



Nowhere has amateur radio technical advance been more rapid than in the field of radioteletype. In the short space of 10 years the earnest group of several thousand printing telegraph enthusiasts have demonstrated that no complex commercial developments exist that will not yield to simplification and a great decrease in cost. As is generally the case, radio amateur interest in new methods of communication results in worthwhile improvements which commercial concerns are quick to recognize and make use of.

Radioteletype signals may be transmitted over systems using CW, FSK, AFSK, multitone and pulse techniques. They may be single channel or several simultaneous channels (multiplex). CW, known as "Make-and-Break" keying to RTTY men, has proven impractical for amateurs and professionals alike since it requires signals from 10 to 1000 times greater than those which will reproduce "solid" copy with FSK and AFSK. Multitone methods of reducing printing errors caused by fading and weak signals find no application in the restricted space of the narrow amateur bands. Pulse systems are limited, by federal regulation, to the UHF range, leaving only the two frequency shift techniques.

FSK is a form of very narrow-band frequency modulation in which the modulating intelligence, a square keying wave with a frequency of about 22 cycles at typing speeds of 60 to 65 WPM, causes the radio carrier frequency to vary a few cycles in time with the opening and closing of the contacts in the teletypewriter sending mechanism. AFSK is used exclusively on VHF and UHF bands and on 11 meters where the ultimate in spectrum economy is not required and lack of receiver and transmitter stability may cause problems. In AFSK the r.f. carrier frequency is not shifted but, instead, the shift is applied to the frequency of an audio tone (sub-carrier) modulated onto the carrier. Amplitude modulation is customarily used but FM is also possible and has seen some application on the 6 and 2 meter bands. AFSK is peculiarly wellsuited for VHF operation but would be prohibitively wasteful of space in the lower fre-

quency amateur bands.

For reasons of economy it has been common practice, hitherto, for radio amateurs to design their receiving equipment to take care of both FSK and AFSK emissions. This has necessitated the conversion of shift-signal to teletype impulses at audio frequencies. Most of the circuits thus far published in CQ have been of the audio frequency variety of converter because of the great predominance of VHF operation. The number of stations employing FSK only has more than doubled since the frequencies below 27 mc have become available. Many of these low frequency RTTY stations are located in areas where VHF communications do not exist or are impractical. For these amateurs a radioteletype converter obtaining its discrimination at i.f. rather than at audio frequencies may have certain advantages. A substantial advantage is the fact that tuned circuits with adequate "Q" are easily achieved in the i.f. range. AVC may be used in the receiver since the BFO is switched off ith this system. With 40 or 50 db of instanneous "limiting" in the converter, in addition an equal amount of compression by AVC, most any degree of fading can be tolerated.

A large number of commercial and military rcuits have been developed which secure eir discrimination between the mark and ace signals at intermediate frequencies. The rcuit of the unit illustrated was derived from e military CV31/A and adapted to better it radio amateur needs by the elimination of dual-diversity, drift-compensator ark-hold circuitry. Since the radio receiver in e writer's station makes use of a low freiency receiver fed from the last intermediate age of the h-f receiver as a Q5'er, a very pular combination among RTTY men,\* it as decided to tap off some of the 85 kc i.f. the Q5'er and construct the teletype conrter to make use of this low i.f. frequency. t 85 kc it is easy to secure adequate disimination of the 850 cycle shift in carrier equency from mark to space which is the mmercial, military and amateur standard. arrower shift can be easily accommodated by slight retuning of the discriminator coils. Or, parate trimmers could be employed with a vitch having its two positions marked "narw" and "wide".


The block diagram of Fig. 1 gives a general lea of the converter and the main diagram ay be better comprehended by the following

lige-by-stage description.

The limiter-amplifier serves as a straight amifier for weak signals and as a limiter for rong signals. The first tube, V1, behaves as class A amplifier on low-level signals and see July 1953 CQ, P25

passes them to the next stage, V2, where they will be strong enough to produce some limiting action. If the incoming signal is very strong the grid of the input tube will draw current. Because of the series grid resistor the voltage at the grid cannot rise above the point at which the grid begins to draw current. The plate voltage is quite low on this tube and produces an additional limiting effect above a certain value of plate current. The next two limiter stages operate in the same manner as the first, with the exception that the grid circuits are provided with negatively biased shunt diodes. These diodes act to clamp the negative excursions of the signal waveform, the positive excursions being clamped by the rectifying action of the amplifier tube grids. As a consequence of the successive stages of amplification and limiting the discriminator will receive a constant amplitude signal even though the 85 kc input to the converter is varying over a very wide range. From almost minimum to maximum gain of the O5'er the oscilloscope shows that the limiter-amplifier produces relatively square waves of constant amplitude. To the large amount of limiting this converter owes its ability to print a signal way down in the noise or to print perfect copy without readjustment when the signal has climbed to 50 db over nine.

The purpose of the discriminator is to transform the frequency shifts into positive and negative d.c. voltages which, through the d.c. amplifier stages, key the teletypewriter machine. By making use of the double-tuned arrangement there was no need for a special discriminator-type i.f. transformer which might be difficult and expensive to obtain for the 85 kc frequency. All that is required are two 85



Rear view, Converter chassis kc i.f. transformers from a *Q5'er*. These are tuned about a kilocycle above and below the 85 kc i.f. frequency. When the discriminator stage has been properly adjusted it will produce, just as in any other FM discriminator, zero output voltage when the signal input is at the 85 kc center frequency and positive and negative output voltages when the signal varies above and below this frequency.

The next stage is a cathode follower triode serving to isolate the load of the driver from



Panel, RTTY FSK Converter


the discriminator. The driver, with its bias control and its plate circuit voltage-divider, furnishes a means of correcting for lop-sided keying signals, whether caused by unsymmetrical conditions in the converter itself or originating at the transmitter through faulty adjustment. The driver for the output stages is picked off the driver plate voltage divider at a point at which approximately equal positive and negative voltage swing is observed with respect to the driver cathode. The location of this point may be determined with a voltmeter while alternate mark and space signals or the repeated letters "RYRYRYRY" are being received.

Two output circuits are provided, making the unit very flexible. The circuit providing polarized DC output can be utilized to operate a printer of the style having a polarized selector magnet without a retracting spring or a standard Model 12 teletypewriter. The Model 12 is normally used in conjunction with a polarized relay. The polar output, derived from V11 and V12 may also be connected directly to a polar telegraph line in emergency relaying of teletype traffic into wire-line circuits such as Western Union, Civil Defense, Red Cross, etc. The neutral output from V8 and V9 provides a "make and break" d-c current which may be used to energize other styles of teletypewriters such as the Model 400, 100, 26, 14, 15, etc. It may also be fed to a neutral Teletype line. Neutral lines are used where only a short distance is to be spanned. Both outputs may be used simultaneously, making it possible to operate several printers at the same time, key a wire line while monitoring the traffic on a local printer, or retransmit an incoming teleprinter signal on another frequency or another band. When only one of the outputs is to be used the other should be shunted with

a 200-ohm 1-watt resistor to maintain propoperation of the output amplifiers.


The polar output stage is arranged in sur a way that when one tube is conducting, t other is cut off and vice versa. When a ma signal is being received V11 will receive negative signal voltage on its control grid sufficient magnitude to cut it off. This caus V12 to conduct positive current through t polar output terminals. When a space signal received V11 will be driven into conducti. through a positive grid and pass current fro its -150 volt cathode to its plate to the pol output terminals through the two 820-ohm sistors. The voltage drop across the two resistors furnishes cut-off bias for V12. The direction current flow is the reverse of that caused by mark signal. Separate control of current flow the two directions is enabled by the individu 6V6 screen potentiometers. The two curren should be equal and within the range of 18 30 milliamperes.

The neutral output circuit is somewhat similar to the one just described. V8 will be drive negative when a mark signal is received, ju as V11 was, since their grids are connected together. V8, then, will cut off on a mark it put. The plate of V8 and the grid of V9 as tied to different points on a voltage divide extending from the minus 400-volt supply the plus 275-volt supply. These points, a voltages, are selected so that when V8 is confit the grid of V9 will go more positive with respect to its minus 150-volt cathode and will conduct. This permits current to pass from the cathode to plate, through the printer selected.



Converter chassis, bottom view

magnet or polar relay winding, to grounreturn. During a spacing signal V8 will conduct, causing the grid of V9 to go less positive than its mark value and, thus, to cut off. The neutral output current will be on for marand off for space. This "make and break" current can also be used to operate printering of the Model 12 and 21-A variety through a polar relay wired for neutral operation. The screen potentiometer of V9 is used to adjusthe output current to the standard value of 60 milliamperes.






Power supply, bottom view

The tuning of the discriminator should be performed only after all the power supply voltages have been adjusted to the indicated values and the limiter-amplifier has been checked. Being a double-tuned type no particular difficulty should be encountered. One may first tune both primaries and secondaries to exactly 85 kc and then tune one secondary to 84 kc and the other to 86 kc. The writer found this circuit easy to tune and very tolerant of adjustment with the transformers used Of course an attempt should be made to secure balanced output symmetrical with respect to the 85 kc center frequency. It is definitely not critical.

The output of the discriminator should be plus or minus 10 or 15 volts for proper operation of the d-c amplifiers. This is indicated on the panel meter at all times and serves as a constant check of signal strength, limiting action, tuning and discriminator operation. The same meter functions as the tuning indicator. Next the output currents should be checked and set at their correct values and then, while receiving signals, the driver bias should be adjusted with the potentiometer. The bias potentiometer should be turned in the negative direction until the printer locks up and stands idle without printing even though a strong signal is being received. This point should be noted or marked on the chassis and the control should be turned in the reverse direction until the printer runs open or wild, also unaffected by the signal. The permanent bias control setting is midway between these two extremes.





Rear view,

After careful alignment and tuning, operation of the unit is very simple. The FSK signal is located by means of the BFO, which is then switched off so that it will not interfere with the converter's proper functioning. From there on all tuning can be done by watching the discriminator voltmeter. Tune back and forth across the desired signal until the meter reading averages zero. Then turn on the printer motor and get that thrill that only an RTTY fan can get when he reads the results of a man's typing on a typewriter, perhaps on the other side of the world! By watching the meter, drifting of the receiver tuning can be compensated before it becomes serious enough to

cause misprinting.

The power supply is straightforward, consisting of an arrangement of standard circuits to obtain the necessary output voltages. The two unregulated and three regulated voltages are obtained from only two power transformers, one a 100 ma. unit and the other a 50 ma. job. The potentiometers permit setting of three of the voltages to the exact values. The plus 275 and minus 400 are not critical.

Addition of a switch to connect the discriminator output to an external audio amplifier allows the converter to be used as an excellent NBFM adaptor.

(photos by Bob Sturgess, W7AKW)



### Synchro Book

What do you know about synchros? Just as we thought, you are staggering along in the dark ages without a complete understanding of these amazing devices. They are available surplus for ridiculous prices and can do all sorts of things, "Synchros, Self-Synchronous Devices and Electrical Servo-Mechanisms" by Leonard R. Crow will repair this oversight on your part. It costs \$4.20 postpaid from the Scientific Book Publishing Company. Vincennes, Indiana. 222 pages, 171 illustrations, etc.



#### New Radio Handbook

Editors and Engineers have just brought out the fourteenth edition of their Radio Handbook. This 766 page book is a must for every ham shack. Edited by Bill Orr, W6SAI, it covers just about every phase of ham radio. A monumental work. This is not a run of the mill "handbook" built out of reprints of magazine articles. Like construction articles? There are hundreds in this book. Grab it from your local dealer for \$7.50 or send to Editors and Engineers, Summerland, California (add 10% for direct orders).



Free Swap & Shop Table, partial view. Hamfesters bring gear for sale or trade, display it here.

# Good Day

## at Starved Rock

Wow! We knew that if people are having hamfests all over the country, somewhere someone must be staging a Super-Hamfest, and it looks like this might be the one. For the tenth year running, the Illinois' Starved Rock Radio Club will hold forth, this year at the C.I.O. grounds at Ottawa, Illinois, where last year's attendance exceeded all previous years with about 4000 guests, of whom 1500 were licensed amateurs! Hams from 9 states and Nova Scotia showed up for the biggest, fun-havingest hamfest in Starved Rock history.

The secret of the tremendous popularity of the Starved Rock Hamfest? Who knows? Maybe just the right combination of club spirit, location, experience, and people remembering what a good time they had last year coming back, bringing friends. Anyhow it's off the ground now and flying high, with this year's 'fest scheduled for Sunday, June 3, with the usual games and entertainment for the whole family plus technical sessions on Beams, SSB, RTTY, etc. with a goodly group of well-known hams presiding. And Door Prizes, of a quality and quantity to hoist many an everyow

and quantity to hoist many an eyebrow.

From 9 a.m. registration til darkness breaks things up about 9 p.m. Picnic style, or food and refreshments available on grounds, with free coffee and doughnuts for early comers, til 10 a.m. Unboredom guaranteed. Go see. Find out. Or, if you're too far off, why not see what your club can do to match the success of the Starved Rock gang?



Non-Cinerama view shows only a part of the picnic area, playground facilities.



Stunning mobile rig belongs to W7VUR, Arizona visitor in '55.



Bob Adams, K2DW

245 Revere Road, Roslyn Heights, N. Y.

This month we inaugurate our SINGLE-SIDE AND column. SSB popularity, world wide, as rapidly increased to a point where we believe it warrants this recognition. There are ow FIFTY countries with SSB operation. We elcome the following newcomers: JA1ACB, S6CW, CP5EK, OA4CL, ELØA, KX6NB, R2CG, VS6CW, VS6BJ, VS6BE, VU2RC, P2CR and CX5AF. Quite a juicy list, eh? Empty' of ZS6KD made it 40 countries when the contacted CX5AF.

Many old timers who had lost interest in the battle of the heterodynes" have found relewed interest in SSB. Among these are Bill Talligan W9AC, Fred Schnell W9FZ, Ronnie Durham W5ATB, Tom Davis WØSW, George ailey W2KH, Bill McGuire W1IF, and Harey Sampson W2IJL. The huge success of the lixth Annual Single-Side Band Dinner, held farch 20th in New York attested to the poputrity of SSB. From Cyril, VK3AEE we learn nat the following 'sidebanders' are active on 0 down-under: VK2 VA, DQ, ZF, AC, IU, VK3WR, AEE, VK4VJ, CC, AB, P, L2KW, GL, AG, IA, ZL3IA, AR, and L4FO. We welcome Joe ZD4BF with his big ignal, from a new QTH on the Gold Coast.

We are happy to see South American acivity increasing. For a long time 'Corny' (V5FL was the only station in South America or WAC-SSB. Peter of OZ3EA reports over 0 SSB stations active in Denmark, mostly on '5. SVØWA, PAØIF, HB9FU, I1BAO, F8RQ, AP2BP, and KT1DD are keeping their repective countries active. It is amazing to hear

so many "bare" exciters of 10 to 20 watts making 'Q5' DX contacts. Reggie Tibbets of W6ITH flew a kilowatt side-band rig from California to Marigot, French St. Martin, and operating as FS7RT gave hundreds of hams a new country. His QSL is a beauty. Side Band is showing its superiority in the hundreds of phone patches placed through KC4USA at the South Pole. Art Collins WØCXX installed a SSB rig in an Army plane and flew across the Pacific to Japan, maintaining reliable and consistent contacts with his home base. QSOs were made with hundreds of hams while enroute.

Germany is well represented with fine signals from DL4RM, MW, WX, SX, EW, ZM, CX, YU and DL6WL.

Harry, W2JXH who was first SSB to WAC now has 38 countries without a beam. To really appreciate SSB one should listen to mobile W8DLD, W2EWL, W2ICA and W2ALZ 'breaking' kilowatts in South Africa while in motion.

Many fine QSOs are being made on 15 meters and ZS6KD reports a 5 continent round-table. He anticipates a WAC round table is only a matter of time.

The 75 meter gang continues to grow, and while many are moving to 20 for the Summer period, one never is lonesome on 75. One point of concern by your conductor is why the SSB activity is confined to a relatively few KC on the band edges. We hope you liked this first attempt and that you will send along news and information for our future columns.

73, Bob; K2DW



Helen Hargreaves, fresh out of radio school in 1929. She obtained first-hand experience operating aboard ferries crossing Lake Michigan during 7-hour run between the radio school and her home. Now Helen Cloutier, she is W8GJX.

man's job—that of radio operator, or "sparl From the time the first "sparkette" sailed 1910 to the present day, fewer than the women have held this job on ships flying United States flag—and half that number w WAC's on wartime duty. To all these operators goes credit for being real pione in a field traditionally masculine.

#### Pioneer Girl Marine Operators

In one chapter of his book "SOS to the Rescue," Karl Baarslag has recorded expendences of some of the earliest girl marine raction operators during the years 1910-1929. So of the following details are from this book.

In the year 1910 Miss Graynella Packer I came America's first woman marine operate. She had some Western Union experience, a applied for a position as wireless operator withe United Wireless Co. Officials were skeptic—a woman operator was unheard of. But

# YL Marine Radio Operators

One evening not long after World War II had ended in the Pacific, the U.S. Army Hospital Ship Chateau Thierry slipped quietly into the lagoon at Eniwetok. As she took her place among the many warships, the radio operator on duty contacted the shore station by blinker. After completing the ship's business the shore operator queried by blinker, "Are you WAC's?"

"Yes," came the blinker reply from the Chateau Thierry. Instantly 150 ships moored in the lagoon, whose operators had been "reading the mail" were furiously blinking for a contact. The three WAC operators aboard the Chateau Thierry spent the remainder of the night at three blinker stations in QSO with the OM ops on other ships moored in the area. Some of the fellows had been in the Pacific nearly two years. After establishing home state and city, the next question from the lonely GIs inevitably was, "Are you blonde or brunette?"

Such is the reception that has been met by the girls who have gone down to the sea in a Louisa B. Sando, W5RZ Jicarilla Apache Indian School

Dulce, New Mexico



Mabelle Kelso wearing headphones outside the radio room aboard the S. S. Mariposa, on which she was radio operator during the summer of 1912.

<sup>\*</sup>This book is out of print but copies may be obtained on inter-library loan. Another maritime book available from your State Library Extension Service is "'CQ,' or in the Wireless House," by Arthur Train, published in 1912. The author had little regard for Hams, but nonetheless it's quite a fascinating novel of the high seas.



Billie L. Adels, W4CJV, ex-W6HBO, veteran YL maritime radio operator, in eight years at sea served aboard two Norwegian vessels and several flying the U.S. flag.

Atlantic coastwise passenger line felt that a "wireless woman" might be good publicity. As yet no government license was required and after short training with the chief operator at old station "NY" atop 42 Broadway in New York, Miss Packer got the job of "sparks" on the S.S. Mohawk in Nov. 1910.

Men operators aboard other ships accepted her graciously and helped her in every way they could. But the news spread fast—a woman wireless operator—and Graynella was in her glory. Newspaper reporters and writers besieged her and Graynella was a bit incautious in endorsing radio as a profession for women offering travel, good pay with light work, romance. The old marine ops didn't like this. Women had already taken over many of their jobs when the telegraph operators had been out on strike. The men had taken to the sea—and now girls were going after even these jobs. The men who had been so willing to assist her in the beginning became indifferent. Others when transmitting to her "burned up the key" at speeds she couldn't copy, and profanity over the air became thicker than ever. Graynella left the sea in April 1911.

Out on the Pacific coast the first woman to go to sea as ship's operator was a Miss Tucker who in 1911 sailed out of Seattle on the S.S. Indianapolis. Also in 1911 Miss Edith Coombs was in charge of the S.S. Roanoke's radio on the Pacific. At this time Congress was drafting legislation to force all U.S. passenger ships to carry radio equipment. The question arose whether a woman operator should stick to her key, while a vessel sank, or hold out for the old rule of the sea—women and children first. Edith said to just give her a chance, she would stick to the ship, but she had no occasion to prove it while she served.

In June 1912 Miss Mabelle Kelso shipped as radio operator aboard the S.S. *Mariposa*, an excursion boat plying between Seattle and Alaska. Mabelle had studied Morse at the Pittsburgh Technical College in 1908 and after graduation had worked in a Western Union branch office for six months and later for Postal Telegraph.

On the Pacific Coast she found United Wireless had decided to accept two girls to study wireless. They had many applications but no others had Morse experience so they put Mabelle in the class with the men. There she learned the Continental code and studied

U.S.A.H.S. Chateau Thierry, one of four U.S. Army hospital ships on which WAC radio operators served during World War II.





These Norwegian girls were pupils in the radio class graduating in June 1954 from the Bergen Sjomannskole (Bergen Nautical School). The one at the right was only 17. Their instructor comments all of them are sweet girls.

the apparatus sufficiently to be able to make minor repairs at sea. On graduation Mabelle went to the Bremerton Navy Yard, where a lieutenant of the U.S. Navy gave her the usual examination. At that time no formal licenses were issued, only a Certificate of Skill in Radiocommunication. Mabelle was told at the time that her certificate (dated June 6, 1912) was the first license ever issued by any Government to any woman to operate wireless.

Mabelle served on the *Mariposa* until Sept. 1912 when Marconi bought United Wireless and refused to allow women to operate aboard ship. Marconi took her into their land office in Seattle where she handled all messages from all their ships, transmitted from the station in the University District to the downtown office over a buzzer, kept the books, and did stenographic work. She stayed with them for a year, but they did not pay the salary she could make in other fields.

Mabelle says she enjoyed the wireless work very much and intended to make it her life work, until Marconi ended her dream. Shortly after she left the *Mariposa*, the Titanic disaster occurred in the Atlantic. As a result of the investigation which followed, all radio operators certificates were cancelled and 1st, 2nd

and 3rd grade licenses issued.

She at that time was in the Marconi land office and rather than be left without a license, she returned to Bremerton Navy Yard, took another examination and in Feb. 1913 obtained a First Grade License, one of the very first women to hold such a license. (This was issued by the Department of Commerce and Labor.) In 1917 Mabelle married Lt. James Shaw and since 1924 she has worked as a doctor of chiropractic.

In 1912 Mrs. H. E. Soule, wife of the master of the S.S. Windber, acted as radio operator on that ship after attending radio school for three months and securing her license. The Windber was in the Alaska canning trade and carried passengers, so radio equipment

was required.

Several girls have seen service on the Great Lakes. In 1913 Miss Margaret King spent some time on the S.S. Eastland (this steamer two years later overturned with a loss of 815 lives). A Miss Mason was on a Lake Michigan ship in 1918 and in 1919 a Miss Welch was operator on the passenger vessel Seeandbee.

Back on the East Coast there was a Mrs. Frank Chambers who went to sea in the early days from the Port of Philadelphia aboard the old Merchant & Miners Line ships. W2ZI adds that her OM Frank made some of the prettiest spark gear of that time down on 7th St. in

Philly—this was about 1910.



One of fourteen WACs who served on U.S. Army hospital ships during World War II, Sgt. Alice Loree is shown in blinker contact in Avonmouth River area, British Isles.

In 1917 a Miss Du Val obtained a commercial license and her ambition was to work in a Navy Coast station. Unable to get this position she was given a trial on the S.S. *Howard*. War came, however, the Government started taking over the ships and commercial operators were replaced by Navy men, forcing Miss DuVal to leave the sea.

#### First Girl to Send SOS

One girl, at least, stayed with her ship as radio operator during World War I. Miss Lena Michelson shipped out of New Orleans in March 1918 on the tanker *Tamesi*, which her father commanded. Seven months later, on Sept. 16, 1918 the *Tamesi* went aground on a bar off Texas in a heavy fog. As it was being ground to bits on the rocks Lena's dad gave her the order to send an SOS—so Lena Michelson became the first woman to send out the sea's call for help. Her SOS was picked up by station NBK at Galveston, but by dumping their oil in the Gulf, the *Tamesi* washed free and made shore under her own power.

Lena stayed on her dad's ship throughout the war and later transferred with him to another tanker, the Eugene V. R. Thayer, where she worked for five years. This gave her a total of eight years as a seagoing radio operator! Well liked by the marine ops, Lena was skilled operator and knew all the facets of er trade. When she came ashore in 1926 she ecame assignment clerk with the Radiomarine torp.

In 1929 on the Atlantic Coast Mrs. Elizaeth White served for three months on the S. Trimountain, of which her husband was

laster.

In this same year Helen Hargreaves (now Ars. Cloutier) was attending radio school in rankfort, Michigan, across the Lake from Ianistique, her home town. The chief of the adio school also was chief radio operator at ne main land station for the Ann Arbor Carerrys and all students going to his school got rst-hand experience. Most of the radio operaors aboard the fleet of ships were students and raduates of this school. On weekends, when Ielen went home—a seven-hour run across he lake—she helped the fellows with their vork, reports and ship-to-shore traffic. This vas the era of "blue bottles" that lit the entire oom when one closed the key. Helen did not nake radio her lifetime profession, but she vent on the air as an amateur at the same time nd has been on the air ever since 1929, her resent station call being W8GJX.

The only other girl to have been assigned s radio operator on Great Lakes vessels was

n Alice Joyce who served in 1942.

#### World War II Operators

The feminine radio ops who found such an inthusiastic welcome among the operators on varships at Eniwetok were three of fourteen VACs who sailed as marine radio operators on Army hospital ships during World War II.

Toward the end of 1944 the U.S. Army bicked a group of WAC radio operators to be rained for duty aboard Army hospital ships.



Since the women's services were on non-combat status, WACs were ideally suited to serve aboard hospital ships because there were other women aboard (Army nurses), the ships travelled under the Geneva Treaty as neutral vessels and were therefore unarmed and fully lighted at night.

In order to qualify for this assignment a WAC had to attend a special Army school in Brooklyn, N.Y. where she unlearned all of the procedures in which she had been trained as an Army operator, and learned regular peacetime commercial procedures. She also had to attain a code speed of 35 words per minute and be able to send and receive blinker signals at 12 WPM. In addition she was trained in servicing batteries, the use of lifeboat emergency equipment and other duties peculiar to ships at sea.

Radio operators on Army ships during the war were all enlisted personnel, most of them held ratings of Technician Fourth Grade or better. The fourteen WACs who sailed as marine radio operators on Army hospital ships were: Lucy Alter, Elaine Corrum, Katheryn Barnes, Lillian Browning, Del Kumnick, Terry Mezzanotti, Paula Sanborn, Bernadine Kurtz, Esther Given, Alice Loree, Lorraine Hand, Regina Rice, Rose Landrey and Virginia Kidd.

The first group of three girls sailed in Dec. 1944 from Charleston, S.C., aboard the U.S. Army Hospital Ship Louise A. Milne. Other ships on which the girls served were the U.S.A.H.S. Ernestine Koranda, Jarrett M.

Huddleston, and the Larkspur.

Sergeants Given, Loree and Hand were assigned aboard the U.S.A.H.S. Chateau Thierry, a converted transport which was equipped to handle between 480 and 500 patients in addition to some 400 crew and medical compliment. The ship sailed from Charleston to Bristol (Avonmouth), England, early in 1945. Esther Given has related some of their experiences.

For this first trip, two of the former ships operators remained aboard to act in advisory capacity to the "sparkettes." The chief operator's first official statement to the girls was that a "spark" stood his/her four-hour watch regardless of mal-de-mer and that he and the other operator were just going along for the ride on this trip. The girls were expected to take over fully; however, the men would be there in case of dire emergency. (It was later discovered that the two men had worked out a schedule between them so that they would be able to stand 24-hour watch when the ex-

At the close of World War II, with a shortage of men, Sgts. Given, Loree and Hand received discharges from the WAC and then signed aboard their same ship, the Chateau Thierry, as lieutenants in the Army Transport Service. Here Lt. Alice Loree (left) and Lt. Esther Given (W6BDE) wear their new uniforms in their Civil Service status.

periment of having women as radio operators failed!) Much to the credit of the gals, they proved to be equally as capable as the men

operators in their assignments.

No indoctrination could be more wicked than that of landing on a new job assignment in entirely foreign surroundings as G.I. guinea pigs (with two strikes against them for being girls), plus the added feature of the elements brewing up a juicy North Atlantic storm for the event. The first two days were pure misery for the girls, two of whom were prairie raised and had never before been aboard a ship. Each



Copy of operator's Certificate of Skill in Radiocommunication issued to Mabelle Kelso June 6, 1912. Mabelle was told that this was the first license ever issued by any government to any woman to operate wireless.

This extificate is notify for two years, subject to suspensions as accordation by the Bacustany of Commesses and Rober to assess. At their Dis host tolers is son the chorus to offices of the custome as other offices of the Question and the distribution of the Question and the Commesses and the custome as affects of the Commesses and the custome as affects of the Commesses and the custome as affects of the Commesses and the custome as a continuous and the custome as a contin

4-hour watch was an eon of sitting with "cans" on the ears copying press at 30 WPM for the skipper's morning news, with a bucket clamped tightly betwixt the knees. By the second day it was obvious that something had to give, and it was not about to be the girl guinea pigs, so it would have to be the bucket. Thus ended the mal-de-mer session.

Among duties of a radio operator aboard ship is the care of batteries and emergency distress equipment in the lifeboats. Probably the most tedious job for the gals on hospital ships was this particular duty. On the *Chateau* 

Thierry two lifeboats containing such equiling ment were slung some 30 feet above the de and had to be serviced each week. A long tension ladder was placed against a bow which ran parallel to the swinging lifebol The operator climbed to the top of the ladd straddled the boom and waited till a list of ship swung the lifeboat near enough to jun in. All the time the op was holding a can distilled water and a hydrometer. The on change in the descent was that the hydror eter and water can could be lowered to 11 deck by means of a rope, but the problem getting back on the ladder was greater this that of getting into the boat in the first place It was no help when a full audience of amb latory patients was on the deck below givi advice and yelling "Woops!" and "Look out at tense moments.

On one trip from England en route Charleston, with all the lights ablaze, as a quired by the Geneva Treaty on a neutral shi a voice came booming out of the depths night, "Turn off your lights and stand by we'll blow you out of the water!" The hospit ship had sailed straight into the center of Canadian convey and was silhouetting each their ships to any enemy who might be scoutin about. Needless to say the lights were turned out and the ship stood by. Next morning who light came the hospital ship stood alone the middle of the Atlantic with no sign of the hundreds of ships she had unknowingly jeor ardized the night before.

During the War radar was considered "weapon" so hospital ships could not b "armed" with such navigational aids. As soo as the War ended, however, all these ship were immediately fitted with radar equipmen

At the close of World War II Army opera tors were replaced by civilians on Army ship as quickly as possible. When the *Chatea Thierry* came into port in San Francisco i Dec. 1945 the WAC operators were informed they were to be replaced. At this time each of the girls had sufficient points for discharge from the Army and the San Francisco port of embarkation was having a hard time finding enough civilian operators to fill these vacated posts. After several contacts between the Signal Corps, Water Division and the powers in Washington, it was arranged that the three girls could sail as civilian operators if they sailed together on the same ship and were the full radio complement aboard. Next day the WAC's went to Camp Bealle, Calif., received their honorable discharges from the WAC as sergeants, came back to San Francisco and signed aboard their same ship as lieutenants in the Army Transport Service as civilian operators on Civil Service status.

No uniform had been designed for women in this capacity. A quick trip was made to purchase Navy nurse uniforms, Army Transport insignia and white shirts. Being Army terans with ribbons from many theatres of cupation, these gals made quite an impresse sight. Once in Honolulu a shore patrolman d to be shown Army discharge papers, ship's pers, Coast Guard identification, et al, bere he was convinced they were not impernating officers of the U.S. forces!

Most of the fourteen girls have married and ntacts have been lost, but none of them will er quite lose the feeling of challenge and rvice that was theirs as liaison between a ercy ship and the rest of the world. One at ast, Esther Given, so enjoyed the radio work at she obtained her amateur license and since

146 has been on the air as W6BDE.

Another YL, Gladys Goff, W9EKS, served board two ships on the East Coast. She was hed up to go aboard her third ship when a rike delayed the sailing. Then she chose a bastal station, WPG in Norfolk (no longer in sistence), in order to get more experience. '5MET ex-MM, who worked her, credits ladys with swinging a "mean bug" on 500 kc.

#### W6HBO/MM

Although Lena Michelsen holds the record or women marine operators on U.S. ships ith her eight years at sea, Miss Billie L.

dels is a close runner up.

It all started for Billie by accident during Vorld War II. At this time she was taking a re-medical course at the University of New Jerico, but her eyesight would not permit her continue her intensive studies. Returning to er home in San Francisco, Hawaiian-born stillie (she also has spent several years in australia) decided to work in a war industry. While waiting at an employment office she officed an opening for a stewardess on a Norwegian ship, and got the position.

At this time on Norwegian ships girls were beginning to take over the work of radio operators, so the skipper talked to Billie about the Back at the Pacific Radio School for three nonths Billie obtained her license and in Dec. 945 sailed as radio operator on the Norwegian ship M/S General Ruge. In 1946 she operated aboard another Norwegian ship, the

M/S Hoyanger.



The S.S. Gulf Banker was home to Billie Adels for 4½ years on voyages through the Caribbean.



QSL card used by Billie Adels, W6HBO/MM, while aboard the S.S. Gulf Banker.

Billie's first American ship was the S.S. Edward J. Berwin, and at this time she was the only American woman to serve as a regular

seaman on a U.S.-flag freighter.

In 1948 Billie sailed on the Liberty ship S.S. John Gibbon. The ship left Philadelphia the day after New Year's and, as Billie tells it, hit a whiz bang of a storm, which washed two men overboard. Both men were rescued, one being washed back on the ship and the other was finally pulled back after they found they could not launch the one lifeboat left (the other was mashed by a good-sized wave), this one being frozen in the blocks and immovable. Then the cargo shifted, an all-coal cargo for Antwerp. They got into Falmouth, England, with a 14-degree list.

Billie describes the *John Gibbon* as having no "belly band" and on the way back it developed more and more cracks. In the Bay of Biscay they hit a 75-mph gale, the telemotor went out, and the ship rolled helplessly. By 11 p.m. Billie was called to stand watch. Souping up the main transmitter as high as it would go, Billie waited with bated breath for instructions to send an SOS. Lifeboats would have been useless. Luck was with them; the steering gear was fixed and they battled their

way through the storm.

On Sept. 7, 1948, Billie hit the front page of Hong Kong's China Mail with the headlines "Pretty Blonde Does Work of Two Men." As radio operator and purser of the 2,127-ton freighter Union Carrier, Billie was the first American girl to visit the colony in her capacity. This ship, formerly the Hickory Ghyll, was one of seven Victories which the U.S. had transferred to the Chinese National government. American crews sailed all the ships to Chinese ports.

Billie had some novel experiences on this ship. On the first pay day the 22 men in the motley crew crowded her office, peeping over each other's shoulders to have a look at their new purser. Billie shooed the men down the

[Continued on page 101]



Walt, W8ZCV, listens as John Reinartz explains some of the finer points during Novice-Tech forum.

# The 1956 Hamvention

The fifth annual Dayton "Hamvention" was held on April 14 at the Biltmore Hotel in Dayton, Ohio, with a larger-than-ever attendance and many interesting speakers and exhibits dealing with all phases of amateur radio.

Capt. John L. Reinartz, U.S.N. (ret.), K6BJ, was the main speaker at the evening banquet, which also featured a prize drawing at which W8GVE, Howard Reichle, Bedford, O., captured the headline prize of a Hammarlund PRO-310.

Now, these two paragraphs might be said to be a report on the Dayton "Hamvention"—

but let's explore and examine.

Actually here is a one-day meeting of hams that brings together more than two thousand licensed amateurs and their friends, whose list of exhibitors reads like a Who's Who of the manufacturers and wholesalers, and whose speakers really do come from the top names in communications, electronics and the associated fields. The registration lists hams from every state, Canada and Alaska, and often real DX calls appear.

To make such an affair possible, the Dayton Amateur Radio Association begins work on each succeeding Hamvention almost as soon as the last prize is distributed at the big banquet (in fact, even before, for the dates for these meetings must be established a year or more in advance). The General Chairman is chosen within six weeks after the yearly event, and he in turn chooses his committee heads within a short time, and the wheels begin to turn.

Leading the parade is the Arrangements committee, which is the actual liaison between all Hamventon committees, functions, and the hotel staff. This group is hard at work months before many other groups swing into action. Perhaps the next most important factor is the

setting up of the program theme for the affair and choosing representative speakers. Her again, the Program chairman and his cohort begin their efforts long in advance, and after comprehensive meetings with the committee at a whole.

In succeeding sessions, the committee carelfully screens all phases of the operation, and since each chairman is picked for a particular job, (there are no overlapping or dual appointments made), in due time the Hamvention takes shape.

The effect of all this preparation and planning can best be realized by a comparison of the first Hamvention in 1951, and the '56 Hamvention just concluded. From an attendance of approximately a thousand, the registration has shown a steady growth to twice that number, and probably several hundred could be added if the attendance in the hotel were limited to ticket holders only. In looking at the



Editor of obscure amateur journal addresses multitudes assembled at the Hamvention Banquet.

panquet, we see a gain of from around six hundred to a crowd of more than a thousand which taxes to its utmost the capacity of the two ballrooms used as the banquet site.

Also witness the expansion to a registration and gabfest on the evening preceding the affair, at which time most of the convention's



This shot during the early hours as the registration desk was in full swing.

exhibits are on display, thus permitting extra time for visitors to meet old friends, see the newer gear, and have a clear slate for the sessions which begin in the early morning and continue until late afternoon.

Nor have the ladies, XYL's and YL's, been forgotten. It has been the custom to provide entertainment for those hardy souls who are beset by the rigors of our hobby, but with the 1956 Hamvention came a program planned especially for them, and a YL forum moderated by our own Betty Hall, WN8AXA which had as speakers several of the leading YL operators from the area of Ohio and neighboring states.

The morning sessions heard Merten, K2AAA, tell about the new rig, the world's smallest KW; W8HOX was moderator for the session that enjoyed Wes Schum, W9DYV,



Hamvention Chairman Rudy Plak confers with committee heads Gunston, McNutt, Rineer, and

and Ernest Pappenfus, WØSYF, expounding on those ideas which make SSB "more better," as it were. And while the SSB lads were enjoying their session, Walt, W8ZCV, held forth with a forum at which John Reinartz, K6BJ, in his inimitable manner, spoke of Instrumentation in the Hamshack. This was scheduled as a Novice-Technician meeting, but seen leaving the session were many, many holders of the higher class tickets.

Following the lunch break, Hamventioneers first heard Fritz Franke's talk on modern receiver design, then followed Lew McCoy with "Causes and Cures of TVI." To round out the afternoon, W8SVI, Bill Ingling, conducted a well attended VHF forum with Paul Wilson, W4HHK, and Bob Rafuse, W1RUD, sharing the speaker's rostrum.

The final session was the ARRL forum led by Jack Brabb, W8SPF, at which League affairs were taken up by Bob Davis, W8EYE, Dana Cartwright, W8UPS, and Wilson Weckel, W8AL.

The program for the day began for the ladies at 8 in the morning with a coffee hour, followed by conducted tours of the Hamvention, and a musical program produced by one of the Dayton Junior Achievement groups. Following the noon luncheon, the ladies heard a talk on "History and Romance of Lace." Then entertainment of various types was pro-


[Continued on page 120]




Scene at prize booth during the day. Winning numbers were drawn after each session, then returned for main prize drawing in the evening.



# licensed hams... GQ's growth tells the story



PAGES OF ADVERTISING IN CQ PER MONTH (Average for 12 month period)



TOTAL PAGES PER ISSUE IN CQ (Average for 12 month period)

• СФ • June, 1956

# More than 56% of these hams read --

# CO RADIO AMATEURS' JOURNAL

#### HERE'S WHY:

- ★ CQ is for active Hams, edited by active Hams.
- ★ CQ usually carries more technical and construction articles than all other amateur magazines combined.
- ★ CQ's readers number the most active Hams in the world, eagerly keeping up with the newest developments.
- ★ CQ is independent and constantly growing.

These outstanding features have built CQ's circulation to an all-time high in excess of 70,000 active Ham readers. Surveys show that more than 45,000 of these Hams read no other Ham magazine.

Today CQ is the buying guide of the amateur industry. If you have a product for the Ham, you'll sell it faster through

CQ, the Radio Amateurs' Journal

# Antennas Are Easy

Wayne Green, W2N Editor CQ

Being lazy, that is, wishing to accomplish each purpose with a minimum expenditure of energy and money, I have been using folded dipoles on most bands ever since the advent of twin-lead. Little brown ribbons cut for two, six, ten, twenty, and seventy-five meters have been draped all around the house and environs

off and on for over ten years.

A wee mite of sales talk might be in order in case you are inclined to sneer at the old dipole. Granted that for permanent use a beam is a valuable asset, however, even on the VHF bands the folded dipole can be made and hung up in a few moments and well serves as a first antenna for tooling up on a new band. It will do a pretty good job for you too, as I found out many times on two meters and six meters (where I worked California with only 10 watts). On ten and twenty meters you can




Figure 1

(with reasonable power) work about anyth on the band except during the DX Conwhen it is best to plan for a short vacati

On seventy-five meters your folded dip will give you a better than even start with majority of stations since they tend to try load up plain dipoles and various lengths wire. Beams are seldom found on this ba (WIFZJ excepted). Operating from the mid of Flatbush, Brooklyn, using 75 watts on meter phone I have worked all states a twelve countries. With higher power this been raised to a total of 40 countries on meter phone, including Japan, South Afri and New Zealand.

Neglecting for a moment the fine perfor ance of the folded dipole let's examine son of the other factors that are important in t selection of an antenna: cost, ease of erection directivity, ease of feeding, and ease of a justment. Perhaps I loaded that list unfair for as it stands the folded dipole wins han down. Costwise you can generally figure th the antenna will cost about 51/2¢ per met wavelength plus \$2 for the feeder. The who thing shouldn't take over a half hour to med ure, cut, erect, and test. Allow one more ha hour for tuning it exactly. It is by far the easiest antenna to feed from the transmitt since it requires no antenna tuning netwo and can be linked directly to the final tar coil. Pi-networks work well too. The adjust ment procedure, a very simple process, will I covered later.

#### The First Step

Since the folded dipole works well only of the band it is cut for it is well to make some sort of decision as to the bands you want use and put up a separate antenna for each band. A second antenna frequently comes i handy if you want to operate the receive while transmitting. Figure 1 will give you th approximate lengths of the antenna for th various bands so that you can go out and survey your house and trees for likely antenna hanging places. The ideal is two trees suitabl.

7.2 MCS.

far apart, though it is possible to hang the antenna from a tree to the house. Try to have the center of the antenna as near to the radio shack as possible so as to keep the feeder short. This saves both money and r.f. If you look hard enough you will generally find at least one good antenna location. I have operated 75 meters from nine different locations and in every one been able to put up a folded dipole in a matter of minutes. There is almost always a way if you really want to put one up.

Pace off the distance between the trees and estimate the height of the trees so that you can make a good estimate of how much rope will be necessary for the ends of the antenna. Estimate too the length of the feeder from the

center of the antenna to the shack.

#### **Buying the Materials**

Add the length given in Figure 1 to the estimated length of the feeder, being generous to make sure you will have enough feed line. Buy a good grade of 300 ohm television receiving line, being careful not to get any of the 1¢ a foot stuff or twin-lead with the solid wire conductors. The wire should cost about 3 cents a foot. Other materials that will be needed are Itwo antenna insulators for the ends of the antenna; these should cost from five to ten cents each and may be of porcelain or glass. The center insulator is the Mosley type 261 Dipole Connector and costs about 35¢. Unless you are well insured it is a good idea to invest in a lightning arrester which will cost a bit lover a dollar. Buy some plastic television line standoffs to hold the feeder in place: 5¢ each. The only remaining item is the rope for the lends of the antenna. If you have some extra clothesline around that will do a good job. Lighter line will do though, just be sure that it looks strong. I prefer 1/4" sisal line which it looks strong. I prefer 1/4' sells for as little as 1¢ a foot in some places. Buy plenty of line so that the rope can be passed over one of the top branches of the tree and then brought down and tied near the ground. In one of my locations there was no nearby handy tree so it was necessary to run about a hundred feet of rope to one end of the antenna. In addition to the rope for the antenna buy a roll of light twine which will serve as a throwing line to start the heavier rope over the tree.

Let's add that up for the 80 meter antenna and see what the total cost will be:

Automo wino	4.20	140 feet
Antenna wire		
End Insulators	.20	2
Center Insulator	.35	1
End Rope	2.00	200 feet
Throwing Twine	.50	200 feet
Feeder Wire	1.80	60 feet
Feeder Standoffs	.20	4
Lightning Arrester	1.00	1
Total	\$10.25	d

#### Hoisting the Antenna

The length of time that your antenna will stay up depends upon your care in putting it together and the neighbors' kids. A surveyors tape is handy to have around for measuring the antenna length, but who has one? Next best is to measure off, say, three feet on the side of the house to use as a measuring stick. Measure one half of the antenna and then use that half to measure the other half. Cut off the excess twin-lead and use it for the feeder. To attach the insulators to the ends of the antenna split each end for about three inches and strip the insulation for 34". Feed the two split ends through the hole in the insulator in opposite directions, cross the stripped wires and twist them. Later, when you have the antenna cut exactly to length, you should Solder the twisted end quickly so that the insulation does not get too hot and peel back from the wire. This makes an end connection that will last for years. Next put in the center insulator and connect the feeder.

Tie a weight to the end of the twine and pay out the twine on the ground, keeping the end in your hand or under your foot. Most




Figure 2

normal size trees can be conquered in this way, taller trees may require special equipment such as a bow and arrow or a gas filled balloon and .22 gun. On most trees it is best to pick a good sturdy branch and swing the weight over that. Two or three trys should do it, if not, call your son, you're getting old. With real thick trees it will be simpler to just throw the weight completely over the tree and let the rope do the branch finding. Tie the rope to the twine and pull it through. Allow enough rope on each end of the antenna so you will be able to lower the antenna to the ground for tuning. If you cut it off short when the antenna is up in place you will have to splice to it later when you want to work on it. Put up the other end of the antenna in the same way and pull the antenna up into the operating position.

Several factors influence the resonant frequency of an antenna. Such items as height and ground coefficient make the exact calculation of the length of an antenna impossible without a test in its actual operating position. All of the lengths in *Figure 1* were made a

[continued on page 92]



Guy Slaughter, K9AZG. P. O. Box 192, Crown Point, Indiana

# Signal-Separation

for us peasant types

While the Q-Multiplier has been around for quite a few years now, and has received a bit of publicity from time to time, it doesn't seem to be particularly well-known in ham circles. And that's a shame. Because it is capable of converting a so-so receiver into a really good performer.

So far as the average ham is concerned, there are two kinds of receivers: those he'd like to own, and those he can afford. The experienced ham knows, and the novice soon learns, that while sensitivity, stability, adequate bandspread, conveniently-grouped controls, and relative freedom from drift aren't necessarily expensive items in today's receivers, selectivity is.

Particularly to the novice trying to work his crowded bands with his hundred-bucks-special, this one shortcoming of inadequate selectivity is enough to condemn a moderately-priced receiver as unusable. (A Novice, for the record, may be here defined as an amateur operator who is currently considering hocking the family furniture in order to buy more radio gear; a General is one who already has.) But by the simple and inexpensive expedient of adding a Q-Multiplier, that hundred-bucker can be transformed into a competent signal-separator.

Until recently, a commercial Q-Multiplier cost somewhere in the twenty-five to fifty buck region. Now one can be had, in kit form, for a hair under ten. So for a sawbuck and an evening's work, we peasants with our poor-man's

receiving gear, can henceforth tune the bands with nearly the same QRM-lessness as can our aristocratic brothers sporting their Super-Meteor-Specials.

Here at K9AZG, our problem was typical of our poverty-stricken peers; we had invested \$75.00 in a second-hand Hallicrafters S-40B, and found we had a good hot receiver, stable, sensitive, and easy to tune. But there was the usual catch: any two signals of comparable S



The first phase of surgery calls for installation of a socket to feed filament and B voltage to the multiplier.



The second and final phase of surgery. An RCA type phono jack is installed on the receiver chassis, close to the mixer tube, and connected to the high side of the input IF transformer.

value within one dial division of each other would sneak through the i.f. bandpass together like Siamese twins. And, like Siamese twins, the

signals would prove inseparable.

Since we couldn't hock the family furniture for enough cash to buy a 75A4 or an NC300, we looked for ways to strengthen our position without bending our budget. And we found it. The Heath company came through with one of their QF-1 kits for ten bucks, and Voila! We haven't lost a contact because of QRM since.

The Q-Multiplier is, of course, a simple gadget. It utilizes an iron core coil of extremely high Q in a tuned circuit which, shunted across the primary of a receiver's input i-f transformer, narrows the bandpass of that stage by an amount which is proportional to the Q of the circuit itself. While the basic Q of the iron core coil approximates 200 in the QF-1, this figure is increased by a simple triode positive-feedback circuit to a value of around 4000. The selectivity curve of the input i-f stage, therefore, becomes extremely steep-skirted, and any signal

falling to either side of the sharp peak is shunted to ground and greatly attenuated, while a signal falling exactly on the peak of the curve is actually boosted. Because the tuned circuit includes a variable condenser, the peak can be moved across the bandpass of the receiver's i-f system, and can be tuned to boost any desired signal, while attenuating all others. The gain of the triode, and hence the sharpness of the selectivity curve, is variable, so that the bandpass can be changed from broad to extremely sharp at the twist of a knob.

The QF-1 can also be used as a nulling device. A second triode amplifier, this time switched into a negative feedback arrangement while the high-Q circuit is switched to a series-resonant condition, provides a narrow notch at resonance, allowing an undesired heterodyne or signal to be shunted to ground, while adjacent

signals are unattenuated.


Since installing the Q multiplier, we nave been repeatedly asked the same questions concerning it, on the air, by brother peasants interested in improving the signal-separating powers of their own receivers. These questions fall into three categories: how does the QF-1 compare with a crystal filter; how great is the insertion loss; and does its installation require tearing into


the receiver? We answer thusly:

(1) In our experience, the QF-1 is approximately equal to the average crystal filter in degree of selectivity, and has a couple of advantages of its own; it doesn't "ping" or "ring" quite so badly as does a crystal at maximum selectivity; it is tunable across the i.f. bandpass and allows desired signals to be hunted for and peaked with its own control, thus minimizing the possibility of losing the signal as sometimes happens when the receiver tuning is varied to "center" a weak one; it can be used, by itself or in conjunction with a crystal filter, to null out an undesired signal without affecting the one being copied.

(2) There is no insertion loss. Rather, there is an actual gain of one to three S units of a

(continued on page 121)







Gathered and reported by

R. C. "Dick" Spenceley, KV4AA

Box 403, St. Thomas, Virgin Islands.

We welcome the following newcomers to the HONOR ROLL:


W8CED	39-180	WIDSF	35-157
WIJNV	37-181	W9NN	35-157
W8PUD	37-166	K2QQO	35-110
K6IOI	36-121		

PORTUGUESE TIMOR, CR1ØAA: This station has been appearing near 14082 around 1400 GMT with a T7C QRI. Beam headings on him from W6 seem satisfactory.

AVES ISLAND, YVØ: Things continue to look good for the appearance of this expedition between July first and eighth. Venezuelan President, General Perez Jimenez, with staff, made a holiday visit to Aves on the destroyer Zulia on March 25th. A new metal flag and bronze plaque were placed on the island to commemorate the visit. President Jimenez has expressed interest in the proposed radio expedition.

COMORO ISLANDS, FB8BR/FB: Hubert was unable to make this trip on April 13th as he had to attend an air erash inquiry. Next trip to this QTH was due in early May.

CANTON ISLAND, BRITISH PHOENIX, VR1B: At time of writing Danny, of the "YASME" expedition, has done much to justify all the effort and contributions put into this venture. His contacts on phone and CW now number well over 2000 and he will not leave until sometime in June. Sideband devotees will be interested to know that a move is being made to augment his present gear with an SSB rig which he may have by the time this is read. First contacts from VRIB, March 27, 28, were: KV4AA, FO8AB (A3), W8DAW, W5ABY, W6ALQ, W6TXL, W5ADZ, W9NDA, W6CYV, W9YFV, W9QLH, W7KVU, W6NHA, W1TYQ, W6MX, W6EFV, W8TMA, K6GUZ, W7TML, W4TO, W8OCT, W2AGW, W6WB, W7HXG, W5FXN, W5BZ, W6KSF, W9JUV, W8DMD etc. in that order. Some time in July Danny should reach Nauru Island where he has been assigned the call of VK9TW. Next in line are VR4, CR1Ø and VU5.



VS1GX, Bill Savage, Singapore, runs PP 807's on all bands. Receiver is an HRO. Bill has worked 120 countries and 34 zones since July '55. VS1GX is most active on 14 and 21.

SIKKIM, AC3SQ: Saja now sports a BC-610 rig and has been heard on phone, 14090, around 1300 GMT. We hope this presages a return to normal activity.

LITTLE AMERICA, KC4USA: Considerable activity has been reported from this station mostly on SSB, 14295, between 0700 and 1200 GMT. Also

some CW near 14315.

GATTI EXPEDITION: Commander Attilio Gatti has launched his 13th African expedition for the purpose of making TV films for the ABC network. Radio gear will consist of a B and W 5100 transmitter with 51SSB generator, easy-way tower and full sized telrex beam. This equipment will be truck mounted and manned by Jimmy Chapman, ZS6HG, who goes along as chief op. Activity will be mainly on 14 Mc. SSB altho some AM and CW is promised. The expedition should be on the air from mid-April and, with a brief return home in June, continue from six to nine months. Countries to be visited are: Kenya VQ4, Nyasaland ZD6, Tanganyika VQ3, Belgian Congo OQ5, Ruanda-Urundi OQØ, Uganda VQ5, French Equatorial Africa FQ8, Rhodesia VQ2/ZE, South Africa ZS1-6, Swaziland ZS7 and possibly two or three other countries. (Thanks W2AOX)

ANDA, VQ5GC: Neville writes that it has vays been his ambition to operate from VQ1 VQ9. He is definitely going to spend a week or operating from Zanzibar, later in the year, en enough money to cover the trip is accumued. A trip to the Seychelles is more difficult as resents a transport problem. It is not so hard to there but the boat does not call back there for eral weeks. In the meantime Nev is going to anda-Urundi, OQØ, for a few days and proby will have been heard from this spot as this ead. VO5GC continues to be very active from anda, all bands phone and CW with 150 watts, l QSL's 100%. Former calls have been VS6AC, 6CE, G3IAD and VQ4GC. (Ed-We will see at can be done about the VQ9 trip on a "dollar-5-QSL" basis. This idea has worked very satistorily in the case of VR1B and the DX fraternity been most cooperative. Expected squawks, ecially from the "millionaries", have not mate-

VENCH TOGOLAND, FESAC: According to RS a station signing this call will be on from

goland shortly.

VI EXPEDITION, KT1UX/KT1EXO: Efforts break through the red tape and obtain a license this jaunt have apparently not jelled. Another ort will be made when KT1EXO returns from 1 states in August. The 2½ day drive to Ifni m Tangier will be made with a jeep hauling a riler full of radio gear. A 75A-2 and 32V-2 will used. Five days of 24 hour operation is planned.



ET3TRC, is the Amateur Radio Exhibit at the Haile Selassie first silver Jubilee Fair in Addis Ababa. At the throttle is Leon, ET3LF. (Photo courtesy W6BIL)

DCOS-KEELING, ZC2PJ: This station was ace from this QTH for two or three days April

th to 14th. Name was "Dean".

VO JIMA, KAØ: Rod, W7YBX, now operating at A7HH, advises that he plans to go to this spot two weeks around the time of the next CQ ternational DX contest (October/November). He shes to know, however, if this spot is rare ough to warrant such a trip (We think so). ould you think so, please drop Rod an airmail ter. The volume of letters received will do much

towards his getting the necessary permission. In fact your letters might result in having a permanent "ham" stationed at Iwo. Ham gear is available for Iwo but the op isn't! Letters go to: A/1C Rod Linkous, AF 19496651, 37 Troop Carrier Sqdn (m), APO 75, PM, San Francisco, Calif. LUXEMBOURG, LX: Bob, QN4QX, advises that a Belgian expedition to this spot is planned for June 9th and 10th. QTH will be Bhoey, near Wiltz, in Luxembourg. The following ON4's will make the trip and appear on their special bands as follows: 14 Mc CW ON4QX, ON4TQ and ON4FU. 14 Mc. phone ON4LJ. 7 and 3.5 Mc ON4AB and ON4CC. 2 meters ON4DE and ON4RB. Authorization is expected to come through shortly.

DUTCH SAINT MARTIN, PJ2MA: We hear from Bill, W6SAI, that negotiations are progressing towards permission to operate from this rare QTH and that he, accompanied by George, PJ2AA, should appear from there some time this Summer. FANNIÑG ISLAND, VR3: VE7ASL/VR3 was recently heard from this QTH on 28414 kc phone, 0230 GMT, QSL's go via South Pacific Airways, International Airport, Honolulu, Hawaii.

Luis, CE3AG, says that lack of interest on the part of the present officer stationed at Easter Island's CEØAD is keeping that station off the air on the ham bands. It is hoped that his relief, next year, will be more interested in amateur communications . . . AC4LP, claiming to be in Lhasa, Tibet, has made quite a number of contacts and claims to be running a KW. We understand he is now QRT. . . . YJ1AA holds forth, most nights, from 0700 to 0900 GMT, near 14050 . . . VQ1EQ may be OK but he wouldn't give his QTH to VQ5GC! . . . A station signing AC5PN was worked on April 17th at 2015 GMT. He put a 579 signal into the east coast and gave the right name "Chhawna". Outside of that he didn't recognize KV4AA (Which he should have. We have QSO'ed and corresponded) and said he was on every night when, at the time, it was 2 AM in Bhutan! The beam here was on Europe . . . Bulgarian hams have now been permitted to operate their own stations. Licenses have been issued to LZIAF, LZ1AX, LZ1SR, LZ1VK, LZ1AL, LZ2PA and others. LZISR and LZ2PA are already on the air . . . We are advised that LZ1DX/ZA, 9B3AA etc



Bill, MP4KAC, (center) was snapped during a recent visit to Tangier where the DX situation was re-hashed with Jim, KT1EXO (left), and Carl, KT1UX.

(Photo courtesy W9HUZ)



Myint, XZ2OM, Rangoon, Burma, is seen here with attractive XYL, Sein, and (very ditto) YL, Shiela.

(Photo ccurtesy W6EFV)

are NG!... In addition to the Norwegian prefixes, given in the May issue, the prefix "LJ" is used for military school stations . . . VP7NG, Glenn, now QRT's from the Bahamas and goes to Puerto Rico as W4PDZ/KP4... Leny, VQ8CB, leaves Chagos in August and possibly will settle in ZL... Via F9RS we hear: FB8XX will not be on the ham bands this season. FB8AX, Terre Adelie (Antarctica), may be active from May. Activity is also expected from FD4BD by now on phone and CW with new station. F8EX says St. Martin is NG for DUF. FU8AA is active with 350 watts and 600 foot long wire. FD8AM will be heard on phone. F3UR/MM is on the MV ARAMIS. FF8BH and FF8BM have returned to France for good . . .

W8FGX reports KC6AL is on Eastern Caroli 14070 . . . W8AUS nabbed FU8AC, on pha 0700 GMT . . . SVØWA was QSO'd, SSB, 14 0010 GMT . . . UP2KBC says QSL via Box : Sofia, Bulgaria . . . W3JTK ponders one YZ2F who said he was in Nepal with a Yugoslav exp tion to the Himalayas. Said, QSL via VU2RU Fergus, MP4QAL, is now equipped to dispe phone contacts from Qatar . . . BV1US now longs to the Taipeh Radio Club and QSL's being printed . . . W6NTR received UQ2AN via the YO bureau . . . Bill, ex-JA2KW/K6C and 7th op at XE2NF in '56 ARRL test will s be heard from KR6-land using a Viking Ran 160 through 28 CW (A3 in contests only) VK1II is consistently on from Macquarie Isla CW and phone around 1600 GMT. KP6AK, myra Island, is infrequently on 14217, A3, v most contacts being KH6's (So. Cal. Bulletin) 3W8AK is active from South Viet-Nam on phy . . . XW8AB has dropped out of sight. If he still alive we are sure that missing QSL's eventually come through . . . EA9DF, Rio de C says he will go to Ifni this summer . . . W6H will be VP5SH on Grand Turks Island. Rig i Ranger and A3 most likely (North Cal. DX'er) VS1EW (ex-VS5EW) is building 250 watt S rig . . .

#### **VQ** Certificate

The radio Society of East Africa, Box 264, Naku Kenya, has made available a new award to known as "WAVQA", Worked all VQ areas. Ap

#### Last Minute Items

FESAE is now active from French Cameroons, Frequency 14106 CW and time 1930 GMT. QSL's should go to Box 408, Duala . . . Latest reports say that Hubert, FB8BR, will again visit the Comoro Islands in late May or early June . . . Activity should be expected from FB8BC on the Glorious Islands in June. This may (or may not) be a separate one . . . There is no present activity from Tromelin Island (FB8BK) but we trust that he will be on in the near future . . . CN8MM advises that the call FB8PP, used by a station claiming to be on St. Paul Island, has not been issued . . . A new ham in French Morocco is CN8MH. This is none other than H.R.H. Prince Moulay Hassan, son of the reigning Sultan . . . We hear that the calls of the British Antarctic Expedition are VP8AO and VP8BO . . . The DX'pedition to Aves Island seems to be all set for the first week of July. It does not look like KV4BB will go along as the group will sail directly from YV to YVØ . . . VQ5GC plans a radio expedition to the Seychelles in mid-July. A two weeks stay will be made. This trip will be made possible on a dollarper-QSL basis which, via our experience with VRIB, has the approval of the DX fraternity. QSL's for contacts between VQ9 and W/VE will be handled by KV4AA. Also, a trip to IFNI, by

EA9DF, on a similar basis, is very likely to Summer. Possible call at VQ9 will be VQ9AA. VQ9GC . . . W2HQL advises that new calls in effect in Surinam as follows: PZ1PA is PZ1A PZ1BS is PZ1AH, PZ1LM is PZ1AJ, PZ1LL PZ1AI, PZ1CD is PZ1AP, PZ1RM is PZ1AC a PZ1AM is a new ham . . . AC3SQ put on an a pearance on April 23rd, 14080, 1300/1430 GM and among the lucky recipients of contacts we W9ABA, W9YFV, W8A W8FGX, W6NNV a W9NDA, W9KOK, W8NBK, W8DUY, W3CRA. We understand that QSL's go W9KOK . . . W5CFG plans to operate from K this Summer . . . VR1B should leave Canton early June. He will not stop at Wallis, FW8, H proceed directly to NAURU where the cal VK9TH, will be used . . . YV4AU is ex-I1A! . . . Many reports have come through that Russii hams may now contact USA. While this may true we have not received any definite confirmation of the fact . . . KC4USV has been on 14057 C around 1200 GMT . . . AP2M is W5LAK at was worked on 14083 around 2200 GMT. Q\$ via AP bureau . . . 9S4BN has new 3 eleme mini-beam . . . DJ2PQ will obtain a LX licen and may have been heard on the air by no 73, Dick, KV4A ints must submit confirmations of contacts as fol-

a. One VQ1 contact.

b. Ten VQ2 contacts.

c. Five VQ3 contacts.

d. Twenty VQ4 contacts.

e. Five VQ5 contacts.

f. One VQ6 contact.

g. One VQ8 contact (Mauritius).

h. One VQ8 contact (Chagos).

i. One VQ9 contact. (45 cards in all).

ive extra confirmations from any VQ call area lay be submitted as a substitution for any one hissing card. Remittance of one dollar or 20 IRC's tust accompany list. List may be submitted in lace of QSL's if countersigned and checked by the Secretary of a recognized Radio Club. Certicates are issued Phone to Phone or CW to CW. Inimum reports RST 338. Contacts after fovember 1st 1945. (Looks like a toughie!)

#### D X'ploits

rank, W6SYG, leads off this month with the ddition of AC5PN which gives him 261 . . . Iowie, W2AGW, upped to 257 with FS7RT and S4RO while Jim, G6ZO, made it 256 with VR3B . . Glenn, W8KIA, made VR1B his No. 256 as im, W8JIN, hit 254 with AC5PN . . . Oscar, V3JNN, submitted revised list giving him 253 /hile Roger, W3EVW, reached 252 thanks to S7RT . . Ed, W6DZZ, rose to 251 with FS7RT nd FB8BR/FB as Ozzie, W9VND, added YJ1AA nd VR1B for 251 . . . Gene, W6EBG, made it 48 with EA9DF while Ed, W6TS, also hit 248 vith YA1AM, FB8BR/FB, HI8EC, ZD3BFC,

FB8XX, XW8AB, FW8AB, YJ1DL, FS7RT, PJ2MA and LU3ZY . . . Bill, W6SAI, reached 247 with FS7RT, YJ1DL and FB8BR/FB as Horace, W6TI, rested at 239 with FW8AB, H18FR, YI2AM and YA1AM . . . Vince, W5KC, went to 239 with VR1B and FS7RT while Luis, CE3AG, also hit 239 with ZD8AA, LU3ZY and 3W8AA . . . George, W1GKK, keyed with VR1B and FB8BR/ FB for 238 as John, W7GUV, also upped to 238 with ZS8I, FB8BR/FB, FB8ZZ, LU3ZY and FS7RT . . . Maxine, W6UHA, comes up to date with EA6AF, FB8BR/FB, ZD3A, XW8AB, ZS2MI, YJ1DL, FS7RT, PJ2MA, and LU3ZY to reach 232 as Guy, W6DLY, snagged ZD1DR and LU2ZY for 229 . . . George, W7GBW, submitted new list raising him from 127 to 226 while Ed, W6LDD, upped to 216 with FB8BR/FB, FS7RT, YI2AM, ZS2MI, VR6AC, LU3ZY, ZS8L, MP4QAL, XW8AB and VK9OQ . . . Burt, W6EHV, nipped VR1B, MP4QAL and EA9AP for a 215 total as Thor, W6LN, hit 213 thanks to MP4QAL, LU3ZY, VP2SX, YI2AM and FP8AK/VP2 . . . Don, W6LRU, moved to 212 with 3A2AN, ZD3A and VR1B while Bob, W6NGA, made it 205 with FS7RT, LZ1KAA, LU3ZY, VP2GW, FB8ZZ, VO6LO etc . . . Wally, W7ENW, rose to 204 with Y12AM and VR1B as Don, W6BVM, broke through the double century barrier with F9YP/FC, FQ8AY, VR1B, YI2AM and AP2RH for 201 . . . Shelley, W6BAM, sent in 23 additions to reach 193 while Hal, W6JK, upped to 190 with VR1B, VR3B, FB8ZZ, YJ1AA, VQ6LQ, VQ5GC etc . . . Norm, W9YNB, added LZ2KSK, VQ6LQ, VR2BA, VR3B, VR1B, VQ5GC and EAØAB for 189 as Buck, W4RBQ, nailed ZS9G to reach 207





Henry, W4JVJ, with Takeo, JA1CR, snapped in front of Takeo's, Tokyo, QTH. Operating position at JA1CR with Takeosan. 100 watts is the present power but new rig, left, will put 200 watts on all bands.





FOSAN, on the YASME, departing Papeete for Canton Island and VR1B.

.. Dan, W6PH, goes to 181 with VP8BS, VR3B, ZK1BS and YI2AM while Vip, W6ID, hit 180 with FP8AK/VP2, MP4QAL and VQ6LQ . . . Hal, W6BUO, added such as 3V8AN, FS7RT, LU3ZY, VP8BK, VQ6LQ, ZD6BX, PZ1BS and FB8ZZ for 179 as Dick, W6ATO, added 11 including ZD3A, VQ6LQ, FS7RT and FB8BR to hit 178 . . . George, W6BIL, rose to 164 with HZ1HZ, FY7YF, PZ1BS, YI2AM and FB8ZZ while Dick, KV4AA, made it 252 with VR1B . . . Al, W2WZ, nabbed FS7RT for 248 as Stan, W1CLX, pulled in Danny, VR1B, for No. 246 . Art, W9LNM, added FS7RT, YJ1AA, MP4KAC and VR1B to reach 243 while Bob, W3EPV, rests on 243 with ZA1KAD, LU3ZY, YA1AM, PJ2MA, XW8AB, ZC5CT, KC6CG etc. . . . John, W1BIH, goes to 240 with FS7AA, VR1B, FD4BD and LU3ZY as Van, W9HUZ, hauled in VR1B for No. 237 . . . Howie, W2QHH, slid to 236 with VS1GX and VR1B while Norm, W1HX, nicked VP8BT, FS7RT and VR1B for 246 ... Joe, W8UAS, keyed with SVØWN and VR1B for 233 as Bob, W4GG, upped to 232 v YA1AM, FB8ZZ, FS7RT and HI8FR . . . Geo W2HZY, goes to 228 with YA1AM and MP4Q while Chuck, W4LVV, pulled in FS7RT VR1B for 218 . . . Chas., W3DKT, made it with FS7AA as Clif, WØAZT, went to 212 w FB8BR/FB, 4S7MG, FS7RT, CR4AG, VR1B VOSCB . . . Bob, W1KFV, hits 209 with VR SVØWN, VR1B, VQ8CB and 4S7MG while I W2GVZ, goes to 205 with MP4BAU, VU21 VR3B, VR1B and FS7RT . . . Vern, W7CN makes it 193 with 22 additions which inclu VQ6LQ, LU3ZY, YA1AM and VR1B as B WØQVZ, snagged FB8ZZ, VP8BD and 4S7N for 188 . . . Paul, K2GFQ, reaches 186 than to VR1A, VR1B, HI8FR, VK9RM and FB8 while Bob, W6DBP, rounded up VQ5GC, IS1F. FB8ZZ, MP4QAL, VR1B, Y12AM, MP4BBE a LU3ZY for a 180 total . . . Gus, W2HMJ, rises 227 with VR1B as Eric, OZ8BG, adds a new zo with XE2KW plus KB6BA and OA4AI for 2 . . Floyd, W9FNR, reaches 189 with such ZD1DR, KB6BA, FG7XB, YIIAA, KW6WU, VQ5GC, FB8ZZ and ZD3D while Say W3AXT, hits 181 with UC2AA, UB5KAA a VR1B . . . Jim, W9LI, nipped FB8ZZ and VP8I for a 179 total as John, W9WCE, adds UC2A YK1AB, VK9DB and VS1GX to reach 175. Paul, W4LQN, goes to 175 thanks to KR6L ZS9G, VR3B, FC7RT and ET3LF as Mer VE6MN, comes up to date with such as VQ5G SVØWT, FB8BX, ET2AB, LU7ZK and PZ11 for 143 . . . John, W4HA, makes it 211 (195 A with AC5PN, ZK1BS, FB8ZZ, FS7RT, EA9D ZK1BL, FK8AO, VR1B and VP8BK while Fre W8KML, goes to 205 (195 A3) with 3A2BI EAØAB, CR5JB, FB8ZZ, YJ1AA and FK8AO. Doug, W9FDX, upped to 202 with YJ1D1 LU2ZY, ZD6RM, ET3LF, MP4QAL, VP8BI VR3B, FS7RT, CR9AH, VS9AS, VR2CS, FB8Z VR1B, VQ8CB and CR5AC as Glenn, W7AD went to 194 with CR4AG, FB8BR/FB, FS7RT ZS2MI and VQ8AG . . . Harry, WØANF, uppe his total to 188 with FS7RT, FB8ZZ, CR4AC 3V8FA and ZK1BS while Wilson W3WU, hit 178 thanks to ZC4VP, LU3ZY, VR3H ZB1BS and VR1B . . . Gil W1APA, evened it up a 160 with 5A1TZ as Dixie, W2ZVS, now in the



Reception committee for Peps TI2PP, and XYL upon their arriva at the Quito (Ecuador) airpor Left to right are: Len HC1PM, Lui HC1OR and XYL, Judy XYL a HCIFG, Sofie XYL of XEIJK, XY TI2PP, Ruth XYL of HCIRA, Nild XYL of HCIRY, Luis HCIRA, Isabe XYL HC1HN, Fred HC1FS, Inez XY of HCIPM, Hilda XYL of HCIFR (head only), Ricardo HCIRY, Erii Bob HCICF (head only), Ricard HC1RY, Eric HC1ES, Graciele HC1SR, Luis HC1LE, Carlos (Presi dent of A.R.E.) HC1FG, Jose TI2PP Frank HC1FR, Humberto HC1HN and Pat, 2nd op of HCIOR.

KASAB. That's WITTA at the Mic. who with W6DUS made Top Five both on Fone and CW in the Multi-Operator section of the recent CQ World Wide DX Contest. The photo shows a BC 610 Xmtr, 75A4 Rcvr, DB 22 and other equipment. Antennas include an assortment of a Rotary, Ground Plane and Rhombic for 14., 21., and 28. mcs. KA's are not allowed to use the 3.5, 7. or 27. mcs. bands. Alan, WITTA, will be returning to the States this summer and would like to work more W1's before leaving, especially on 10 and 15. Bands are usually open between 20:00 to 03:00 GMT.



service, nabbed FB8BB for No. 182 . . . Bob, W6YMH, went to 137 with VR1B, 4S7MG and VU2JG while Mickey, W8YIN, was making it 195 with LU3ZY, 4S7MG, VR1B, FS7RT, W4IKC/KW6 and YA1AM . . . Duke, W6HJ, upped to 129 with ZD3A, TG9WB, HA5KBA and ZD1DR . . . On the "phone only" side Guy, W6DI, made it 218 with PSPCC. Paul, W9NDA added ZD8AA for 225. Willard, W1NWO, miked with FB8ZZ for No. 213 and John, W4HA, went to 195 with such as ZK1BL and FS7RT . . . John W4AUL reaches 152 with VK9RM while VR1B was 132 for Phil, W3SOH . . . Contacts and multipliers for leading KH6 stations in the recent brawl are as follows: KH6IJ 2915-104, KH6AYG 2500-90 (app), KH6MG 2149-88 and KH6PM 1850-86 (app) . . . W6LWB, with a DX-100 has added such as TG9AD, FB8ZZ, CR6AI and ZD2ROC . . . Milt, W4LHT, ex-W8FGA/W3IQC snagged his first Jap, JA4AF, for No. 97 . . . Marvin, W4ENI, is up to 127 with VS1GX. He recently knocked off a 57 minute WAC with FF8AP, VK2ACN, IIZHE, JA4AF, VE7WL and LU3CW . . . Joe, W9JUV, is up to 140 with such as VR1B, YI2AM, YJ1DL, FS7RT and ZK1BS. His phone total is 130 . . . Lloyd, DL4ZC, picked up 3A2•AG on

7 CW, MP4KAC on 21 A3, JA1CO, VU2HF, KL7BKF and VE8WN on 21 CW and AP2RH, FY7YE, GM3GZA (Outer Hebrides until June 1st), VS9RO (First VS9RO QSO), JA2AT and VU2KM on 14 CW . J. Ernie, W3MDO, goes to 142 with KR6SC, VK9RM, VR1B and ZK1BS while VR1B was No. 171 for W6KSM . . . Dave, WØMHS, got bit by the DX bug and is up to 32 mainly from efforts on 21 C W ... Sax, W2SAW, hits 174 with such as FS7RT, 4S7WP, VR2A, W4IKC/KW6, ZK1BS and VR1B as Bill, W2SDB, makes it 115 with VR1B, YI2AM and OY2Z . . . W1WLW goes to 157 with FK8AH while the same station was No. 182 for SM5AQW . . . WIWAI ups to 132 with YI2AM, VPISD etc. as W9OBV goes to 96 with VR1B, VR2CV, LU6ZI, VQ6LQ, EA9AB, CR9AH and FB8BC . . . Dave, PAØUN, made it 250, before moving to South Africa, with VR1B . . . KV4AA was no. 99 for VE8WN in three months operating time . . . K4BYN, Louis, goes to 72 with such as CN2AY, PZ1BS, VP7NG, CT3AB, FY7YF, HP1ZZ and ZE5JA . . . Frank, VK2QL, nabbed EA9DF for No. 214 while Charlie, KV4BK, hit 115 with VR3B and ZP5AY . . . The 2E26 at WØQGI went to 148 with ZK1BS, ZS9G, ZD1DR, FB8BR, 3V8FA, FS7RT and ZD2DCP . . .

The Gang at YI2AM. Left to right.—Derek, Nab, Malcolm, Dick, Tom, Dave and Ros. However there are only three active members at present; Derek, Nab and Ros. YI2AM is the only active station in Iraq at present. The Iraqi Authoritish have discontinued issuing calls to individuals because of lack of facilities to monitor them. The boys are still struggling for WAS and need Vermont, Idaho, Nevada, Utah, Miss. and North and South Dakota.



FLASH! Alfredo, LU3EX, has established what may be a new distance record on 50 Mcs. when JA6FR was worked on phone, 0450 GMT, March 24th. He goes on to say that CP5EK, CE1AH, XE1GE, TG9JW and PZ1AE are like locals. On March 31st he worked his first W's when K6EJO, W6ANN, K6GMV and K6OBO were contacted. W5FXN and W5EXZ have also been worked on phone and CW. LU3EX runs 90 watts to an 829 with a 3 element beam 30 feet up!

#### 160 METERS

(Via W1BB)

February 26th "TEST"-Weather windy/rainy. ARRL DX test on. G5JU, G8IL and HB9CM came through from Europe with G5JU's signal came through from Europe with G5JU's signal being especially good. Scarcity of signals has coincided with the great snow and cold wave all over Europe. W/VE participants were W1AW, W1BB, W1BIL, W1VDB, W2EQS, W3RGQ, W3FNF, W3MSK, W4SGV, K4CDK/4, W8AQ, W8PXK, W8ANO, W8JVA, W9NH, W9PNE, W4VNE. NA/DX-KV4AA, XE20K. DX—G5JU, G7FNL G2GH, G2G G5RI, G3GIL, G3PU, G3IGW, G3ETP, G8IL, G8FW, G8JR, HB9CM, DL1IX, DL1OO, DL3FF, M3KHJ. Temporary authorization to use 160 has been granted to DL1IX, DL1FF, DL1YA, DL3OO, DL1BZ, DL7CZ, DL1DA and DL1SO according to HB9CM. DL1DA uses an abandoned power line for an antennal . . . W9PNE keeps skeds with ZL1BY, KH6IJ and KH6MG.

March 4th "TEST"-WWV/W4, sunspot storm. No European stations heard. YN1AA came through 559x. Later W6KIP/6 put a 339 signal

through to the east coast.

March 11th "TEST"-WWV/N6. Loran QRM seemed to spread more widely than usual. YN1AA and KZ5FA were heard working W8ANO. W6KIP and W7KVU came through weakly.

March 18th "TEST"-Band very noisy. No DX whatsoever. W6KIP/6 and W5SOT were 339

around 0730 GMT.

March 25th "TEST"-WWV/N7. High noise level. W1BB QSO'd G3FPQ who came through weakly between 0545 and 0630 GMT. Second half of ARRL DX test in progress. KV4AA completed all W districts with W7KVU and W6AM (plus VE3IR) for contest QSO's.

This concludes the 1955/1956 top band tests. Although conditions were generally poor the tests were well attended with the following participants logged at one time or another: 16 W1's, 24 W2's, 16 W3's, 17 W4's, 6 W5's, 3 W6's, 2 W7's, 23 W8's 15 W9's 8 WØ's, one each VE1, 2 and 3, 26 G3's, 3 G2's, 5 G5's, 4 G6's, 1 G8, 4 VP's, 3 KZ5's, 4 KP4's, 2 GM's, 2 HB's, 3 ZL's, 3 GI', 9 DL's, 3 XE's, 2 YN's, 5 OK's, 2KV4's, 2 HR's, 2 GC's, 2 KH6's and one each: TI, EI, LU, OA, GD, SP and HE.

1850 KC LORAN-We owe many thanks to

WIBUD for his kindness in checking into the Loran QRM which, when active, made 160 DX an impossibility for the east coast. It was found that the QRM was caused by a temporary gim-mick known as "EPI," Electronic Position Indicator, which had been operated in the Boston and Nantucket areas. EPI also caused QRM to the U.S. Coast Guard and its future operation will be restricted as possible to minimize that interference. We are most happy to know that this is not a PERMANENT situation!

#### **ADDRESSES**

		VARIATION
F	B8X	Box 38, Pointe a Pitre, Guadloupe, F.W.I.
F	B8B Y7YE	Box 587, Tananarive, Madagascar. (Now) Via W5JLU.
H	118FR	Martinez, Estacion de Radio Afi-
ш	IZ2AEH	cionado de la Feria, de la Paz, Cuidad Trujillo, Dominican Rep. SFC W. A. Brewster, RA 14296401
	IEEE/EII	8688 DU USA Section, MAAG, APO 616, PM, N. Y.
	5RAM	Box 179, Mogadiscio, Italian Somali-
K	(2HGU/KW6	Roger, c/o C.A.A. Wake Island.
		Roger, c/o C.A.A. Wake Island. Capt. Calvin M. Preston, 745 TCS, FPO 230, Seattle, Wash.
K	(A2EC	R. H. Mitchell, H&MS-11 (Metc) MAG-11, FPO, San Francisco, Calif.
K	(A9MF	Field Stn 8612 AAU, APO 181, PM, San Francisco, Calif.
K	L7BSR	Box 219, Anchorage, Alaska.
е	x-TF2WAY	.G. S. Fly, K4AZC, Box 4155, Mo-
٧	E4AR/VE8	Geoff, via VE8NK.
		Geoff. via VE8NK. Don Daly, 208 Almond St., Georgetown, British Guiana.
٧	/P5SH	(W6HNX) RCA Mtr. Grand Turks
V	/P8BL	Is. via Patrick AFB, Cocoa, Fla. Box 182, Port Stanley, Falkland Is.
٧	/Q8CB	(Chagos Is.) Leny Mazery, Box 155, Mauritius.
		(YASME, Canton Is., British Phoe-
٧	/R2BC	G. B. Gregory, Dept. of Agriculture, Koronivia, Nausori P.O. Fiii Is
	3202	Malaya
٧	/U2HF	Harry Fox, Methani Colliery, Sit- apampur P.O., Burdwan Dist., Ben-
٧	W3UIF/KG6	gal, India.
\ \	W8EBK/KL7	Bill, Box 70, Navy 943, FPO, San Francisco, Calif. (ex-KL7PIV) E. W. Goodhue, 2201
		Sunrise Dr. Anchorage, Alaska
\	W8EBM/K <b>L7</b>	(ex-KL/BHE) Sheila F. Goodhue, 2201 Sunrise Dr., Anchorage,
)	(E3AR	Alaska. Napoleon Correa, 1-A Ave Norte-5,
		Apartado 57, Tapachula, Chiapas, Mexico
		Stan Williams, Room B-20, RAF,
1		Signals, Gifford Camp, Accra, Gold Coast.
5	A2CO	Cable and Wireless Benghazi Libya
' I	hanks to West	Gulf Bulletin, No. Calif. DX'er, W4ML, WØQGI, K6IYJ, W10DW.

#### HERE AND THERE

Beda, OK1MB, wishes to thank all for letters and messages received during his recent illness. He is slowly recovering but will not be on the air for quite some time . . . Dave, YJ1DL, is in FO8-land for a month. Ed, W6LDD, has his logs covering the period between April 11 and October 21st 1955 and all cards are going out via Bureaus. W6LDD does not want YJ1DL cards sent to him as no arrangements were made for this . . . Expedition minded are W6NJU, W5CFG, W9OWZ, W9ASB and W9ZTD (let's get together) . . . Larry, WØANY/VO4, advises that he will be in

#### Belgian Award

The Antwerp Group of the U.B.A. offer the "WOSA" certificate for any amateur station submitting logs which show contacts with Antwerp stations as follows:

- A—5 Antwerp Stations on Phone or CW for all countries outside of Europe.
  - B-6 Antwerp stations on Phone or CW for all European countries.
  - C—8 Antwerp stations on Phone or CW for the Benelux countries.
  - D—10 Antwerp stations on Phone or CW for all listeners (HOSA Award).
- Contacts shall date after January 1st 1954.
   Minimum reports CW 448, Phone 45.
- 3. QSL cards not necessary. Just a list giving QSO data.
- 4. Your QSL must be in the possession of the Antwerp stations listed.
- 5. 5 IRC Coupons must accompany application.
  6. Applications are sent to ON4QX. Dr. L. Th. Berge, 33, Everdystreet, Antwerp, Belgium. (There are over 50 Antwerp stations)

VO4 until June 1959. They are on the air daily from 1200 GMT on 21350 to 21425 and 28.4 to 28.5. They will be glad to handle any Newfoundland or Greenland traffic. QSL QTH is: A1C Loren Bump, 52nd Air Rescue Sqdn. Ernest Harmon AFB, Stephenville, NFLD . . . W4LVV has contest logs from FG7XB . . . W3CHH still has a few QSL's available for his W3CHH/IWO activity if any are missing . . . W6LJQ is now K2RMW . . . W8PXP is now K9CLO in Indian-



Operating position at G3AWZ. AR 88 receiver.

apolis . . . W6NIF/4 received big batch of SUIREC cards and will send direct to those who include self-addressed, stamped, envelope. Otherwise via bureaus . . . We recommend W6SAI's Beam Antenna Book for the real low-down on beam operation, . . . W2AIW just hired a new technician whose call, of all things, was K2AIW! . . . Congrats to Stan, W7TML, on the fine Willamette Valley DX Bulletin . . . KA8GH goes QRT during the first of March and, for QSL purposes, may now be found at the following address: Capt. G. L. Heller, 81st Air Rescue Sqdn, APO 130, PM, N. Y. . . . W4JVJ, stationed in JA, advises that there are about 3100 2nd class ham stations (up to 100 watts) and 310 first class stations (up to 500 watts) in Japan. 20% are located in the Tokyo area. Low voltage, down to 75 volts, is often a problem. Jap ops must pass a test which, besides theory, calls for a code speed of 60 letters per minute, regular morse, and 50 LPM in Jap code which, incidentally, has 51 characters or letters. Conditions towards IA may be checked by listening to JJY on 4 and 8 Mcs. JJY is a standard frequency station with time signals . . . Joe, W2JME, ex-W3COP, is now W1GET in Plaistow, N. H. . . . The Ohio Valley Club will hold its annual picnic on June 10th at the usual place in Evendale, Ohio. Further details may be obtained from W4OMW . . . KV4AA had the plesaure of logging visits from WØNLY, W9EUJ, VP9BM, K2GFQ, VEØNA, VE3ZC (VE1FB), K2CIQ and W3EUP/4 . . . DL4UM, USAF, is the Dad of F7DI....

73, Dick, KV4AA

# **Honor Roll**

(To April 15th 1956)

Last complete HONOR ROLL appeared in the May issue.

	Next complete h	IONOR ROLL appear	s in the Septemb	per issue.	W8KML	37-205
W6SYG 40-	261 W6LRU	40-212	W4GG		W9FDX W7ADS	37-202 37-194
W2AGW 40-		40-206		39-228	WØANE	37-188
G6ZO 40-:	256 W6NGA	40-205		39-218	WIINV	37-181
W8K1A 40-		40-204		39-217	W3WU	37-178
W8JIN 40-	254 W6BVW	40-201		39-212	W8PUD	37-166
W3JNN 40-		40-193		39-209	WIAPA	37-160
W3EVW 40-		40-190		39-207	WITYQ	36-185
W6DZZ 40-				39-205	W2ZVS	36-182
W9VND 40-		40-181		39-193	W6YMH	36-137
W6EBG 40-		40-180		39-188	K6JQJ	36-121
W6TS 40-				39-186	W8YIN	35-195
W6SAI 40-		40-178		39-180	WIDSF	35-157
W6T1 40-		40-164		39-180	W9NN	35-157
W5KC 40-		39-252		39-145 38-227	W6HJ	35-129
CE3AG 40-		39-248		38-206	K2QQ0	35-110
	238 WICLX	39-246		38-189		
	238 W9LNN			38-181	PHONE OF	
	232 W3EPV 229 W1B1H	39-243 39-240		38-179	W6DI	39-218
	226 W9HU2		W9WCE	38-175	W9NDA	38-225
	216 W20HF		W4LQN	38-175	W8KML	37 - 197
	215 WIHX	39-236	VEGMIN	38-143	WINWO	36-213
W6LN 40-			W4HA	37-211	W4HA	36-195



Reported by

#### Sam Harris, W1FZJ

P.O. Box 2502, Medfield, Mass

#### Six Meters

Activity on the six-meter band has been increasing so rapidly that it is hard to keep up with developments. Information received from all over the world indicates that the predictions are not excessively optimistic. Big news from LU3EX. Alfredo says: "First QSO between LU and JA on the 24th of March, LU9MA—JA6FR at 0420 GMT and with my station LU3EX-JA6FR at 0450 GMT; with fair signals on fone on 50.350 kc.

"Finished the QSO I had with LU9MA, Mendoza, 1000 km from here, we heard a station calling us, result: JA6FR. At first, we believed it was a joke but the direction of our beams were right on Japan. He had a flutter, QSB, usually heard on the band on stations of DX. The band was open till 0530 GMT. LU2EW also tried a contact but signals were down and no confirmation of contact were established. The time of opening here for JA6FR is late in the night, or better said early in the morning, 0120 LU time. It was a big surprise to make this first JA-LU QSO.

"When I receive the QSL card it will mean a new DX Record on 50 Mc JA-LU.

"My rig is crystal controlled 6Y6, 6V6, 829 with 70-100 watts input. Antenna, 3 element beam thirty feet high. Receiver: crystal controlled converter with cascode input and an HRO tuning 3,300—5 Mc. QTH is ten miles north of Buenos Aires City, place named Villa Adelina."

Since the letter from LU3EX arrived, we got one from W5FXN. His log shows contacts with LU3EX on the first of April (1609 local) and

#### Early Scores, April VHF Contest

Here are the top 14 turned in so far:

W3TDF	8050	K2IEJ	3960
K2CMB	6727	W1FZJ/1	3745
WIRUD	5896	WØETJ/2	3690
W2NSD	5244	W2FBZ	3564
WIFOS	4386	W8SFG	3431
W2OIB	4350	W9BRN	3420
K2BKU/2	4219.5	WIHOY	3390

just to prove that it wasn't an April fool joke his entries for the fourth of April show contacts with LU3EX, XE1GE, LU9MA. On the seventh he snagged LU7DDG and LU8AE. The following quote from his letter is of interest to any dx minded six-meter operator:

"Band was open intermittently all day, 4-8-56, but sigs too weak. Please impress on the gang the importance of being able to work c.w. on V.H.F.—could have worked several South Americans yesterday (8th) if they had tried c.w., as their phone was ruined by QSB. Hear several Spanish speaking stations but



W4HHK, W1RUD, W8SVI. Hamvention VHF Forum.

couldn't identify them due to QSB. South American signals peaked a bit west of true path."

From Mexico Jeff (XE1GE) send information on both the foregoing openings, plus a few of his own. "This year the path to Argentine opened up somewhere towards the end of February or the beginning of March, I did not get back on the air due to illness until March 11th. Starting at 1640 CST worked LU7DDG and LU9MA and at 1700 worked my first CE stations on six. CE3TB and CE3CC and continued to work LU stations until the band went out at about 1730. Since the 11th of March I have worked the LU stations practically every day starting in with the Buenos Aires district around 1500 CST and on through up to about 2100. LU9MA in western Argentine usually comes through on an average about 2000. As you have obably heard by now what appears to be a w record for Six Meters was set up between J9MA and JA6FR. This took place at 0115 gentine time Saturday the 24th of March. 215 CST Friday the 23rd.) Up to this date a LU's had only been working PY, PZ, CP, A, TG and XE. What appears to be one of a first W-LU contacts of this 19th cycle took ace on March 28th at about 1900 Argentine ne between K60BO and two or three L'U's.

y first W5 opening of this year took place. April 4th. I started working the LU's as rly as 1350 CST and at 1900 CST, W5FXN d other Texas stations were worked (these approximately 1600 kilometers from this cation). Although I turned m ybeam to the lorth, I continued to work the LU's during is one hour and a half opening to W5 land. In this year no other six meter stations we been heard or worked outside the LU's, E's and W5's."

And last but not least we hear from Major

"I wish to advise that I have worked four In Districts on 50 mc on 1/4/56. Stations brked include JA3NE, JA1AND, JA1GP, A1ID, JA3JJ, JA2QR, JA4GJ, JA3EK, A1APQ and JA3FA. On the following day, 4/56, some of the above stations were

orked again in addition to JA1NF.

"The gear here is 100 watts, push pull F100's, Class B TZ40 Mods. RX double concrision with two RF stages, 4 element beam, ty feet high.

"What about some W Contacts?"

Meanwhile back at the ranch we enjoyed hat (to date at least) was probably the most idespread six-meter opening on record. At THOY signals were heard from every state st of the Mississippi and many on the western de. Helen made contact with twenty-nine different states (twenty of them were new ones for pr). From nine o'clock Sunday morning until ne o'clock Sunday night, April 15th, signals ere coming in from all points. A really odigious band opening which defies descripton. You just had to be there to believe it.

### The Dayton Hamfest VHF Section W1RUD

Well, we started from Cambridge, Massanusetts with a *Gonset* in the car, very grateral to Norm (WN1FMW) for so good naturedly aning us his rig for the weekend, and we arved at the top of the Taconic Trail in Petersurg, New York to spend the evening. Worked everal W2's in the Albany area with our peanut histle and 4 element beam before going to bed, inally hit the real long trail the next morning 6:00 a.m. and finally made it to Dayton at hidnight the same day.

Really didn't find much in the way of activity n the way until we hit the Dayton area. Boy, nen we had QRM several layers deep.

We were talked into town by W8FPZ, Art,

and finally managed to get to bed in the room reserved for Sam, who, as everyone now knows, unfortunately was not able to make it.

Before we went to bed, however, we put the Gonset with its whip up on the bed table. Worked enough stations to qualify for the WADH award (for the uninitiated, "Worked All

Dayton Hotels").

Next day Paul and I met practically everyone who is, was, or will be on Two in W8 (which explains why we didn't work a soul all the way down Route 42 from Cleveland to Route 40 and Route 40 into Springfield.) The band was so dead that even the ignition noise sounded lonely. The picture of some of the gang really doesn't even begin to include everybody. (Couldn't fit them all into one spot anyway.) (Ed. note: wasn't good enough to print either, so don't make a frantic search for it.) At the V. H. F. talk Saturday afternoon, Paul, W4HHK, gave an interesting talk on meteor scatter work, past and proposed, and I blew the whistle on a few points on the moon bounce project and my own pet project on power which has been discussed previously in the column. By the way, several people told me afterward that they agreed with me but hadn't written. Please write fellows, and let us know your opinions, even if they are negative!

Paul, W4HHK, and John, W9WOK, are designing a new i.f. strip to use after V.H.F. converters. This should be the i.f. to end all

i.f.'s. Hope they finish it soon.

W8HOH, Whitey, plans to put his 64 back up soon (after the aurora season, of course) and W8SVI, Bill, (who by the way, very ably directed the V.H.F. activities at the Dayton Hamfest) was going to put his antenna back up the Sunday after the Hamvention. (Didn't see him working on it though, as we drove by his place at 1000 Sunday on the way home. Hi!) Al, W8WXV, will be on as soon as he figures



One of the greatest living two-meter DX men, Al Burson, W8WXV. DB standing next to Al is probably best known as the XYL of W4HHK. She is one of the reasons why Paul is a 28 state man on Two.



VHF men assembled to talk over the contest. Left to right: WIVXW, WIPYM, WIRUD, WIWID, W100P and W1EGE.

out a way to put his antenna up without using a tower. So, it looks like we will have some

more big signal W8's before long.

Found out why Claude, W8SDJ, and Hank, W8IFX, were on that famous morning of February 25th. They were up checking crystal frequencies because Claude found out how to etch crystals and went out and got 60 odd crystals to move into the two-meter band.

Well, after the best time we have had at a Hamfest, Paul, W1PYM, and myself left for home. From what we heard when we got home, we realized why there was hardly any two-meter activity on the way. Too bad we didn't have

a six-meter communicator along, Hi!

So we're home now, recuperating from that 900 mile marathon drive and I'm back on the air. (I put my 32 back up again for the third time after a windstorm, with the help of Sam and son, Pat.) So we'll be looking west again. Hope we have our 128 elements up before the summer is over.

Well, guess I'll close now and see about buying some stock in an aluminum company so I can start getting materials for the big baby.

#### Letters

Dallas, Texas: We hear again from the "Lone Star" state and Bruno (W5ZUL), who

Says:

"As the 'Ft. Worth-Dallas Six-Meter' net grew larger, we decided to change the net to 'North Texas Six-Meter Net' as this name was more rpresentative of the net area. Our last net night showed twenty-seven stations checking in, which I think is a fine showing. I do too Bruno. How long did it take to get them all checked in?

"The majority of the members have not been idle



W4HHK (center) discusses meteor propagation with interested VHF'ers at Dayton

during the winter but have been working on high ouring the winter but have been working on his powered transmitters, converters, beam antennas a other projects. Included in this list is a 750 wand a 200 watt transmitter, So-oo-o when the bapens up soon, we all hope to be there, provide contacts to all who need Texas for a WAS on 'SIX' liberarian' O.M.—Signed, Helen, With' Bruno also listed thirty-three active six-meter stions in the net, W5's and K5's, ten of which also mobile. also mobile.

Ashton, Illinois: The "Prairie" state a Denny (W9JDJ) contributes thusly:

"The band used here is six meters. I run fit watts input to a Harvey Wells TBS 50D. The tenna is a three element rotary beam about twen five feet high. I use a Tecraft converter with a BC-as a variable i.f. stage. Frequencies are 50.25 a

as a variant of the worked that VS6DE has heard W1's, W3's as W0's on Six Meters. If this is true, good dx sho be worked this year." You're not kiddin' about the Denny, surely should be good dx.

Euclid, Ohio: A note from Dave (W8OZF/ and the good old "Buckeye" state:

d the good old "Buckeye" state:

"How about some mention of activity in a around Cleveland, Ohio. Glad to Dave. Glad to. He are some triodes that are being used, VT 12 100TH's, 35TG and 826. My little 'Rock Crusher' z uses a TU-75A to drive a pair of 100TH's at 7 watts input (2500 V. 280 Ma.) with 50 ma. drive. The rack is a 6.5 open frame without a shielding. The home rig will be off the air un April. In the meantime, I will be on with 20 war from Angola, Indiana. I forgot to say that all this is Six Meters." Hurrah, for you Dave, good hear from the Cleveland territory again.

Dayton, Ohio: Another "Buckeye" in th form of Amos (W8INQ) comes forth with:

"Would like to sked any station in Michigan this using about same set-up. Miller 90810 Transmitted 829B final, 4 element beam, crystal converter to a NC240 D. Power is 45 watts because of Channel Have skeds on Tuesdays and Thursdays of each west with the following stations: 2150 EST with W8EV Ernie in Columbus, Ohio; 2200 with W9MHP, De in Indianapolis, Indiana; and at 2215 the above two stations have a sked to try to make contact." How about a sked with Massachusetts, Amos. I'm reach any old time. Signed—W1HOY.

The Stamford, Connecticut: "Nutmeg state and John (W1BOM) say:

"Have a five over five beam to go up fifty fewhen the weather is warmer. Haven't you ever hear John, that the worse the weather, the more antenne go up? Also have a Tecraft converter working into 75A3. Hope to have a fifty watt rig on when the beam goes up." Hope you do John, we'll surely se

**Portland, Oregon:** Floyd (W7RGS) from the "Sunset" state emits with:

"We have done quite a little work on 50 mc an "We have done quite a little work on 50 mc an have some big beams coming up for next summed Yeh, man! We've heard some bursts on Six an some good S9 signals from W6 land around 9:00 p.m. and we all think that more power and big beam will help greatly. Have 18 states on Six Meters.. Agree with you on the beams and power, Floyd. Hope to see you on the band soon.

Rensselaer, Indiana: A "Hoosier," Bill (W9KLR) comes forth with:

"I don't claim to be much of a c.w. operator, but at least I have made aurora contact with W2CXY. W2WFB, W2RXG, W2CCR, K2IXJ, etc. I don't eithe Bill. You don't have to be a forty words a minute marfor aurora. Those were on the aurora sessions of January 24th and 27th. There were several W1's coming through on February 28th including Rhode Island Connecticut and Massachusetts."

Jackson Heights, New York: Make what you can or what you wish from the following short but graphic note from Fred (W2AMB) resident of the "Empire" state:

"Hi, Sam! Yea Boy, SSB on V.H.F.! 73 and cutherel" Golly, wonder what he could mean.

72 • CQ • June. 1956 Oil City, Pennsylvania: The "Keystone"

tate says by way of Joe (W3LST):

"A few lines to let you know it is very likely that I will be on the air with my new rig with a small change of plans. Instead of 600 watts to 4X150, it is now a KW to 4X250's. However, I will not be able to run that much power input until I rewire my shack." Funny thing how something like rewiring a shack or something like it always seems to interfere at the wrong moment. Get with it Joe. Lots of aurora.

Elizabethtown, Kentucky: Our old standby Shelby (W4WNH) from the "Blue Grass" coun-

ry comes through again:

"About 0800 Saturday, February 25, my rotor tore in two, pitching the beam 30 feet to the ground. In falling, it caught my ten meter doublet and pulled it across two sets of power wires. So I had to go out while the wind was still blowing about 40 miles per hour and shoot the insulators in two. A relative of Dan'l Boone maybe?

"I set a 5 alternat year unstains to well. There

of Dan't Boone maybe?
"I set a 5 element yagi upstairs to work Tom (W4HJQ), but a few days later he lost his beam. Welcome to the clan, Tom. His beam was hanging upside down by its feeder, fifty feet up. Eurekal Someone is ready for Moon Bounce. Also about this time, the beam of K4ESD bent over. Now it looks at the ground toward the north and looks at the moon toward the south.

moon toward the south.

"I now have a new rotor and new beam but they aren't up yet. March 24th, Tom took his beam and 50 foot crank-up tower down and put up a 50 foot windmill tower. The reason—he very soon hopes to have a 96 element beam on it. Just a 'little' one. "Received a letter from W4PCT/Ø, who is in Iowa now. He doesn't expect to get back on two until later this year." Antennas, beams, guys, etc., sure can make hum radio interesting (?). How about a "Two-meter Beam is Down' club?

Fairfield, Connecticut: Another epistle from the "Nutmeg" state, this time via WIREZ):

"Since we're running high power now we have since we're running high power now we have given first Connecticut contacts to quite a few stations in Western Pennsylvania, Western New York, Ohio, Michigan and Indiana. The big beam is going up this month (April) at sixty feet, when we will start skeds for scatter tests. Anyone interested?" Hope there will be lots of takers on that Ray and good luck with the big beam.

Ontario, California: The "Golden" state con-

ctributes the following, via Don Stoner:

"As you know, the 416 is an expensive jug, but I think that I have found a good substitute. There are quite a few of those UHF radio sonode balloon transmitters floating around the west coast (no pun intended). I pulled out the cavity oscillator and dismantled same. The cavity contains a 5794 pencil triode that is hotter than a spark gap, I installed it in our two-meter converter and obtained a noise figure of 3.2 after diddling the input coil. Thought your readers might be interested." Thanks Don, our readers are interested in anything and everything concerning VHF so I know they'll be glad to know about this. about this.

Sacramento, California: A fellow "Gold-hunter" Lloyd Lane (W6APE) sez:

"I have an NC24OD and would be very happy if you would give me the details on just how you accomplished the installation of the low-noise figure front end." Lloyd, to you and the many others who have inquired about this modification; there will be an article in the near future in "CQ" concerning

**Tarpon Springs, Florida:** Dick Barry (K4DMB) from the "Flower" state relates the

following tale:

"As of this writing, I have nothing but a long line of C.Q.'s in my log. What happened to the sixmeter operation at Leesburg and Lakeland, Florida. Hope you boys have a good excuse.
"I have a four element beam, Tecraft converter and an S-77A receiver. Later on intend to go about

500 watts.
"Does anyone have any actual operating characteristics of the WE-701A. Would appreciate hearing



The operating position at K4DMB. Dick is working on a 500 watt final to make it easier to work Florida.

from anyone. Also interested in hearing from anyone in this area who might be getting on 220 Mc." Don't know how activity usually is on six meters down there Dick, but it surely was there for the band-opening on the fifteenth of April.

Langhorne, Pennsylvania: Another "Pennanite" heard from by the name of Ray and the call W3TDF:

"My letter which you reprinted brought to light some activity in Charleston, South Carolina. However, still no news of activity between there and Orlando, Florida. Also am trying to locate WlGJO who is now in Ft. Myers, Florida, to fill in the gap to Miami. For these reasons the East Coast Relay will have to be postponed possibly until June or July." Hope you find that fill-in station Ray.

Maryville, Tennessee: From the "Volunteer" state and W. J. Huffstetler (W4BXG) comes:

"This has been a very progressive month (March) for the two-meter activity in East Tennessee. On the 17th of March, several of the stations here made thir first Georgia contact with W4ZXA/4 just north of Dahlonega. KN41BS is now on the air with a new 32 element colinear beam and there are eight more such antenna's scheduled to go up here in the very near future. Yeah man! W4UVU in Athens is now on Two Meters with a good signal. W4LNB has a new thirty-two element antenna that is sixty feet up in the air. Needless to say he also puts out a good signal. O.K., we won't say it then. W4LNB reports that there is to be a two meter station located on top of the mountain at Chattanooga with an antenna approximately 200 feet above the top of the antenna approximately 200 feet above the top of the

"The Smoky Mountain Amateur Radio Club will be operating from a 6000 foot Field Day location in the Great Smoky Mountain National Park and using a Gonset Communicator and feeding a thirty-two element horizontal beam. We will be using the club call W40LB/4." Glad to hear of the progress in Tennessee, O.M., and also to hear about the Field Day location.

Salt Lake City, Utah: Ken (W7WLV) from the "Land of the Mormons" comes forth with the following:

"Looks like kind of a dead season for six-meter openings around here. Have not heard any so far." Think you will have by the time this is in print Ken. We've had several beautiful openings to the west, and expect more. Now have my four element beam up.

Shelley, Idaho: We hear the following from Louie (W7ACD) and the home of the "Idaho Potato":

"I have been active on the 50 mc band for some years now and have worked forty-four states. Starting May 15th of this year I will be monitoring 50 mc most of the time and will be on 50.100 and 50.156 most of the time. If the band is wide open and lots of QRM I'll be on 50.580.

"I am using a four element beam with a pair of 75TL's, 400 watts. I have two receivers, a VHF 152A and Tecraft converter.

"I am especially watching for Rhode Island, Vermont, Utah and Montana. Am afraid it will be mighty hard to work Utah and Montana although there is more activity in Utah this year. But Montana is inactive. O.K. You Montana boys, let's hear some howls of negation.

[Continued on page 98]

#### Last Minute Forecast

Most probable periods of ionospheric disturbances during June are June 15-17 (moderate) and 19-21 (severe) with a good possibility of extensive aurora occurring during the latter period. Exceptionally good short wave radio conditions are forecast for the period June 3-9.

	ALT. TI	MES IN EST				ALL TI	IMES IN CS	T	
EASTERN USA TO:		· 15 Meters	20 Meters	40/80 Meters	CENTRAL USA TO:		15 Meters	20 Meters	40/80 Meterr
Western Europe	1300-1700 (1)	0700-1300 (2) 1300-1800 (4)	1400-2200 (4) 2000-0200 (3)	1830-2000 (2) 2000-0100 (4)	South East Asia	NIL	1700-2200 (2)	1600-0000 (2) 0600-0900 (2)	NIL
Southern	1200 1600 11	1800-2000 (2)	0200-1400 (2)	0100-0300 (?) 2030-0000 (±)* 1800-2100 (3)	Hawaii	1800-0000 (2)	0000-0200 (2) 1000-1500 (3) 1500-0000 (4)	0000-0300 (4) 0300-0800 (3) 0800-1900 (2)	2200-0630 ( 2300-0530 (
Southern Europe & North Africa	1200-1500 (1) 1500-1700 (2) 1700-1830 (1)	0700-1300 (2) 1300-1800 (4) 1800-2000 (2)	0300-0600 (2) 0600-1300 (2) 1300-1600 (3) 1600-2200 (4) 2200-0300 (3)	1800-2100 (3) 2100-0000 (4) 0000-0200 (2) 2100-0100 (2)*	Australasia	1800-2200 (1)	1600-1800 (2) • 1800-2200 (3)	1900-0000 (5) 0200-0400 (3) 0400-1000 (2)	0200-0600 (3 0230-0500 (2
Near & Middle East	1400-1700 (1)	10900-1300 (1) 1300-1600 (3) 1600-1800 (2)	1300-1700 (2) 1700-2100 (4) 2100-2300 (3) 2300-0300 (2)	1900-2300-(2) 2000-2200 (1)*		AI.I. TI	2200-0000 (2) MES IN PST	1800-2200 (3) 2200-0200 (4)	
Antarctica	1300-1500 (1)	1300-1500 (2)	1500-1630 (2)	2200-0500 (2)	WESTERN USA TO:		15 Meters	20 Meters	40/80 Meters
	500 (1)	1500-1700 (2)	1630-1630 (2) 1630-1730 (3) 1730-1900 (1)	(0)	Europe & North	NIL	0800-1300 (2)	1400-1600 (2)	1800-2100 (1
South America	0900-1200 (2) 1200-1400 (3) 1400-1800 (4)	0500-0900 (3) 0900-1500 (2) 1500-1700 (3)	0200-0600 (3) 0600-1600 (2) 1600-1900 (3)	1900-2200 (2) 2200-0500 (3) 2000-0400 (2)*	Africa		1300-1300 (2) 1300-1800 (3) 1800-1930 (2)	1600-1800 (2) 1600-1800 (3) 1800-2100 (4) 2100-0100 (3)	1830-2030 (1
Parith P	1800-2100 (2)	1700-2100 (4) 2100-0100 (3)	1900-0200 (5)		Central & South Africa	NIL	2100-0000 (2) 0900-1100 (2) 1100-1400 (3)	2100-0000 (3) 1400-1600 (2) 1600-1900 (3)	1900-2300 (2 1930-2200 (1
South East Asia	NIL	0600-0800 (1) 1700-2100 (2)	0600-0900 (2) 1700-2100 (1) 2100-0000 (2)	NIL	South America	1000-1200 (3) 1200-1700 (4) 1700-1900 (2)	0500-0700 (3) 0700-1300 (2) 1300-1600 (4)	0700-1400 (2) 1400-1600 (3) 1600-2300 (5)	1800-0200 (3 2000-0100 (2
Australasia	1900-2300 (1)	0700-0930 (2) 1700-1900 (2) 1900-2130 (3) 2130-2300 (2)	0000-0300 (4) 0300-0600 (2) 0600-0800 (3) 0800-0900 (2)	0200-0500 (2) 0230-0400 (1)*	Guam & Mariana	1600-1900 (2)	1600-1900 (5) 1900-0000 (2) 0800-1200 (3)	2300-0700 (3)	0100 0000
Guam & Pacific	NIL	2130-2300 (2) 1600-1900 (2) 1900-2100 (3)	0800-0900 (2) 1800-0000 (3) 0100-0530 (2) 0530-0800 (3)	2300-0300 (1)	Guam & Mariana Islands	1600-1900 (2) 1900-2300 (3)	0800-1200 (3) 1200-1900 (2) 1900-2300 (4) 2300-0200 (2)	0600-0900 (4) 0900-1200 (2) 2000-2300 (3) 2300-0200 (4) 0200-0600 (3)	0100-0500 (3 0200-0400 (2
		2100-2300 (2)	0800-0930 (2) 1800-2100 (2) 2100-0100 (3)		Australasia	1200-1500 (2) 1500-1800 (3) 1800-2000 (4)	1100~1800 (2) 1800~2000 (3) 2000~2300 (4)	0200-0600 (3) 0200-0800 (3) 0800-1100 (2) 1900-2100 (2)	2300-0630 (3 0000-0400 (1
Japan & Far East	NIL	1700-2100 (2)	0000-0600 (2) 0600-0830 (3)	2100-0100 (1)		2000-2200 (2)	2300-0200 (2)	2100-0200 (4)	
Greenland	NIL	0900-1300 (1)	1700-2100 (2) 2100-0000 (3) 0600-1500 (3)	1700-1900 (2)	Japan, Okinawa & Far East	NIL	0700-1200 (3) 1200-1800 (2) 1800-2200 (4) 2200-0100 (2)	0000-0600 (3) 0600-1000 (4) 1000-2000 (3) 2000-0000 (4)	0100-0500 (3 0200-0400 (2
		1300-1730 (3) 1730-1900 (2)	1500-2100 (4) 2100-0600 (2)	1900-0300 (3) 0300-0500 (2) 2100-0200 (1)*	Philippine Islands & East Indies	0900-1100 (1) 1400-1600 (1) 1900-2300 (2)	0800-1100 (3) 1100-1500 (2) 2200-0000 (1)	0000-0200 (1) 0200-0800 (2) 0800-1100 (3) 1100-1300 (1)	0400-0600 (1
		IMES IN CS			Malaya & South	1800-2200 (1)	0900-1400 (3)	0100-0400 (1)	.0400-0700 (1)
CENTRAL USA TO:	10 Meters	15 Meters	20 Meters	40/30 Meters	East Asia		1400-2200 (1) 2200-0000 (2)	0400-0800 (2) 0800-1200 (3)	
Western Europe	1200-1400 (1)	0700-1000 (2) 1000-1500 (4) 1500-2000 (2)	0400-0600 (2) 0600-1400 (1) 1400-1700 (2) 1700-2200 (4) 2200-0400 (2)	1800-0100 (2) 1930-0000 (1)*	Hong Kong, Macao & Formosa	0700-0900 (1) 1900-2300 (1)	0700-1006 (4) 1000-1500 (3) 1500-2200 (1) 2200-0200 (3)	0000-0300 (2) 0300-0600 (3) 0600-1400 (2)	0200-0600 (2 0300-0500 (1
Southern Europe & North Africa	1200-1700 (2)	0700-1200 (2) 1200-1800 (4) 1800-2000 (2)	0300-0500 (3) 0500-1300 (2) 1300-1500 (3) 1500-2000 (4) 2000-0300 (2)	1800~0100 (3) 2000-2230 (2)*					
Central & South Africa	0800-1200 (2) 1200-1500 (1) 1500-1800 (3)	1300-1500 (2) 1500-2000 (3) 2000-0000 (2)	1300-1500 (2) 1500-1700 (3) 1700-2100 (4) 2100-0300 (2)	1900-0000 (2) 2000-2200 (1)*			DAYS CIRCUIT F		
Central America & Northern S. America	1200-1400 (2) 1400-1700 (4) 1700-1900 (2)	0600-0900 (4) 0900-1400 (3) 1400-1600 (4) 1600-2000 (5) 2000-0200 (3)	0000-0500 (3) 0500-9800 (4) 0800-1400 (3) 1400-0000 (5)	1900-2200 (2) 2200-0400 (3) 0400-0630 (2) 2000-0300 (2)*			12-18 days (4) 1		over 26 days
South America	0800-1100 (2) 1100-1800 (4) 1800-2000 (2)	0600-0800 (4) 0800-1400 (3) 1400-2100 (5) 2100-0100 (4) 0100-0600 (1)	0800-1400 (1) 1400-1800 (3) 1800-0100 (5) 0100-0800 (3)	2000-0400 (3) 0400-0630 (2) 2030-0400 (2)	and Sacram	and are centered nento, California	s are based upon on Washington, I	D. C., St. Louis sts are calculated	s, Mo.,
Japan & Far East	NIL	1600-1800 (2) 1800-2100 (3)	0600-0830 (3) 1700-1900 (2)	0000-0530 (1)	basic ionos	spheric data publ	lished by the CRP through July 15,	PL of the Nationa	al Bureau

0600-0830 (3) 0000-0530 (1) 1700-1900 (2) 1900-0200 (3)

June, 1956



Forecasts By: **George Jacobs**, W3ASK/W2PAJ 607 Beacon Road Silver Spring, Md.

eneral Propagation Conditions, June:

On June 21st the summer solstice will occur. is is the day that the sun reaches the most of them point on its apparent travel from athern to northern skies. This phenomenon arks the beginning of the summer season in Northern Hemisphere and also has a solutions

Because the sun is more directly overhead, at radiated from the sun during the summer onths strikes the earth more directly than ring the winter months. This direct, and Erefore more intense heat radiation causes gases that exist in the region of the ionohere to expand. As a result of this expansion electronic density of the ionosphere, or degree of ionization per unit volume of the nosphere, decreases. This reduction in elecn density means a weaker F-2 layer in the hosphere during the daylight hours of the mmer months as compared to the stronger nized daytime layer of the winter months. uring June and the summer months, the asonal trend in the Northern Hemisphere is r lower daytime maximum usable frequenes. This will be particularly noticeable on the meter band where fewer DX openings are pected to occur than did during the winter d spring months.

On the other hand, during June and the mmer months, the hours of daylight are nsiderably increased. This permits ionization the various layers of the ionosphere to cur for a much longer period of time than assible during the shorter hours of daylight the winter months. Since there are also wer hours of darkness during the summer onths, there is less time for the reflecting yers of the ionosphere to de-ionize. This imbination results in a considerably stronger nized layer during the late afternoon and rening hours of June and the summer months and during the winter months and frequencies high as the 20 meter band will be reflected

during the entire period of darkness and around the clock. The 15 meter band should be usable from dawn until past midnight, *local standard* time.

During June and the summer months, atmospheric noise and static levels continue to increase and will be most noticeable on the 160 and 80 meter bands and to some extent on the 40 meter band. Ionospheric absorption also tends to increase somewhat during June and the summer months, and signal levels during the daytime hours may be weaker than during the winter months.

June and July are the most active months of the entire year for short-skip Sporadic-E propagation and frequent openings, up to about 1400 miles, are expected on the 6, 10 and 15 meter bands.

The following is an overall picture of band conditions forecast for June, 1956, with a brief discussion of the qualitative changes in each amateur high frequency band from month to month. For specific times of band openings for a particular DX circuit, refer to the CQ Propagation Charts appearing on the opposite page.

#### 6 Meters:

A considerable number of openings are expected between skip distances of approximately 1000 and 1400 miles as a result of the seasonal increase in sporadic-E type propagation. For a small percentage of time two-hop sporadic-E propagation may also be possible between most areas of the United States and Central America. The geometry of propagation is such that as the shortskip distances decrease on the 10 and 15 meter bands, the frequency that will be reflected by the sporadic-E cloud is increasing. When the skip distance on 10 meters is observed to be less than 500 miles, chances are very good that 6 meters will open in the same general direction, with the skip distance out beyond 1000 miles.

#### 10 Meters:

World-wide DX conditions remain fairly good despite the fact that the band will open on fewer days than during the winter and spring months. Conditions are expected to be optimum from shortly before noon to shortly after sundown, local standard time. Sporadic-E, short-skip propagation between skip distances of 750 and 1400 miles should be possible for at least 25% of the time during June. Late afternoon and early evening regular layer F-2 propagation, between skip distances of 1300 and 2400 miles, is also expected on several days.

#### 15 Meters:

Exceptionally good world-wide DX is expected daily from shortly after sunrise to midnight. During periods of exceptionally good propagation conditions, the band may remain open around the clock on north-south circuits to Central and South America. Optimum DX conditions will occur from shortly after noon through the early evening hours. A considerable increase in sporadic-E, short-skip, propagation will occur with skip distances between 250 and 1300 miles. Regular layer short-skip propagation, with skip distances between 1300 and 2400 miles, is expected from about noon to midnight, peaking in the late afternoon and early evening hours.

#### 20 Meters:

As a result of the seasonal propagation trend, and the rapid rise in solar activity, the 20 meter band will be exceptionally good for world-wide DX around the clock. Conditions will be optimum from late afternoon until midnight, but DX from some area of the world should be coming through at all hours. Short-skip propagation will also be possible around the clock, with the skip distance as short as 250 miles at noon time, and extending beyond 2400 miles during the late afternoon and evening hours.

#### 40 Meters:

Despite higher ionospheric absorption and static levels, fairly good DX propagation is expected from shortly before sunset to

about sunrise, local standard to Short-skip propagation will possible around the clock, withe skip distance as short as miles during the late afternations. During the daytime hostonospheric absorption will lift the maximum range on this base to about 750 miles, with the sincreasing to beyond 2400 m as the hours of darkness approar

#### 80 Meters:

DX conditions will be no better than fair, and in general ration poor on this band during summer months. Static levels who considerably higher and significant the daylight hours, absorptivill limit maximum range about 200 miles or less, increasing to beyond 2400 miles during thours of darkness.

#### 160 Meters:

During the daylight hours sk wave propagation will not possible because of excessionospheric absorption, and make mum range will be limited about 25 miles or so from the transmitter. During the hours darkness, when ionospheric as sorption is minimum, skywa propagation up to distances 1300 miles should be possible and when static levels are exceptionally low, the skip may extend upwards to 2400 miles.

#### Sunspot Data

The Swiss Federal Solar Observatory report that the monthly Zurich sunspot number for March, 1956 was 116. This results in a previsional 12-month smoothed sunspot number of 55 centered on September, 1955. All propagation data utilized for this month's forecast are based upon a predicted smoothed sunsponumber of 120 centered on June, 1956.

Latest reports from the Swiss Observator continue to confirm the fact that the comin sunspot maximum will be one of outstandin intensity. According to the latest predictions of the Swiss Observatory, the maximum of the present sunspot cycle may occur as early as February, 1957, and will be higher than an one previously recorded, with the maximum smoothed sunspot number forecast to be of the order of 170. Because of the direct con relation between sunspot activity and ionor spheric characteristics, shortwave radio conditions during the next few years may be better than they have ever been in the histor of radio.

A considerable amount of favorable

nment has been received regarding Part 1 "The Sunspot Story: Cycle 19" which apared in the March issue of CQ. In this icle, of timely interest to all amateurs, the ects of this unprecedented rise in sunspot ivity upon ionospheric propagation is dis-issed. Part 1 reviewed the origin of sunspots if the effects of solar radiation upon the osphere and discussed the present sunspot le trend and the trend expected over 'the ltt few years. Part 2 of this timely article apars in this month's issue of CQ. It further cusses the effects of increased sunspot activin relation to ionospheric propagation conlions in each amateur high frequency band through 160 meters. Possible once in a lifene conditions on the 6 meter band is also cussed as well as the effects of the rapid e in sunspot activity in the VHF spectrum d the possibility of long distance, world-wide 7. Other phenomena believed to be associ-4:d with the sunspot cycle are also briefly disssed. Don't miss it, it appears elsewhere in is month's copy of CQ.

#### Solar Eclipse

As mentioned last month, a total eclipse of the sun will occur on June 8, 1956. It will be visible, clouds permitting, over vast areas of the South Pacific. While not visible in the United States, its influence upon shortwave radio will no doubt be noticed here on signals passing through the area of eclipse. Since the ionosphere is cut off from the sun during the period of total eclipse, we can expect that signals passing through this area will exhibit a night time effect, that is we would expect an improvement in reception on the night time wavelengths of 40 and 80 meters, and a decrease in signal levels on the daytime 10, 15 and 20 meter bands. This effect has been found to exist during previous eclipses and was quite noticeable during the eclipse of June, 1954, which occurred over the United States. I would be very interested in hearing from readers who may notice such effects during the total eclipse of June 8, 1956.

73, George, W3ASK/W2PAJ

### QSL Contest Winner

This month another DX winner, OZ7FG. Fortunately the impartial, unbiased, stead-fast Official Judging Group holds itself dignifiedly aloof from our greying circulation manager, who by now only moans a little when we tell him another DX station has won (DX subscriptions cost quite a bit more, you know). So you can see that, were we not impartial, unbiased, and steadfast as we are, we would not be erring in favor of the DX men. No, sir, boy. They just happen to be sending better cards, most of the time.

Now, shouldn't it be the other way around? I mean, a DX station can send out almost

any kind of a card and it will be well-received stateside. But don't you think that, added to the deadening similarity of most stateside QSO's, the DX ham may get a little weary of answering stacks of stereotyped QSL's?

(Winners in CQ's monthly QSL Contest receive a 2year subscription to CQ)



#### runners up







as reported by

#### Byron H. Kretzman, W2JTP

9620 160th Ave., Howard Beach 14, N. Y.

Filters. That appears to be the bug-a-boo that has caused many would-be RTTYers to shy away from this relatively new and fascinating phase of amateur radio. Early amateur radio-teletypers built their audio tone mark and space filters out of filter chokes and small receiver output transformers. Today's ewell-informed, and active, RTTYer invariably uses high-Q toroidal inductors in the terminal equipment that he builds. Here-to-fore, toroids were not too easily available. The surplus C-114A loading coils, (CQ, Jan. '56) for example, are just not to be found on the east coast.

Things are looking up now, though. A few months ago an advertisement for "RTTY Filters," allbeit expensive, intrigued me. Writing to the manufacturer, D & R, Ltd. of Santa Barbara, California, it was discovered that the

#### AMATEUR RADIOTELETYPE CHANNELS

**National, FSK** (mark frequencies; space 850 cycles lower) 3620, 7140, 27,200, 29,160, 52,600 kc.

National, AFSK (2125 cycles mark; 2975 cycles space) 27,200, 147,960 kc, calling & autostart; 144,138 kc. repeater & duplex

California, AFSK 147,850 kc. calling & autostart

Washington, D. C. AFSK 147,960 kc. calling & autostart; 147,495 kc. working

**Chicago, AFSK (FM)** 147,700 kc. calling & working

**Detroit, AFSK (FM)** 147,300 kc. calling & working

New York, AFSK 147,960 kc. calling & working

"D" stood for Ray Dawley, W6DHG, a for editor of the old pre-war Radio. Subsequence correspondence with Ray disclosed that high cost of those filters lay in the casing, ting, and hermetic seals required for milicapplications. Ray will make available to a teur RTTYers those very same filters, but cased, at a considerable reduction in cost addition, simple uncased 88 mh. toroids (no can be had for around \$2.25 each, which



Mark and Space Filter Assembly.

doggone good bargain, as anyone who has even unpotted a C-114A on the XYL's kitchen storial

The accompanying photo shows an assembly of the mark and space filters mounted together Fig. 1 indicates the response curves for the filters. Note, in particular, the broad, flat, top This permits a practicable amount of tranmitter and receiver drift without causing bill distortion. Five toroids in each filter are en ployed to get this kind of response. Fig. 2 show one type of circuit for driving these filter which are of 600 ohms impedance. The banpass filter is of similar construction, and ha the response curve depicted in Fig. 3. By maling the proper connections, 500 to 15,000 ohm 15,000 to 15,000 ohms, 15,000 to 500 ohms, 4 500 to 500 ohms impedance transformation are possible. The nice part of this whole deal that these filters can be purchased from D & for only \$16 each. To the best of our knowledg Dick Urian, W3CRO, Demonstrates a Printer Selector Unit.



this is the first time that completely adjusted high-Q filters have been available to the amateur RTTYer at a reasonable cost.

This month we have omitted the usual "RTTY Principles & Practice" section in your RTTY column in order to bring you the above story on the availability of filters and toroids. So many fellows have said that they would like to get on RTTY but were afraid to tangle with toroids. (Have you ever wound any, yourself?) I Adjustment of filters can be tricky as well as time consuming, but if you still want the fun of tuning up the toroids, the high-Q coils available from D & H will permit you to build a very fine set of filters yourself. Next month we hope to bring you a section devoted to tape equipment. Use of perforated tape can really move traffic on an RTTY net.




Fig. 2. Cathode Follower Filter Circuit.

"Where can I find some basic information on Teletype?" This is the question most often asked of your RTTY editor by so many hams, old and new, fellows who have become aware that something else besides the International Morse Code is being transmitted in our "CW" bands. Only recently, the Teletype Corporation, the manufacturer of just about all of the teleprinter machines that we use, has brought out a very informative booklet called, "The ABC's of Teletype Equipment." This skillfully prepared booklet not only discusses the fundamentals, terminology, and use of teleprinter transmission, but illustrates them as well with excellent drawings and pictures, including pictures of the related machines. It covers tape transmission and equipment as well as the page printing gear that most of us are familiar with. The booklet can be obtained simply by writing to:

> Teletype Corporation J. G. Hammer Department 1261 RTTY 4100 Fullerton Avenue Chicago 39, Illinois

#### **NYC RTTY Dinner**

The RTTY dinner held in New York City on March 19th was a howling success, with the wind doing most of the howling. In spite of the worst storm of the winter to hit New York, 38 hale and hearty RTTYers showed up. Some of the fellows from southern New Jersey spent most of the day getting there, too. Nine others didn't make it at all.

Phil Catona, W2JAV, and Dick Urian, W3CRO, teamed up to put over a bang-up talk on the Model 26. Phil discussed in fine detail the importance of ranging, distortion, and range-finder adjustment. Dick had brought up a Model 26 in a suitcase—disassembled! He used the various parts to illustrate difficulties, their correction, and other important adjustments. He didn't try to explain, of course, how and




Fig. 1. Frequency Response Curves, Mark and Space Filters.

why W2BDI's Model 26 could back-space! (Ed swears it's true!)

Merrill Swan, W6AEE, spoke briefly about west coast activity and the possibility in the future of obtaining FSK privileges for the 160 meter band. F. E. Handy, W1BDI, suggested that we contact our ARRL Directors concerning this matter. He said that the "... Coast Guard was not unfavorable." Ed also commented that the ever increasing attractiveness of RTTY was because it was "... an accurate and fast means of handling traffic." Jack Berman, W1BGW, spoke of the new birth of 2 meter AFSK ac-




Fig. 3. Frequency Response Curve, Band-Pass Filter.

tivity in the Boston area. Jack said that their are 16 stations on, including W1FZJ, CQ's VH Editor. Wayne Green, W2NSD, ye Editor spoke briefly on single-sideband. It was recalled that someone using an SSB exciter for RTT was cited for spurious frequencies, and it was suggested that extreme caution be used. Bo Straub, W2PBG, reported on his survey of 4 meter band occupancy, the object in view of abandoning 7140 kc as the "national" RTT frequency. Bob reports that, from his point of view, (New York City) 7105 or 7110 kc would be infinitely better. Joe Juel, W9BGC, spoke of the probability of another RTTY Meeting i Chicago this coming October. Joe asked tha each fellow drop him a card with comments.

W9NOE won a subscription to *CQ* and W2LLR won a subscription to *RTTY*. Polar relays, given as door prizes, were won b W2ZKV, W2AKE, and W3FMC. Dick Urian W3CRO, won a copy of TM 11-680, "Tele typewriter Circuits and Equipment (Fundameters)

mentals)"!

Those who attended were, W1AFN, W1BD W1BGW, W1EVZ, W1FGL, W1FZJ, W1RBF W1WB, W1WEW, W2AKE, W2AVI, W2BDI W2EBZ, W2GHH, W2JAV, W2JTP, W2KXT W2LLR, W2MIB, W2NSD, W2PBG, W2PTD W2QGH, W2QQG, W2RMB, W2TBD W2ZKV, W3FMC, W3CRO, W3MHD W5UHV, W6AEE, W6DRL. W9BGC W9NOE, KØDFR, W9TPU, Rud and Couppez.

Those who didn't quite make it because of the storm, were, K2CSC, K2HHJ, W2IRT W2JYD, W2OOG, W2PAU, W2PEE, W2TKO

and W4LNW.

This NYC RTTY dinner was better than las year's. Next year we hope it will be better than this year's. At least the weather has a good chance of being better! (It couldn't be worse!) See you all there.

#### Across the Nation

W3LGK and W3MHD have worked out a system of break-in which permits rapid interchange of RTTY communication. Each installed a microswitch so that it would be actuated by the bell lever. (upper case "S") This switch, via a ratchet relay, then alternately places the printer, and transmitter, in a send or receive condition whenever the bell is rung—once. Of course, operators must be present. FCC approval was obtained. (See Feb. '56 RTTY).

W7JFU received his Model 12 with an a-c motor on the keyboard/distributor and a d-c motor on the printer! For anyone in a similar fix, see the de-hashing dope for d-c motors in the RTTY column in the April '56 CQ. W7JLF in the Olympia-Thurston County part of Washington offers to help anyone in his area that is interested in RTTY. Sam uses his Model 26 with a W4TJU TU, a BC-348, and a Ranger, on 40 meter FSK.

W5WZF, a technician in Houston, Texas, is all fired up on 6 meter AFSK on 52.6 Mc. Bill frould like to exchange tape-recorder (3.75 ma/sec) tapes of AFSK with anyone interested. It will also be looking for any other RTTYers at the Galveston Convention in June. W5AXY, Austin, Texas, has a Model 19 complete except for keyboard. Lee reports, "There are quite a lew of the fellows down here trying to get on, but we all need a lot of help." Any volunteers for the Austin area? KØDFR, ex-W5IJC, is low in St. Louis. Baity says there is little activity in his area. Can that be?

W2ANB, and XYL W2ZPR, have a Model 5 and some tape gear working on local loops. ust the simple matter of hooking up to the transmitter and receiver remains, John reports. V2PEE still hasn't found a printer with weather

lymbols. Can anybody help?

VE3BAD of Toronto, Canada, is putting a me signal into New York City on 3620 kc. George has been investigating various types of f converters. VE7KX, on Lulu Island, Vanouver, and SS contest winner, pours a good dignal into the east coast on 40.

W1FGL reports that he, W1WB, W1WEW, and W1EFF, of Gray, Maine, are now proud

possessors of Model 26's.

WØSV has worked out a tone standard using

gears which will be described shortly in this column. W4LMN is using a simplified method of frequency shifting his VFO directly from the keyboard of his Model 26. This, too, will be described in detail in a forthcoming column.

#### Comments

When your RTTY column was started, we said that the basic purpose was to serve as a communication center for information concerning radioteletype. One of the ways that we have been trying to do this is to bring to your attention books and articles in other periodicals of special interest to the RTTYer. This month, of particular interest to those of you that are designing and building converters, we suggest that you read "Bandwidth Requirements of SW Radio Telegraphy," by J. B. Moore, in the March '56 issue of Tele-Tech & Electronic Industries magazine. This is an absorbing, but not too theoretical, treatment of a subject of great importance to all of us who are continually searching for the ultimate in converter design.

Since the Fritz Franke converter, (Nov. '54 RTTY) and W2BDI's version, little has been seen of anything new in the way of an i-f converter design. W2JTP is just starting one at this time. Is anyone else working along these lines? Let's hear from you. 73, Byron, W2JTP

#### Windblowers Four State Jamboree

The Windblowers VHF Society, certainly one of the most aggressive VHF clubs in the country, set up four stations in four states on April 28th and for twelve hours worked every wo-meter station they could hear. Since cerificates were promised for all stations that nanaged to work all four of the Windblowers here was no shortage of contacts. All four tations were set up in good locations with easonable power and good vertical and horizontal antennas. W3CIP/3 thundered into New York, some 75 miles away, and that was he furthest of the four.

A preliminary report from the foursome

zives the following results:

Station .	Location	Nr.	Contacts	Certificates
W2IMG/2	Middletown,		180	9
W2IMI/1	N. Y. Redding Ridge, Conn.		142	48
W3CIP/3	High Knob, Pa.		157	24
W2GEX	Tenafly, N. J.		178	25

When any station contacted his fourth Windblower he gave his QTH so they could send the certificate. This also made it simple for the Windblowers to know just how many stations had managed to qualify. The total number of certificates was 160. Last year's Big Blow resulted in only 64 certificates so it would

seem that interest in this event is on the rise.

Each of the stations had their own miseries and fortunately there were plenty of extra hands around to build and repair while the operators kept something on the air. W3CIP/3 was off the air for an hour when a fierce storm struck. The tent had to be taken down to keep it from blowing away and the beams had to be hastily struck. Despite the high winds and heavy rain they had a good time. W2IMI/1 also had a bad storm to cope with. This one rain-soaked their generator which then had to be taken into the trailer and cleaned inside and out. Net: 30 minutes off the air. And such static! W2IMG/2 had to spend two hours on a Gonset Communicator while a new fuel pump was installed on the generator. This didn't really hurt the signal much though, for what is a few db when the signal is 30 db over 9? The crew at W2GEX had the toughest time of all. This station, operating at the home QTH of W2GEX, had to cope with a full-fledged roast beef dinner and all sorts of other goodies served by the XYL. No other problems were encountered.

Activities of this nature are good for the two-meter band and it is hoped that other clubs will work up some activities which will benefit themselves and the VHF's.



reported by Walt Burdine, W8ZCV Waynesville, Ohio

The big Dayton Hamvention has passed. If you were there, I'm sure I met you. If not, you sure missed a good time. There were 1924 guests registered during the day. Anyone that attended the Novice and Technician Forum, listened to the two wonderful speakers appearing on that forum, and didn't go away determined to be a better ham really missed the boat and can start his other hobby. Lew Mc-Coy, W1ICP of ARRL's Technical Staff warned us of the big increase in second harmonic radiation notices from the FCC that are appearing in Novice mailboxes. Let's clean up those signals. Read your handbook and the Novice Shack for May. Lew has your interests at heart, do you?

John L. Reinartz, K6BJ was the main speaker. "Instrumentation In The Hamshack" was his subject. If you ever get a chance to hear this speech, don't let it pass. It's a rare privilege to see, hear and heed John's very good advice. I really think a lot of the radio signals leaving the Tri-state area will be improved by those who heard this speech.

Another interesting display was the first radio license of Daniel C. "Dan" McCoy, W8DG. This certificate of proficiency and operating skill was issued in 1912. Dan was a Commercial Operator at the tender age of 15 years, Amateur at 11 (Novice, did you say?).

I did get a chance to get acquainted with the "Boss" from CQ. Wayne, W2NSD and Jim, K2OLK came to visit me at just the right time. The six-meter band was wide open and S9 signals were coming in from the entire east coast area. I do believe Wayne was the first ham signing the call W8ZCV to work Pennsylvania, but I worked another one there so I now have 36 states on Six Meters. Jim was thus awakened to the possibilities of the six-meter band. Jim read CQ and you can find some dope on six-meter gear there. I guess anyone on Six could have worked 20 states or so April 15.

With this opening of the six-meter band, were reminded again that Sam Harris at Helen, W1FZJ and W1HOY missed the Harry vention because of an opening (a nasty gas in the forehead)—toooo bad, Sam, and this one boy that sure hopes you have a speed recovery from your unfortunate auto accident We called W1HOY quite a few times Sundal

I have always been proud of my ham ticked but I am even prouder than ever since I may so many readers of CQ and The Novice Shack this last weekend. I will try to make the column ever better in the future—thanks for all of the help. Attending such gatherings and your regular radio club meetings and helping when asked to do a little work will make you a better ham, and you'll find more enjoymer in Ham Radio, where there's always room for improvement.

#### Re: QSL's

Have you seen the new QSL's of the ed torial staff of CQ? I'm proud of mine.

#### Net News:

The Novices of the Akron Radio Club hav a Net that meets at 1830 EST Wednesday of 3712 kc. For more information contact Dich Bitner, WN8HYD, 210 Kenwood Avenue, Akron 13, Ohio.

News of nets for Novices will appear in this column if you let me know of their existence by letter. Novice nets can improve your operating procedure. They provide good training ground for the newcomer. Let me know of the net you are in if it hasn't appeared in the Novice Shack net listing. Be sure to give the name and address of the net manager, the name of the net, the frequency and time of operation.

#### NNQB

The QSL managers of the National Novice Technician Association's QSL bureau are open

for business and you should at least send a card with your name to the one in your district. Send him a stamped self-addressed envelope for the cards for you that he has or may get. Use the NNQB to deliver those cards that you can't get delivered otherwise. The QSL managers are:

W1......W1BPW, 88 South Avenue, Whitman, Massachusetts

W2 KN2PQY, 85 Nassau Road, Massapequa, Nèw

W3 ...... WN3DGY, 1204 Broadway, Hanover, Pennsylvania.

W4 K4DWP, 154 Claredon Circle, Danville, Vir-

W5 K5ATT, 554 Hermine, San Antonio, Texas. K60GM, 4832 North Fruit Avenue, Fresno, W6. California.

W7ZSE, 4447 Eastland Street, Tucson, Arizona. W8 .WN8CZN, Jim Tullis, R. #3, Waynesville,

Ohio. W9 W9JZK, 4224 Bobolink, Skokie, Illinois.

W.Ø.....KNØCFH, 202 North Russell Avenue, Ames, KH6BIF, 157 Alae Street, Hilo, Hawaii.

KL7.... ..No appointee as yet (can you help?). KP4.....KP4QA, P.O. Box 2573, San Juan, Puerto Rico.

Any questions on the NNQB should be sent to Barry T. Joseph, W7ZSE, 4447 Eastland, Tucson, Arizona, and questions on the NNTA should be sent to 4490 Van Ness Blvd, Fresno, California.

#### Hint of the Month

There have been quite a few requests in the mail asking how the BC-451 can be used as a Q-5'er and how it is hooked into the regular receiver. In answer to these questions I am publishing a letter from R. K. "Dick" Jump, W9HYV, Cameron, Wisconsin, verbatim. Here is Dick's letter:

"Dear Walt: Here's a tip for anyone wanting to use the ARC-5 or BC-453 as a Q-5'er with the surplus receivers such as the ARC5, BC-454, BC-455 or the BC-348. Assuming power supplies are already available, we will get to the point. Solder a piece of wire to the grid cap of the 12K8 in the Q-5'er, a foot or so long and insulated. Bring it up and out of the case. Now remove the 12SK7 (or 12SF7) tube—the second one behind the antenna post on the BC-454 or BC-455 receiver.

of the case. Now remove the 12SK7 (or 12SK7) tube—the second one behind the antenna post on the BC-454 or BC-455 receiver.

Wrap a turn or so of hookup wire around the plate pin—do not bare the wire (no electrical contact—just capacity—Ed.) Put the tube back in its socket and bring wire up and out of the case. Make a twisted electrical connection of this wire and the wire from the grid cap of the Q-5'er. Now tune the Q-5'er to 415 kc for the BC-455, or 510 kc for the BC-455 receiver. Use the b. f. o. of the Q-5'er. For the BC-348 receiver: insert about 10 inches of insulated (tape the end) wire into the top phone plug of the BC-348 and tune the Q-5'er to 415 kc. Use the b. f. o. in the Q-5'er. Set the NC348 to MVC full on, BFO off, Crystal filter off.

For the Hallicrafters S-40 receiver I have merely attached a piece of wire to the Q-5'er antenna terminal, with the other end in a phone plug inserted in the phone jack of the S-40. The Q-5'er is set to 455 kc using the Q-5'er b. f. o. and controlling the gain from both the Q-5'er and the S-40.

I sure hope this helps some of the fellows with their receivers. I'll be glad to answer any further questions on this. Any 6-meter men up here in my part of the country? where?

Poet of livels on your Nowice column. Walt you are

questions on this. Any 6-meter men up here in a part of the country? where?

Best of luck on your Novice column, Walt, you are doing a wonderful job. I hope to see more for the Technicians. I'm due for my general examination this spring—as soon as Mr. Stork puts in his appearance so I can be away from home for a full day.

73, Dick.

#### Circuit Diagram Discussion

Why do you have trouble drawing diagrams for that test? Do you know why you put this or that component in the schematic? Just what is the difference between an r-f and an i-f amplifier? What is the difference between an r-f amplifier and a multiplier stage in the transmitter? A little study with the handbook and a study guide should help you to answer these questions and to be a better informed ham.

The similarity of the following circuits should be noted and the changes necessary to make them perform in the way that you want them to perform should be recorded in your notes. Please don't forget that circuits of all elements within the tube should be returned to B minus (ground) electrically. This ground return can be through the electron stream in some places and thru the electrical components in the circuit at the other times. In a tube with the emitting element being a cathode ("K"), all the current flowing in the tube comes from the cathode (except the current for the heating element which heats the cathode sleeve). All element voltages for the circuit should be measured from the cathode to the particular element contact of the tube, not from the chassis to the element.







Fig. 1 shows a stage of tuned-radio-frequency amplification, transformer-coupled to the following stage. The purpose of the radiofrequency amplifier is to increase the amplitude of the signal delivered to the following stage. A radio wave coming in on the antenna passes through L1 and induces a voltage in L2 which is tuned to resonance by the parallel condenser C1. This voltage is amplified by the screen-grid tube. The amplified wave passes through the plate circuit and coil in the plate circuit and induces a voltage in the secondary of the coupling coil to the next tube. Sometimes two or more stages of radio-frequency amplification are used to further increase the sensitivity of the radio receiver. The size of the coil-andcondenser combination will determine the frequency to which the circuit will tune (resonate). Remember: the smaller the coil and the condenser the higher in frequency the circuit will resonate: the frequency of a resonant circuit is inversely proportional to the inductance of the coil and the capacity of the condenser. With a fixed value of one, decreasing the value of the other will increase the frequency. The coil is fixed in this circuit and the condenser is a variable unit, therefore the circuit can be resonated.



In Fig. 2 the LC combination is replaced by a resistor and the coupling coils are replaced by a coupling condensers Cc. This circuit is used for any amplifier needing a wide bandwidth such as an audio amplifier. Resistance-coupled amplifiers have been used for i-famplifiers in early high frequency receivers. The value of the coupling condensers will limit to some extent the frequency range of the amplifier. The larger the condenser, the lower the frequency it will pass.




The circuit in Fig. 3 is that of a Class-A intermediate-frequency (i-f) amplifier. This type of amplifier will be tuned to one frequency band and left there. It is not tuned during operation. The frequency is usually in the lower radio-frequency regions between the audio and the broadcast frequencies, hence the term intermediate-frequency amplifier. High stability is important in this type of amplifier in order to keep the resonant frequency of the coils at the same frequency at all times. Operational theory of this amplifier is the same as that of the unit in Fig. 1. The resonant frequency of the inductance in the windings of the transformers and the condensers of the



same unit will determine the frequency of the amplifier.

The circuit of Fig. 4 is that of a radio-frequency amplifier or a frequency-multiplier stage. The radio frequency can be fed to the grid of the tube through the condenser or by using link coupling and a tuned coil-condenser combination tuned to the same frequency as that of the plate tank circuit preceding this stage. The r-f choke in the grid circuit is used to prevent loss of radio-frequency power through the grid circuit. This circuit can be used as a frequency multiplier if the grid resistor is increased in value and the grid drive is increased to make up for the grid losses. The plate should be resonant at the desired multiple



of the grid circuit's frequency. The tank circuit should have a high L-to-C ratio. The efficiency of a multiplier stage ranges from 40 to 50 per cent

The crystal oscillator circuit in Fig. 5 is very near the same as that of the multiplier or radio-frequency amplifier diagram in that all of the components are drawn in the same position except the grid coupling condenser or the grid coil-condenser arrangement is replaced by a crystal. The crystal is the frequency-determining device now, instead of the voltage fed through the coupling condenser from a previous stage. A properly cut quartz crystal is the equivalent of a very high-Q tuned circuit, and holds doggedly to the one frequency for which it is cut.

Now that we have noted the similarity of the foregoing circuits we can go on and apply the same thing to push-pull circuits and make the drawing of those circuits a lot easier for us. A little thought applied to these drawings along with a little practice in using the diagrams as study material will simplify theory study considerably.

#### **Questions and Answers**

A couple of months ago I said in this column that while this subject had been covered in all of the publications dealing with radio a lot of my readers did not have access to these publications because they are newcomers to the hobby of radio. I will try to give you a few representative questions, but I will try to answer them in a slightly different way so that you will understand the reason for the answer.

I feel that if you know the answer to the question in a technical way you will not be the kind of a ham that is lost if the question is worded differently than it was in the study guide. In other words I want you to know the

reasoning behind the answer.

The questions for your examinations are of the multiple-choice type. The answer is right before you, and all you have to do is pick out the right answer and check that answer. There are five answers printed after each question and some of them are a little tricky, for it may seem that there are two correct answers to the question asked. If you know the correct answer, you will have no trouble with the examination. I will give you more about taking the examination, getting the necessary forms and how to get some one to give you the test. The questions contained herein are not a representive sample but if you know these and use your handbook and do some study on the laws and regulations you can pass the novice test. Do not try to memorize the questions and answers just to get a ticket. Try to know the why's and wherefore's for the answers so you can find the answer to any question. A good way to study for the examination is to take the representive question and study the handbook dealing with that particular phase of radio, thereby adding to your knowledge of radio theory. You will be a better ham as the result of the little extra study.

#### Questions and Answers

1.

Q . . . Define the term, "amateur."

A... A radio amateur is a duly-licensed person interested in radio technique solely with a personal aim and without a monetary interest. His interests are as a hobby and not as a business adventure. No money may be received for any service or use of an amateur license, either directly or indirectly. Receiving monetary contributions are against the rules of the Federal Communications Commission.

2

Q . . . Name the four classes of licenses

issued by the FCC.

A... Novice, Technician, General (called the "Conditional" if taken by mail) and the Amateur Extra Class licenses are issued by the FCC.

Q . . . What frequencies are allotted for use

by the Novice?

- A... The following frequencies are allotted the novice: 3.700 to 3.750 Mc for CW. 7.150 to 7.200 Mc for CW. 21.100 to 21.250 Mc for CW. and 145 to 147 Mc for phone or CW.
- Q... What is the penalty for a violation of the rules and regulations of the Federal Communications Commission?

A... A fine of \$500 for each day during

which the offense occurs, suspension of the operator license and revocation of station license.

5.

Q... What is the logbook and what should it contain?

A . . . The log is the written record book of an amateur radio station. The log should contain the date and time of all transmissions, the signature, name and call of any person operating the station. It should record the call of the station called and the name of any one other than the licensed operator who speaks over the microphone. The input power frequency and the type of transmission used should be recorded. A record of any traffic handled, and a copy of such traffic, should be filed and kept for a year. The location of the transmitter should be recorded in the log book. The log book can be used to keep complete records of the operations of the station. By referring to the log you can tell when John or Ruby were at your place and talked to Uncle Bill. All pertinent data concerning the operation of the station will always be on file.

Q... What is the maximum percentage of modulation to be used in an amateur radio-

telephone station? Why?

A . . . Not more than one hundred percent. Overmodulation (more than one hundred percent) causes your signal to occupy too wide a portion of the band. Overmodulation causes serious distortion of the signal, this distortion of the modulation envelope causing new frequencies to be generated which combine with the carrier to form sidebands too far removed from the channel on which you are operating, thus causing the channel to be wider than when operated correctly. These spurious frequencies are commonly called splatter. Splatter is that portion of the signal that causes the "shushshush" you hear on the bands when tuning the ham phone bands. The operator causing splatter has lots of people muttering threats about what should happen to him, none of them good.

7.

Q... What are the rules and regulations regarding the transmission of improper language, false signals, or malicious interference?

A... The transmission of indecent, profane or obscene language is forbidden by law. Malicious interference, deceptive or improper call letters are prohibited by law and are subject to heavy penalties. Let every thing you say or do reflect to the good of amateur radio and the amateur radio operator, that way you won't have to worry about troubles with rules and regulations. The best rule is the Golden Rule. Don't forget that anything you say may be heard by any one in the world—you never know who is listening to you. So be careful of what you say. That anyone should have to be warned against using indecent, profane or ob-

scene language is truly a shame. He "shoulda been brung up better.'

#### Letters

Al, WN8HYR, 632 Kedzie Drive, East

Lansing, Michigan writes:

"Dear Walt: I am writing to tell you how much I enjoy your column. I get a real kick out of reading the letters from the fellows that I have worked. I have 17 states confirmed here on 40 Meters. The rig is an AT-I and an AR-2. The best DX so far is KN5DGI in Shreveport, Louisians. I will sked anyone needing Michigan. Thanks and 73, Al.



Milt Rosenblum, KN9ASR, 2709 West Granville, Chicago, Illinois says his pet peeve is the lid that calls CQ at 15 wpm and can't copy more than 5, says he has to QRT and then calls CQ again. Please send at the speed that you can copy. Milt has 21 states confirmed.

Dick Bittner (14), WN8HYD, 210 Kenwood

Avenue, Akron 13, Ohio says:
"Dear Walt: I have read Novice Shack for a long

time and I want to say what a fine job you are doing as editor.

The rig here is about the average but I'm real proud of it. The transmitter is a Heathkit AT-1 and it is converted to Six Meters. The receiver is a BC-312 and the antenna is a freak doublet for trans-

BC-312 and the antenna is a treak doublet for transmitting and a 15-meter vertical for receiving.

My ticket is about 4 months old and is becoming more fun every day. I will take the test for the Technician as soon as the test comes. This summer I will sked anyone on Six Meters who wants to ragchew or anyone that needs Ohio for WAS. I owe



Bob Carlson, WN7AMY, 2446 North East 58, Portland 13, Oregon surely has garnered some nice QSL cards. Among those worked are PY7, PY2, JA1, CX2, KZ5 and CO2 on 15 meters, also ZL2LL on 40 meters. That's a neat layout, Bob.

my interest in ham radio to Phil, W8TTN and Jon, WN8GKB who rammed the code into me. Keep up the good work, Walt and 73, Dick."

Edward A. Whitman, KN2MFY, 35 Crown

Street, Brooklyn 25, New York writes:

"Dear Walt: My time as a Novice is drawing to a close, but I expect my General license to come any day now. I have been on the air for about ten months. For the first five months I was on 40 and 80 Meters. For the last five months I have been on Fifteen Meters. I have 36 states and 86 foreign contacts in 34 countries and 4 continents. The best DX was VQ-4 land.

The rig is a Viking Adventurer and the receiver is an S-38-C. I think that the S-38-C is the best of the low priced receivers. The antenna is an 80 meter dipole (130 feet) fed with 72-ohm coax.

dipole (130 feet) fed with 72-ohm coax.

I will gladly schedule anyone needing New York, especially the W7 land. I would like to have skeds on 15 Meters. I will answer all letters. So keep up the good work, Walt and 73, Eddie."

P. S. If any novice is expecting DX QSL's it would be a good idea to send a stamped self-addressed envelope to your ARRL QSL Bureau.

That is a very good idea, Eddie and also while you are at it why not send a couple to your N.N.T.A. QSL Bureau and get those overdue QSL's that he has on hand. They are piling up and also some other mail is being sent through them for you Novices and Technicians. It would be to your advantage to take advantage of the N.N.T.A. QSL Bureau in your district. A list of them appears in the novice column this month. this month.

Tom Eavenson, KN5BWZ, 248 Roma Drive, Shreveport, Louisiana pens this letter:

"Dear Walt: The Novice Shack is my favorite part of CQ. Some of my friends have written you and had



Doris Ann Eggleston (16), KN5CPA, 1229 Dunn Lane, Corpus Christi, Texas has worked 33 states, KZ5 and VE3 since October 4. Her Frequency is 21.135 and 21.180 and she operates every afternoon around 1700 CST. Her mother is KN5COZ and her dad is W5QEM.

very good results.

am 14 years old and in the 9th grade at Byrd

High School.

I work 40 Meters only, as I don't have enough room in the yard for an 80-meter antenna. The rig is an AT-1 and a Super-Pro. I have worked 23 states and an XE2

I would like to have skeds with KN6's and WN7's, I will sked anyone needing Louisiana for WAS. I QSL 100% here when I can get the address. Good luck, Tom."

Utah is again represented in novice shack by the letter from K. J. Farnsworth, W7WLV, 3708 South 23rd East, Salt Lake City, Utah.

"Dear Walt: I understand that your column is also for the Technician. Well, I am one and you might pass along the word that early in the spring like this we should listen in the mornings for 6-meter openings. I am on every morning from 6:30 to 8:30 a.m. calling and listening. (DOES ANY ONE NEED TRAME)

I sure do miss my Novice days. I guess I will finally break down and go up for my General ticket. Even



# steps to superior signals with B & W

### 1) MODEL 5100-B-AN OUTSTANDING AM-

high level push-to-talk AM telephony . . . 140 vatts input • clean CW break-in on all bands . . 180 watts input • sparkling SSB . . . 180 vatts input . . . when combined with the 51SB-B ompanion sideband generator • bandswitched hroughout • integral VFO or crystal frequency control • coverage of 80 through 10 meter amaleur bands • unitized construction • pi-network inal • integral low-pass filter • handsome styling • TVI suppression.

Net Price . . . . . . . . . . . . . . . . \$475.00







3



4



# Model 51SB-B Generator Superlative SSB

completely bandswitched

voice operated control

powered by 5100-B transmitter

No wiring required

push-to-talk • speaker deactivating circuit—TVI suppression • unitized construction.

et Price . . . . \$265.00

#### (3) Model 370 Adapter For Reception You Never Dreamed Possible

- truly exceptional SSB reception, select upper or lower sideband at the flip of a switch
- true single signal CW operation suppresses unwanted heterodyne by 50 db
- select either sideband of an AM signal
- may be combined with any communications receiver
- normal operation of your receiver is not disturbed in any way

Net Price . . . . \$131.50

#### (4) Model 51SB Generator For Sparkling SSB With Your Present Transmitter

- easily added to your present B&W 5100-5100B, Collins, Johnson, or other commercial composite home built transmitters
- complete with power supply and tubes
- outstanding SSB transmission from 80 through 10 meters with frequency control provided by your own transmitter
- all the features of the 51SB-B SSB generator at left.

Net Price . . . . . \$279.50


WRITE FOR LITERATURE, OR SEE THESE FINE PRODUCTS AT YOUR DISTRIBUTORS

Prices Subject to Change without notice

B&W

BARKER & WILLIAMSON, INC.

237 Fairfield Avenue, Upper Darby, Pa.



Norman C. Peterson, K6ANE, 2003: Clark Street, Fresno 4, California. Norman says his biggest problem is trying to share a room with the rig and a room mate at the dorm at Fresno State College, looks like he is successful though. Norm says he enjoyed ham radio more as a novice.


then I will still like to work the novice bands. 73,

(DOES ANY ONE NEED UTAH? That is the \$64,000 question and I am just "the guy what kin anser hit." Next to Nevada, where the six-meter operation is nil, Utah is in much demand. An expedition from the East Coast put Utah on the sixpedition from the East Coast put Utah on the sizmeter map last year and made quite a few new states in their six-meter logs. These same hams put Nevada in the logs of more hams than ever before. I have said before in my column that we are sadly in need of hams that will operate the high frequency bands consistently so that we back-east hams can have something West to look for, we can better judge our efforts that way. You Technician operators get your back issues of CQ and start building for the greatest boom in v-h-f activity the ham fraternity has ever known. Don't leave it to George (unless he has a license) to do all the operating and the experimenting to help save these bands for the amateurs. So, K. J., I will pass along the thanks of all Eastern hams for putting Utah on the v-h-f bands.)
Here is a letter that gives us something to ink about:

"Dear Walt: I have been a Commercial for a good many years, Amateur for this time for two years, but the main thing I wanted to bring out is the wonderful job you are doing in the 'Novice' column. I am sure if the person is really interested in his ticket and reads your column, he can make it. (Thank you

for the kind words).

As an instructor in "How to become a Radio Amateur" in Adult Education and at Church, I



M. B. Kilcrease, KN5DXW, 708 North Grand Avenue, Olney, Texas has been on the air for about six weeks but has worked some of the hard to get states for this short time of operation. He needs some help in getting a diagram for an RK-20 final.

recommend without fail that those who are interest recommend without fail that those who are interese in becoming Radio Amateurs read your No Column. This leads me to the next thing at he why does not CQ or someone connected with publish a handbook and license manual plus crecords for the beginner and the Technician? I this sort of thing hard to get. The records on market are inadequate and the handbook avails improperly presented. 73, Walt. E. C. Sher K6JFP, 5406 Churchward Street, San Diego California." California.

Joe E. Minyard KN5DXL, R.F.D. #4, H pora, Mississippi writes:

"Dear Walt: I got my first issue of CQ this mo-and discovered the Novice Shack. I think it is gre I got my license about a month and a half ago have made 131 contacts in 23 states with all confirmed. My best DX is New York, Michigan



Al Johnson, KN6QBY, 10329 East Weaver Street, El Monte, California says "See you on 80 with this nice setup." Besides the TR-75-IV he has a BC-430 for a standby



Tommy Painter (12)KN6MQN, 1428 Conejo Drive, San Bernardino, California says he likes the 15 meter band best but will work you on 40 or 80 if you haven't worked his state for WAS. The rig is a BC-348-O and two ARC-5 receivers for 40 and 80 and an AT-1.

Pennsylvania. I operate 80 Meters only at 3716 at

The rig is a Heathkit AT-1 running 30 watts. T receiver is a Hallicrafters S-53-A. My antenna is 135-foot doublet fed with coax. I also have a hor made CW monitor.

I plan to take my test for the Conditional Licers in about three weeks. I will schedule anyone needit Mississippi for WAS or for a good old rag che I QSL 100%. 73, Joe."

Charles Tannen, KN2ODU, 18 Lake Shord Charles Tannen, KN2ODU, 18 Lake

copeck, Pennsylvania writes:

"Dear Walt: I'm 15 years old and I've had m Novice call for a few weeks now. My call is WN3FM! I haven't had any contacts yet but really hope to going before long. My transmitter is a homemade rig running aroun 30 watts. The receiver is a Heathkit AR-2 and th

# When you go Mobile... you get TOP TRADES ON THIS TOP LINE

ROM the Worlds Largest Distributor of amateur Radio Equipment

#### PMR-7 RECEIVER



Cash Price: \$159.00

New sliderule dial, improved sensitivity, selec-tivity and signal to name Has added features of dual conversion, crystal controlled 2nd Oscillator, controlled 2nd Uscillator, variable injection VFO, R-F gain control, squelch control. Operates from 6, 12V DC or 115 AC Power supplies. 7 bands;—10, 15, 20, 40, 80, 160 plus Broadcast.

Only \$873 PER MO

Bandswitching 160100M. Emission A100M. Emission A100M. Emission A100M. Or crystal operation.
5 circuit meter switch. 60 watts input to plate of final
tube (6146). Coax
conector and universal Pi matching network. Provisions for
60 watts of audio at

40 watts of audio at 500 ohms to drive

higher powered modu-

Cash Price: \$177.00

lators, etc.

160-

Bandswitching

AF-67

TRANS-CITER

Only \$965 PER MO.

SEND

For Complete Information on the Full Line of Multi-

Elmac Products

MULTI-ELMAC

AND

YOU

PAY ONLY

DOWN

#### **PSR-612** POWER SUPPLY

Operates on either 6 or 12V by changing built-in switch. Power turned off and on by receiver control; 250V at 90 Ma. B plus, toutroi; 250V at 90 Ma. B plus, 105V at 10 Ma. regulated. Fil-tered filament supply; 6x4, 6x4, 082 regulator. Completely filter-ed for vibrator hash. External "S" meter may be added. Weight:

Cash Price: \$34.00

For Fixed Station Operation

#### PSR-117 Power Supply

Operates on 115V, 60 cycles. Power turned on and off by receiver control. Calibrated "S" meter and adjusted potentiometer installed. Cash Price: \$47.00

#### PS-2V Power Supply

A universal power supply, but especially designed for use with the AF-67. Separate filament and plate transformers, separate rectifier and filter circuits for dual DC output. Uses one 5U4G and one 6X5GT tube.

Cash Price: \$49.50



#### AND GET THE STORY ON . . .

- The WRL Globe Scout and WRL Globe King
- Up to 50% Savings on Reconditioned Equipment

\* WRL's E-Z Pay Plan!

**FREE 1956** CATALOG!

Over 15,000 Top-Value Items of Interest to the Radio Amateur!



Please send me:   Latest Catalog and	Department of the latest latest	ms checked below! Quote	
your top trade offer on my		(make of present eqpt.)	C-6
s most personalized electronic supply house	☐ Latest Mobile Flyer	Recond. Eqpt. List	

WORLD'S MUST PERSONALIZED ELECTROSTIC CONT.	Latest Mobile Flyer   Recond. Eqpt. E.
World Radio	0
LABORATORIES PH. 2-0277	NAME:
HEADQUARTERS WOALD MODE CHOMES	ADDRESS:
3415 W. BROADWAY COUNCIL BLUFFS, IOWA	CITY & STATE:

antenna is a 170-foot long wire center-fed.

I enjoy the novice shack very much so keep up the tgood work Walt. 73, John."

Dick Mills, W7AMH, 615 West Alturas,

Tucson, Arizona says:

"Dear Walt: I have just received my Conditional Class License. Boy, it feels good to be a ham after about two years of work on it. Any boy or girl needing help in getting his ticket please call me before 7:00 p.m. by phone. The telephone number is 4-7775. I'm on the 40-meter Novice band—7176 and 7194—with 30 watts to a 6C5-6L6 Transmitter. The receivers are an AR-2 and a BC-455. Thanks and 73, Dick."

Jim Grubbs, 833 Highland Terrace, Atlanta,

"Dear Walt: I have been a Novice for about two months and in that time I have had 48 contacts in 8 states. A lot of the boys say I am their first Georgia contact so if any one needs a sked just write me. work 40 and 80

The rig is a HQ-140-X doing a very fine job. The transmitter is a Lysco 650 into a dipole antenna. There is a teen-age net here in Atlanta that meets on 3885 at 1300 EST Saturday. 73, Jim."

A letter from Midway Atoll says:

A letter from Midway Atoll Says:

"Dear Walt: Just a word from 'Gooneybird Island'
to let the fellows know that KM6AX has a Novice
shack now. Our Frequencies are 7175, 7180, 7190 and
7195. The rig is homebrew by two of the General
operators, W6HDO and K4CMP. We now run 40
watts and will soon be up to 75 watts, the receiver is
a BC-342-N and we have a 300 foot long wire. The
operators are watchstanders so we can't handle any operators are watchstanders so we can't handle any skeds, but we will be looking regularly for the fellows from 0500 GMT to 1300 GMT. Sincerely C. C. Butt-schardt, Truste, Midway Amateur Radio Club."

The first letter from Maine came from Joseph A. Foss Jr., WN1HZZ, South Windham,

Maine. Joe writes:

"Dear Walt: I thought where I have a few spare moments that I would write and let you know how WN1HZZ was making out. I got my license January 18. The transmitter is a home made 6AG7-807 combination running about 42 watts input. The antenna is a 125 foot long wire. The receiver is an S-38-D. I am particularly pleased with the transmitter because I laid out only \$11.00 for it. For the power supply I have two old receiver power supplies in series which is doing FB. is doing FB.

which is doing FB.

So far I have worked Maine, New Hampshire, Vermont, Massachusetts, Connecticut, New York, New Jersey, Ohio and Virginia on 80 meters. My contact with W4EII gave me a signal report of 5-8-9, which I think is pretty good for this old bucket of bolts. I work on 3738 kc and my best time is between 5:00 and 7:00 in the morning. I would like to sked anyone needing Maine for WAS. I will QSL 100%. I am 16 years old, 73. Joe."

Gus Britzman, WØJEU, Houston, Missouri

"Dear Walt: I read your Novice column and enjoy it very much. Would anyone be interested in the setup here? I have a 1½ horsepower engine, an auto generator, car battery, vibrator power supply powering a two tube rig. The rig is a 6C5 oscillator feeding a 6V6 amplifier running about 4 watts input to a one half wave dipole antenna. I use less than one gallon of gasoline a week. I worked VE, XE and 40 states. The antenna is fed with 72 ohm twin lead, the two cents kind. I also worked 36 states and some VE's with only 3 watts input with 40 meter CW.

I once hooked my rig to a rural telephone (1 wire) for an antenna but the guys thought I was crazy

for an antenna but the guys thought I was crazy and would QRT when I told them that I was running and would QRT when I told them that I was running 4 watts to a seven mile long wire. A W5 gave 599X but would not finish the QSO with me when I told him of my power input. He didn't QSL either. The receiver is a 3 tube regenerative set using 3-3Q5's using one half of each filament at a time. I worked a W8 in Ohio who said he was running I watt.

This experience should be interesting to someone who is afraid to get his ticket and get on the air due to lack of equipment and power.

I would like to see one day a year when no one runs over 3 watts, perhaps as a contest. 73. Gus."

Editor's Note: Gus, I too would like to see such a contest, then we would locate the HAMS that actually do their experimenting on their own. This would

probably make some of the high power boys star up and take note if they were not in there to cov-the little boys all of the time, I have 5 continent 17 states and 16 countries with 64 watts on te meter phone. Congratulations Gus, on your low power work.

If those western hams don't quit writing suc letters as the following one of them will hav to buy me a ten gallon hat 'cause my head i a growin' too fast. I beg your pardon, but jus let me print a sample.

Ron Sefton, (17) W7VWR, 717 West 16t Avenue, Spokane, Washington sends this gem

"Dear Walt: After reading the February issue of "Dear Walt: After reading the February Issue C CQ and especially your Novice column, I have come to the conclusion that CQ is the only ham magazine Your column with its informality and just plail good old ham news, is typical of the whole CQ effort I hope you can keep up the good work, Walt, you just don't know how much good you are doing for prospective hams and hams of all classes. Thanks for the time, 73, Ron." You are welcome Ron, come again.

#### Help Wanted

Miss Carol Rawie, (13), 230 West 17th Street, Sious Falls, South Dakota needs help in code and theory and advice on equipment.

Lilly Purnell, 708 Linden Street, Camden, New Jersey

Lilly Purnell, 708 Linden Street, Camden, New Jersen needs help in code and theory.

Bill O'Brien Jr., (13), Box 367, Route 2, Pilot Point: Texas needs help with code and theory.

John W. Williams, (46), 22195 Park Street, Dearborns Michigan wants some help with the code.

Ira E. Antley, Box 216, Monroe, Louisiana needs help with code and theory.

Raymond Pint Raymond Jows wants some one to help.

Raymond Pint, Raymond, Iowa wants some one to help with code and theory.

Barry Weiss, (13) 1633 Monroe, Evanston, Illinois needs help with code and theory.

Gary Maher (14), 516 Schenectady Street, Schenectady

New York needs help in code and theory.

Jack Pookiard (13), 1014½ Stanford Street, Concord

California, Phone MU-5-7529 had a code oscillator and
needs a helping hand to practice with. He will answer all letters.

Larry Albert, 150 Long Drive, Hempstead, New York

Arry Albert, 100 Long Drive, Hempsteau, New York needs help in code and theory.

Arnold Fine, (17) 29 Monroe Avenue, Worcester 2.:

Massachusetts needs help with the code. His telephone number is, PL-2-2646.

Jesse Woodson, 14, 1841 South Homan, Chicago.

Illinois would like to have some one to give him the

novice test.

Ernest A. Washburn Jr., (16) Phone: Lakewood 7791, Box 176, Ashville, New York needs help with his code and wants some one to help him design his rig.

Joe Evans, 304½ West Martin, Martinsburg, West Vir-

ginia needs help with code and theory.
Charles M. Weiss, 1611 Carmel Road, Walnut Creek,
California needs help in code and theory. His phonenumber is YE-5-0638.
Ed. A. Daggett, 44 Holmes Court, Albany, New York
needs help in code and theory for the test, he has the

Those aspirants listed above could use some of your time to get started, can you spare a little? To get listed in the column as one desiring help just drop a letter with the full particulars to me: Walter G. Burdine, W8ZCV, R. #3, Waynesville, Ohio. Do not write me in care of the office in New York as that just puts more needless work on the office staff. Please put the full address on the envelope so that I will be sure to get it, I have received letters just sent to Walt ...... Waynesville, Ohio, and sometimes Waynesville is spelled wrong. That may be the reason you didn't get your name in the column. Again, just: Walter G. Burdine, W8ZCV, R. #3, Waynesville, Ohio. Thanks and see you again next month.

73, Walt, W8ZCV.

# HOW MUCH SHOULD YOU PAY FOR A GOOD ROTARY BEAM?

the only true measure of value is (a) performance and b) amount of aluminum per dollar cost. Study these pecifications—compare them—and you too will agree, long with thousands of hams, that GOTHAM beams for best!

TYPE OF BEAM. All Gotham beams are of the full halfave plumber's delight type; i.e., all metal and grounded it the center. No wood, tuning stubs, baluns, coils, or iny other devices are used.

(AIN. Gotham beams give the maximum gain obtainable. Four 2-element beams give a power gain of four (equivalent of db.); our 3-element beams give a power gain of seven 18.1 db.); and our 4-element beams give a power gain of tine (9.6 db.)

r RONT-TO-BACK RATIO. We guarantee a minimum F/B atio of 19 db. for any of our 2-element beams; 29 db. for many of our 3-element beams; 35 db. for 4-element beams.

AATCHING. Matching of the transmission line to the beam sextremely simple and quick. Everything is furnished and he matching is automatic. No electronic equipment or measpring devices are required.

ASSEMBLY AND INSTALLATION. No special tools are lequired for assembly and installation. Entire job can be alone by one man in less than an hour. Full instructions are included with each beam.

MAST. Any Gotham beam can be mounted on a simple pipe nast. Diameter of the pipe should be between 3/4" and 15/8".

standing wave ratio. A very low SWR of approxinately 1.5 to 1 will result from following the instruction sheet, depending on the height above ground and the surounding area. If an SWR indicator is available, Gotham beams can be quickly and easily adjusted to 1.1.

STANDARD AND DELUXE BEAMS. Standard beams in the 6, 10 and 15 meter bands use  $\frac{5}{8}$ " and  $\frac{3}{4}$ " tubing elements; the deluxe models for these bands use  $\frac{7}{8}$ " and 1". In 20 meter beams, the standard has a single boom, while the deluxe uses twin booms.


WHAT WILL A GOTHAM BEAM DO? A Gotham beam will amplify the transmitted and received signal trementously and will greatly reduce noise and QRM.

#### **NEW VERTICAL ANTENNAS**

ENGINEERED VERTICAL ANTENNAS for 40 meters, 80 meters, 160 meters. Gotham Hobby Corporation proudly announces three vertical antennas for unsurpassed performance on 40 meters, 80 meters, and 160 meters. Each antenna is absolutely complete, can be assembled in less than two minutes and requires no special tools or electronic instruments for adjustment and operation. Radiation is omnidirectional, with maximum radiation at the very low angles necessary for DX operation. These three vertical antennas have been developed over a period of three years in response to requests by hams for efficient, fool-proof, small-space, low-cost antennas for 40, 80, and 160 meters. Two 12 foot lengths of tubing and loading coil in each vertical antenna. Literature available.

# V	40	vertical	tor	40	meters
# V	80	vertical	for	80	meters \$16.95
#V1	60	vertical	for	160	meters\$18.95

HOW TO ORDER: Send coupon with cheek or money order directly to GOTHAM or visit your local distributor. Immediate shipment by Railway Express, charges collect. Foreign orders accepted. Some leading distributors who handle GOTHAM beams: Offenbach & Reimus, Curle, M. N. Duffy, Alltroile, Purchass Radie, Lew Bonn Co., Henry Radie, Evans, Gib's Ham Gear, Hobe's Radio, Western Electronics, Harris Radio, Capitol Radio, Kinkade, Johannsen, W. H. Edwards Ca., World Radie Labs, Graham Electronics, Geo. D. Barbey Ca., Hudson Radie, Selectronic, Radio Electric Service, Keel-Els Radie, NRM Wholesale Radio.



2 METED DEAMS

This Full Size
Gotham Cost
Only \$21.95
And Brought
In 87 Foreign
Countries,
All Continents
And 30 Zones
On 35 Watts!

MAIL THIS COUPON TODAY!
10-DAY MONEY BACK GUARANTEE


#### GOTHAM

DEPT. CQ-1

107 E. 126th ST., NEW YORK 35, N. Y. Enclosed find check or money-order for:

Z INILITER DEFINIO			
Deluxe 6-Element 6 METER BEAMS	\$9.95	☐ 12-EI	\$16.95
	12 05	T matc	h 14 95
		T matc	h 24.06
Deluxe 3-El Gamma match		I mate	1 24.90
Std. 4-El Gamma match	16.95	T matc	n 19.95
Deluxe 4-El Gamma match	25.95	T matc	h 28.95
Std. 4-El Gamma match Deluxe 4-El Gamma match METER BEAMS			
Std. 2-El Gamma match	11.95	☐ T matc	h 14.95
Deluxe 2-El Gamma match		T matc	
Deluxe 2-Li danilla illateli	16.95	T matc	h 19 06
Std. 3-El Gamma match			
Deluxe 3-El Gamma match		☐ T matc	
Std. 4-El Gamma match	21.95	T matc	
Deluxe 4-El Gamma match	27.95	☐ T matc	h 30.95
Std. 2-El Gamma match Deluxe 2-El Gamma match Std. 3-El Gamma match Deluxe 3-El Gamma match Std. 4-El Gamma match Deluxe 4-El Gamma match METER BEAMS			
Std. 2-El Gamma match Deluxe 2-El Gamma match Std. 3-El Gamma match Deluxe 3-El Gamma match METER BEAMS	19.95	☐ T matc	h 22.95
Deluxe 2-El Gamma match	29.95	T matc	h 32 95
Deluke 2-Li daililla lilateli	26.95	T matc	
Std. 3-El Gamma match			
Deluxe 3-El Gamma match	36.95	T matc	n 39.95
20 METER BEAMS			
Std. 2-El Gamma match Deluxe 2-El Gamma match	21.95	T matc	h 24.95
Deluxe 2-El Gamma match	31.95	T matc	h 34.95
Std. 3-El Gamma match		T matc	
		T matc	
Deluxe 3-El Gamma match	40.93		
(Note: Gamma-match beams T-match beams use 300 ohm		72 onm co	ax.
NEW! RUGGEDIZED HI-GAIN	6, 10, 1	5 METER	BEAMS
Each has a TWIN boom, extra	reavy bea	m mount c	astings,
extra hardware and everythic Guaranteed high gain, simple	ng neede	ed.	
Guaranteed high gain, simple	installati	on	7/
and all-weather resistant. For 5	2, /2 or 3		<i></i>
ohm transmission line. Specify	which trai	ns	_
mission line you will use.			
Beam #R6 (6 Meters, 4-El) Beam #R10 (10 Meters, 4	\$38.	.95	
Beam #R10 (10 Meters, 4	-ti) 40.	.73	
Beam #R15 (15 Meters, 3-1	EI) 49	.73	•
Name			
Address			
City	Zone	State	

### 21-Mc Preamplifier



This preamp circuit is the acme of simplicity and uses close to the absolute minimum of parts.

According to contributor, W2SHT, none of the local boys who constructed duplicates have run into any tendency to parasitics or instability.

#### **ANTENNAS**

[from page 59]

little long so that the antenna could be pru to length in its operating position.

The lengths set forth on Figure 1 determined as follows:

Length (in feet) =  $\frac{(492K)}{\text{Frequency (mc}}$ 

K is normally accepted as being 0.95 for lower frequencies, however this figure va with the type of ground and surrounding jects. I have found that the same antenn: two different locations will sometimes have be shortened as much as six feet to resonat the same frequency! Thus K would seem vary at least from 0.93 to 0.98. The different is more than slight, changing the resonant quency as much as a hundred kilocycles. T in the above table all lengths are given lon than is considered possible under any cotions so that the antenna can be safely cur this length and then in one step (to be scribed) cut to the correct length. It is easier to prune extra twin-lead off than splice it on if you start too short.

#### Cutting to the Exact Frequency


The folded dipole is quite broad in respond will operate over a wide range of quencies. Most of us have one channel to [continued on page 94]

#### **BASSETT VACUUM COILS**

Pat. Pend.

#### PROVEN PERFORMANCE! EXTREMELY HIGH "Q"!





- The only genuine hermetically sealed antenna loading coils.
- Evacuated and filled with pure helium.
- Impervious to rain and weather. Always super efficient.
- Unconditionally guaranteed.

See Sept. 55 CQ or write for brochure

REX BASSETT, INC.

**Bassett Building** 

Fort Lauderdale, Fla.

YOU GET **MORE** In **knight-kit** HAM GEAR

#### BUY DIRECT AND SAVE



Save On This
Easy-to-Build
Transmitter
only
\$4250

knight-kit

50-WATT CW TRANSMITTER KIT

pact and versatile—the perfect low-power rig for Novice. Features: 50 watts input to 807 final; 7 modified-Pierce oscillator takes crystal or VFO out circuit changes; band-switching coverage of 0, 20, 15, 11-10 meters; pi-section antenna output rmit use with any type of antenna; crisp cathode ng of oscillator and final; power take-off plug supfilament and B-plus voltages for other equipt; excellent TVI suppression; meter reads either or grid current of final; jacks for VFO, crystal key. Size, 8% x 11% x 8¾". Supplied with all s, tubes and step-by-step instructions (less crysind key). Shpg. wt., 18 lbs.

x 255. 50-Watt Transmitter Kit. Only . . . 42.50



Save on This knight-kit Self-Powered VFO KIT

only \$27<sup>50</sup>

Complete with built-in power supply! Careful design and voltage regulation assure high stability. Excellent oscillator keying characteristic for fast break-in with clicks or chirps negligible. Full TVI sup-

teristic for fast break-in with clicks or chirps negligible. Full TVI supsion. Has plenty of bandspread: separate calied scales for 80, 40, 20, 15, 11 and 10 meters; ier drive mechanism. 2-chassis construction keeps from frequency determining circuits. Output e plugs into crystal socket of above Knight-Kitny other transmitter. Output on 80 and 40 meters. h Spot-Off-Transmit switch. Extra switch cons for operating other equipment. Complete kit tubes, all parts and instructions for easy assem-Shpg. wt., 8 lbs.

15 725. Self-Powered VFO Kit. Net...... 27.50



knight-kit
CODE PRACTICE OSCILLATOR KIT
Only Transistorized—

\$395

Transistorized —
Powered by Flashlight Battery

An ideal new code practice oscillator. Uses transistor circuit. Extremely current consumption—powered by single penlight tery. Provides crisp, clear tone (400 to 600 cps). s input jack for earphone; screw-type terminal p for key. In compact bakelite case (23 s x 3 s x \*) with anodized aluminum panel. Complete with

parts, battery and easy-to-follow instructions. 19g. wt., 1 lb. 5 239. Code Practice Oscillator Kit. . . . . . . 3.95

# you get MORE FOR YOUR MONEY AT ALLIED

YOU GET MORE ON TRADE-INS

try us!

We're trading HIGHEST! Try us—get top-dollar value on your trade-ins. Tell us what you want and what you've got to trade—and we'll give you the best deal you can make anywhere—you'll get MORE on every trade...

YOU GET MORE IN RECONDITIONED GEAR

write for lists

Everyone's trading HIGH with ALLIED these days and we have on hand outstanding buys in exceptionally fine reconditioned Ham Gear. Ask for our lists of top-condition equipment—get MORE for your money...

#### YOU GET EASIEST PAY TERMS

Only 10% down on orders as low as \$45—12 full months to pay (no carrying charges if you pay in 60 days)—no red tape—no finance companies...



#### SEE YOUR 324-PAGE ALLIED CATALOG

It's packed with top values and the largest selections of highest quality station equipment—it's your complete buying guide to everything in Electronics. If you haven't a copy, write for it today.

#### **ALLIED RADIO**

100 N. Western Ave., Chicago 80, III.



Our 35th Year

Everything for the Ham

Prices Net B. Chicago

# Sock 'em

#### MOBILE BY DAVIS!



#### NEW! "500 Series" High-Q Coils

Our tests show Q over 400, highest in mobile coils to date. Get fixed station performance with an individual coil for 80, 40, 20, 15 meters & shorting bar for 10 meters. Distinctively color coded! Amateur net: \$6.25 ea. coil. \$3,95 ea. shorting bar, \$26.95 full set.

#### **Hams Say This About** New "500 Series" Coils-

- to W60UI mobile in Long Beach, Calif. using the 40 meter coil.

"Sounds terrific. As good as your home rig." - W7RSY "A most outstanding mobile signal." - W6HLH "Can't believe you're mobile."- W8VDJ

#### NEW! Contour Whip Clamp

Answers need for whip clamp that fits bending angle of whip to protect antenna. Attach to drip moulding of any car without drilling holes. Rustproof, chrome plated metal alloy. Amateur net: \$1.25 ea.





#### NEW! In-Line Whip Flexor

Protects coil when whip strikes overhead objects. Takes strain off antenna when bent for storage in whip clamp. Strong, flexible stainless steel. Amateur net: \$1.95

Other fine mobile equipment by Davis: fibreglass whips; steel base sections; improved all band coil.

At your ham distributors now.



#### DAVIS ELECTRONICS

4002 W. Burbank Blvd. Burbank, California

FREE! Write for catalog of the mobile line

we use most and generally like to have e thing operating at optimum on this chair The Novice will want to cut his antenna: the middle of the Novice band. The p man will cut his for the phone band, etc. cide what frequency you would like to cul antenna to and put that in the formula by as  $F_d$ , the frequency desired.

Determining the resonant frequency of antenna is a bit tricky, but then so am I. can do it with a grid-dip meter if you har ladder to reach up to the center of the antiwhile it is in its operating position. Unfo nately the grid-dip meter tells all sorts of when you try to hook it in at the shack en the feed line. What you really want at time is a v-f-o transmitter, preferably of power, which has a link coupled output st A Pi-Network output circuit will tell you same lies that the grid-dip did. The m reason for using a Pi-Network is because will match almost anything and not be bothered by little things like antennas by cut for the wrong frequency.

Connect the output link to the 300 feeder, set the v.f.o. at one end of the band tune up the rig. Notice how much load you are getting to the final. Move the v up the band in easy stages, say 50 kc : time, until you have passed the peak and loading starts to decrease again. While much simpler to swish the v.f.o. across band and find the point of highest loading is frowned upon by the FCC and is not rec mended, no matter how much it simplifies procedure. Figure out some way to do it is legal.

Let us now say that you have determine the resonant frequency of the antenna erected. Call this frequency  $F_a$ , the acl frequency, in the formula below.

 $L_a$  is the actual length of the antenna. T you can find the length of the antenna ( that will resonate at the desired frequency suggest you make a permanent record of calculation so that you will be able to a the frequency of the antenna in the fut without having to take it down and meas it again should you desire to tune it to anot frequency.

$$L_{d} = \frac{F_{a}}{F_{d}} \frac{\times L_{a}}{\text{Length in feet or inc}} \label{eq:lambda}$$

 $L_d$  will be shorter than  $L_a$  so that you subtract one from the other, take down antenna, and cut one half of the differen from each end of the antenna. Thus in one step you have tuned your antenna to desired frequency.

[continued on page 96]

# Now's the time to go mobile!

... and Burghardt's offer you a complete stock to choose from . . . terrific trade-in allowances, too!



#### GONSET

**G-66 Receiver** — AM, CW and SSB six bands. Excellent sensitivity and selectivity. Antenna trimmer — automatic noise limiter — built-in "S" meter. \$16.95 down. . . . . . \$9.23 per month for 18 months.

6-77 Transmitter — 50-60 watts input. VFO or crystal control. Highly stable VFO. 80, 40, 20, 15 and 10 meters. Exciter gauged with VFO. Pi-network output. (Soon to be released — and we'll have it for you.)

Super-Six Converter — Covers 10 through 75 meters and 19 and 49 mc broadcast bands, Ideal 6-band tuning head for Super-ceiver. Powered by receiver. \$5.25 down......\$4.17 per month for 12 months.



#### HARVEY WELLS

**T-90 Super Bandmaster** — Fixed or mobile operation. Bandswitching. 90 watts CW input, 75 watts phone. Built-in VFO. Complete with tubes.

\$17.95 down.....\$9.78 per month for 18 months.

R-9 Receiver — Double conversion all bands. 63/4"
height permits easy under dash mounting for mobile installation.

\$14.95 down ...\$8.14 per month for 18 months.



#### **MULTI-ELMAC**

AF-67 Transciter — 7 amateur bands 10 through 160 meters. Single knob bandswitching — built-in VFO. 40 watts audio at 500 ohms. Operates from 6 or 12 V AC or DC.

\$17.70 down......\$9.64 per month for 18 months.

PMR-7 Receiver — 10 through 160 meters and standard broadcast. Slide rule dial. High selectivity. Built-in noise limiter — adjustable squelch. Only 7" wide.

\$15.90 down......\$8.66 per month for 18 months.



#### **MORROW**

**MB-560 Transmitter** — 65 watts input. 80 through 10 meters. 6146 final. Shielded exciter. Gang tuned low level stages.

\$21.45 down......\$11.69 per month for 18 months.

MBR-5 Receiver — 80 through 10 meters. 13-tube dual conversion, superhet. With tubes, less speaker and power supply.

\$22.45 down......\$11.89 per month for 18 months.

TOP TRADE-INS—We have hundreds of standard brand pieces of equipment in our trade-in department and prices are realistic! Write for current bulletin, NEW CATALOG—The most up-to-date presentation of amateur equipment available. Chock full of gear and accessories. Write for your free copy today!

# urghardt Radio Suppli

P. O. Box 746, Watertown, So. Dakota • Phone 5749

100% Guarantee
Satisfaction Guaranteed
or your money refunded
after 10 day trial.



Terrific Trade-Ins—As liberal as anyone in the country ... and yours may be worth more at Burghardt's. Trade-ins usually cover down payment on your new gear.

10% Down—Easy Terms
Up to 18 months to pay on balances over \$200. Terms adjusted to your budget. Full payment within 90 days cancels interest.

Speedy Delivery—Personal Attention—No order too large or small for personal attention, All inquiries acknowledged and orders processed day received.

#### METER CONVERTER

Kit (with crystal less tubes)

Complete, wired & tested, with tubes \$1595 & crystals .....

**Broad-Band Crystal** Controlled Converter for 6 Meters

- Compact No alignment necessary
- Simple to assemble Output IF frequency can be changed by merely changing the crystal (crystal range of 40 MC to 50 MC).

#### SPECIFICATIONS PRINTED CIRCUIT 6 METER CONVERTER

Freq. Range 50-54 MC

(51 MC design center)
Sensitivity 1 microvolt or better
Output IF\* (1) 600 KC to 1500 KC

7 MC to 11 MC (3) Special (available any range 600 KC to 35 MCI

range 40 MC to 50 MC).

Plate Power 150 volts to 250 volts DC @ 15 ma to 20 ma Heater Power 6.3 volts @ 60 ma Tubes 6AK5 RF Amplifier 6J6 Mixer Oscillator Size (overall) 4"x3½"x3½"

Weight 3 ounces Crystal Frequency 49.4 MC or 43 MC depending on IF desired. (Oscillator

Specify IF when ordering.

#### FO-1L 100 KC OSCILLATOR

Kit, complete with \$1295 tube & crystal..... Wired & tested..... \$1595

Printed circuit oscillator for band-edge calibrator and frequency standard

FO-1L

Additional requirements: Power 6.3 volts AC @ 150 ma 150 volts DC @ 8 mg

FMV-1 10 KC MULTIVIBRATOR



FMV-1

Wired & tested, \$895 Used in conjunction with the FO-1L 100 KC Oscillator to form a complete

secondary frequency standard. When the FO-1L 100 KC Oscillator is ac-

curately tuned to zero beat with WWV

Kit, less tube

\$595

transmissions, precise frequency measurements to 30 MC can be made. Additional Requirments: Tube — 12AT7

Power - 6.3 volts AC @ 300 ma 150 volts DC @ 15 ma

#### ORDER DIRECT FROM THIS ADVERTISEMENT

When cash accompanies the order, International will prepay the postage; otherwise shipment will be made C.O.D.



18 N. Lee Phone FO 5-1165 OKLAHOMA CITY, OKLA.

[from page 94]

#### Feeding the Antenna

This antenna will handle a kilowatt with difficulty unless you try to tune the feeder then watch long lengths of feeder go up smoke. The best feeding method is to run t feeder directly to the final tank output link. the lower frequencies there may not be enough turns on the commercially made link to lo up the final satisfactorily. Use some good so insulated wire and wind your own, maki five or six turns and trying it for loading. you make too many turns you can leave t link only part way in the tank coil. It is be to have some spare loading available for t loading will drop a bit when it rains and yo can push the link in to compensate.

If you have made both ends of the antenn the same length and have cut it the right leng; the standing wave ratio should be very love The twin-lead indicator mentioned in the ARRL Handbook will provide an indication this ratio and can be put together in a fe minutes. Another method of checking this to pull the link out of the tank coil, tune the tank, then push the link in and notice if the tank condenser has to be retuned very muc Capacitive or inductive reactance reflected from the antenna can be detected in this wal When the antenna is correctly cut it will r

flect neither back to the final.

Most of your rigs that use a Pi-Network final will work with 300 ohm feeders and thu they will load up this antenna with no diff culty. They will load almost anything, but th difference is that with this antenna you wi suddenly find yourself working out.

That's it. In less than an hour you shoul be able to cut and erect a good antenna for any band, all tuned to one specific frequency

You don't even have to climb trees.



"Quite a rig you've got there, Sam!"



### as the future of UNIVAC®

When planning your future, it is necessary to choose that company which presents the most complete program for you. The opportunity at Remington Rand Univac can only be limited by the individual. Excellent salaries, benefits and educational programs are yours to guarantee this limitless future.

At UNIVAC you will be working with men who developed much of the basic knowledge of computers-who designed and produced components being used by the manufacturers in the fieldwho set the standards that the others follow.

Send complete resumé to

Now is the time to come to Univac where ambition and professional skill find their reward in limitless opportunities in an expanding organization.

Immediate openings for:

FIELD LOCATION ENGINEERS with a college degree in a scientific or engineering field and experience in electronics. Extensive electronic background may substitute for some college. Many opportunities for rapid advancement.

FIELD LOCATION TECHNICIANS Technical school background and preferably some experience in electronics. These positions can lead to full engineering responsibility.



Registered in U.S. Patent Office

### Remington Rand Univac

DIVISION OF SPERRY RAND CORPORATION AT ANY ONE OF THESE THREE PLANT LOCATIONS

MR. D. A. BOWDOIN Dept. JP-21 2300 W. Allegheny Ave. Philadelphia, Pa.

MR. KURT PINKE Dept. JS-21 1902 W. Minnehaha Ave. St. Paul W4, Minn.

MR. FRANK KING Dept. JN-21 Wilson Avenue South Norwalk, Conn.



#### **VHF** [from page 73]

Rensselaer, Indiana: Bill (W9KLR) cc through from the "Hoosier" state with:

"Seems like I can hear well enough on meters, just need more power to get through QRM. Have been hearing you on aurora various QRM. Have been hearing you on aurora various in March. The most consistent W1 though is W1. Ray. He never misses any and I've heard hir different days in March. We rag-chewed for two minutes before any other station showed un March 28th. Funniest feeling to have a W1 myself with no competition. Good feeling too, Bill. We had it once from W8 land, first W8 conwith New England.
"We had thirteen days of aurora here during month of March, by far the most I've ever hear Two Meters." From all predictions it surely she a wonderful year for DX on the VHF bands seems like you're active enough that you'll get share.

Merced, California: Another "Gold Hum heard from is George (K6QVW):

"I am on the air every night on 50.67 mc. Rum 120 watts PM into a 4X150A with a 4 element I 40 feet off the ground. There is plenty of activit this region. I talk every night to the San France area, about 135 road miles over a moun Bay

range.
"I'm looking for a good tank coil arrangement will stand power, Helping K6LYB to put his 4-25s Six Meters. It will run about half a gallon." to know that activity is at a high level in your co

Fort Smith, Arkansas: Bob (W5EUQ) fil the "Bear" state has this to say:

"Rig here is a 6BH6-6U3-6C4 cascode output verter. Receiver is an NC18 D and antenna is a h made 4 element widespread beam. Transmitter 12AX7 oscillator, 12BH7 RF amplifier, 6L6 modul

and 12AX s. amp.
"The only place I have worked is here in Smith and 75-80 miles north to Fayetteville, Arkan Stations there are W5BHS and W5TIA. About miles west is Farmington, Arkansas and I've worker.

miles west is Farmington, Arkansas and I've wo: W5WHU several times.
"Opening here on January 23rd when I he W1's, W2's and W3's. Have been glued to my recever since but have just heard meteor bursts." be patient, Bob. Your chance is coming when the W1's, 2's and 3's are fighting to get you on opening. Helen will be one of them.

Another "Buckeye" Akron, Ohio: from, Arline (W8SSF):

"Would like to pass along this information your V.H.F. section. There will be a V.H.F. pa for those who work the 50-54 mc band and tI families. For those who plan to come, bring all a picnic basket as we expect to make a day of and have a lot of fun.

"The date, July 1, 1956, at the home of W8P Homer Everhard, Sr. QTH—145 South Lyman Str Wadsworth, Ohio. Homer will be at his rig for the requesting information also mobiles will be these

requesting information, also mobiles will be there

direct those who have six meters in their cars. "If the weather does not favor us, that will be a hold back, as Homer, W8PTL, has the place take care of all. So, come one, come all, you six-me

operators.

"W8SSD and W8PXX used to have a noon so on six meters. They started to tune for others at the activity has grown so much that they are makenown as the "Noon Day Rattlers." Anyone intested in a six-meter contact just give a listen they tune the band for anyone that wants to get in Thanks, Arline. All good news to know.

73, Sam, W1F

#### 7th Uniontown Gabfest

Saturday, June 30 the Uniontown ARC will hold for at the Club Grounds on the Old Pittsburgh Road j off Route 51, about 2 miles North of Uniontown, I Program includes Auction of radio gear, games Horseshoes, Movies, Prizes and a raffle, and a mystaspeaker (not lined up yet at date of publication). For for the hungry, usual side dishes free, other refrements at a nominal cost. Club House opens at Noo Stag. Registration \$1.50. Club transmitters will be the air. Further info from Club Station W3PIE, Fit 849. Uniontown, Pa. 849, Uniontown, Pa.

#### NEW LOW PRICES! - EFFECTIVE MAY 1st

COMMAND TRANSMITTERS & RECEIVERS-ARC-5 and SCR-274 as available



### FAMOUS "Q" 5'rs

EXC. CONDITION

Receivers, w/o dynamotors

R-23 ea BC-453, 190-550 Ke Exit	\$10.95
R-25 Marine, 1.5-3 MC, used \$5.95, new	. 6.95
R-26 or BC-454, 3-6 Mc, used. Exit	6.95
R-27 or BC-455, 6-9.1 Mc, used. Exit.	. 5.95
R-28, 100-156 Mc, as is, w/o tubes, 7.95, used w/tubes	9.95
Exit	. 13.95
R-4/ARR-2,234-258 MC, as is w/o tubes, \$2,95,	
w/tubes, used	. 3.95

Transmitters, w/o modulator or dynamot	or
T-18 Marine, 2.1-3 Mc, as is, w/tubes, 3.95, used 4.95, boxed	7.95
T-19 or BC-696, 3-4 Mc, as is w/tubes, 6.95, used, 7.95, boxed	8.95
T-20 or BC-457, 4-5.3 Mc, as is w tubes 2.95, used 3.95, boxed	5.95
T-21 or BC-458, 5.3-7 Me, as is w/tubes, 2.95, used 3.95, boxed by depot	4.95
T-22 or BC-459, 7-9.1 Mc, as is w/tubes, 2.95, used 3.95, boxed New	5.95
T-23, 100-156 Mc, as is, w/o tubes, 7.95, used, 9.95, new w/xtals	34.95
Special—one usable R-28 and T-23, both for	17.50
Miss Command For insured and it is	

Operial Wie disable 10-28 and 1-25, both for	17.00
Misc. Command Equipment as available	
Receiver dynamotors 14v used 3.95 new	4.95
BC-456 SC Mod w/tubes, new 4.95, used	3.95
MD-7 ARC-5 Pl Mod w/tubes XInt	8.95
28 v dynamotors inc w/above mods.	
Separately, w/o mod	3.00
Receiver spinner knobs 69¢,	71.50
New 24 V Trans. et at 12v, 2A 110v 60 C input	
Plugs for rear of receiver	1.00
BC-442A Ant. Relay, cont. vacuum cap,50 MMFD 5KV	0.00
Send-Receive relay, RF ammeter, new	
110 1100	



	Jack, and	spinner knob,	With in-
	Structions		1.99
1625 Tubes, for trai	as & mod,	50¢	3/1.00
1625 Tubes, for trans			8.00

	Popular Dynamotor Specials	
4	Recvr. Dyna, 12 V in 220 @ 80 ma Out. new	4.95
6	Same as above, 28 V. new	4.95
er	of above used	3.95
	PE-101C, Transmitter, 12 or	



#### WESTON-SANGAMO-YOUR CHOICE

RK-65 Tetrodes, 500 watts each, 6 watts drive, special, 9.95 each, 2 for

. NEW, 2" SQUARE
0-200 Ma
0-300 Ma 0-500 Ma
0-500 Ma 0-20 VDC
0-40 VDC
0-300 VDC
Special, 3 for 9.00

DM -34 DM -30



8.95

Filament Transformer—240 VAC, Primary 5 VAC, 30 A, 15 KV insulation when used on 120 VAC, gives 2½ VAC for 866's or 249's.  Heavy Duty Collins choke, 300 Ma, can take 500 Ma peaks, new  3.95
249C, 5000 volts, new, each 1.95
Bleeder resistors, 50 K 100 W, new 1.95
Special, all above, including 2 tubes for 500 Ma (50 lbs) 15.95
Transmitter Power Supply Kit contains chassis, 2 transformers, 2 tubes, 2 sets filters and bleeders, gives 500 VDC and 250 VDC, value of parts 23.34 Special
Mobile Microphones, newly assembled, W.E. D173015

.95

1.95

1	Mobile Microphones, newly assembled, W.E. D173015 similar to the TC-128, push-to-talk switch, 3 cond. 5' curl, cord, new
-	Brand New Headphones, your choice of HS-23, 8000 ohms, or HS-33, 600 ohms, complete with brand new rub- ber cushions
1	Used HS-23, w/o cushions
-	Brand new Impedance matching transformer, plug in, 8000 ohms to 600 ohms, takes std plug, boxed 69¢ each, 3 for

for phones, std plug other end brand	
new, boxed	
Brand New J-38 Code Keys, for send-	
ing CW with your transmitter1.45	
Build your Modulator, Input trans.,	
1.50, driver, 2.50, mod. trans. 2.95,	
2 new 1625 tubes, value 7.70, all for	6.95
Stewart Warner Ammeter, 60-0-60 Amps, brand new	

95¢, 6 for			5.00
Phone-CW Filters, 1020			
with switch		2 17 0, 000	1.89
GP-7 transmitter with al	I tubes and	80 meter coil	unit
only			13.95
Less tubes and coil u	nit		7.95

BC-375, 100 w CW or phone	
transmitter, less tuning	
units, contains multiturn	
coil used in KW pl net-	
work final, w/o tuning	
units, but with tubes	12.
TU-7, 4.5-6.2 Mc: TU-8,	
6.2-7.7 Me; TU-9, 7.7-10	
Me: TII-10 10-12 5 Me:	



Tuning Unit for above



MN-26C direction finding Equipment	
MN-26C Receiver w. dyna	10.95
MN-20E Loop	4.95
MN-52H Az Cont Box	2.95
All above new, special, 1 each for	17.95
Antenna Insulators. Bendix MT-48C,	
plated end caps, new, 15¢ each, 10 for	1.25
Control Box w/5 Ma S meter, special	. 1.98
Antenna Reels, new 28VDC, 1/4 Hp,	0.00
w/Gear box	2.95

#### Last Minute Specials

aco. minaro operaro	
12 V Solenoid for Mobiles, 100 Amp Capacity! 1.4	9
New Mfg. Surplus wire wound flat strip resistors. Some contain 3 separate resistors orig. cost	7
Assort12/\$1.0	0
Hey! You sub-miniature Bugs-we have 11/2" speakers.	

2.00 Minimum Order. All prices Subject to Change without Notice. Canada & Mexico minimum 10.00. Cash with Order. Sorry, no COD. California Orders include 4% tax. Prices FOB Los Angeles SAM'S SURPLUS, 1306 Bond St., Los Angeles 15, California

Good until July 30th ONLY

### SPECIAL OFFER



TO INTRODUCE OUR PRODUCT MORE WIDELY

#### NOT SURPLUS

Limited to fundamental frequencies in the three, seven and eight megacycle bands.

Large assortment means we can select your requested freq. plus or minus one kilocycle.

ORDER DIRECT

A PROFESSIONAL CRYSTAL AT AN AMATEUR PRICE

\$200 POSTPAIR

#### E. B. LEWIS CO., INC.

11 BRAGG STREET
EAST HARTFORD 8, CONNECTICUT



MODEL 62T10 CLIMASTER VHF

# NEW! CLEGG VHF 3-BAND, 150 WATT AM/CW TRANSMITTER

10-6-2 meters — completely band switched

Only equipment of its kind combining all these features:

- 10-6-2 meter bandswitching
   TVI suppressed
   High level modulation
   Speech clipping
   100 watts
- Speech clipping
   100 watts AM —
   150 watts CW output on all 3 bands



See your jobber, or write for complete information

CLEGG LABORATORIES, INC.

Morristown

New Jersey

#### MOBILE REFERENCE-SHIFT MODULATOR

[from page 39]

at least 5 h. and a current-carrying capacity c

approximately 200 ma.

Important voltages and currents are show on the schematic, Fig. 2. Total current drain 210 ma. max.; 100 ma. for the final, 100 ma max. for the modulator, and 10 ma. max. for the driver and speech amplifier. Optimum plat voltage is 350—375 v.

Values for C8, C9, and R15 in the final plate and screen circuits depend on the tubrused. Values shown are typical for a 1614 of 6L6. The voltage rating of both C8 and C5 should be at least twice the plate voltage.

Audio quality is good; the modulation leve is equivalent to or higher than that of any conventional modulator running the same maxi

mum input power.

I have not included a description of the resection of the rig since your judgment in this matter is probably as good as or better than mine. However, my rig uses a 6AH6 series tuned Clapp vfo (screen resistor 220,000 ohms and grid resistor 22,000 ohms) doubling in the plate circuit from 160M to 75M. The final is a 1614 operating straight through on 75M

#### Construction

Placement of components is not critical; a reference-shift modulator should be laid out according to the same principles that apply to

any ordinary modulator.

The reference-shift-modulated rig shown in the photograph was built on an LMB 144 box chassis. This chassis consists of two members which form a rectangular box. The member not shown is mounted under the dash with two bolts. When the rig is in place, tubes face the firewall and controls face the front seat. The rig occupies a space under the dash only 2-½ in. high and 10 in. long.

Components are admittedly crowded. I do not recommend you attempt such compact construction unless you are outstandingly pa-

tient.

However, if you do use an LMB 144 box chassis, replace the screws that hold the chassis together. The two 6-32 machine screws supplied are not adequate. Replace them with two no. 8 x ½-in. sheet-metal screws.

#### Conclusion

The reference-shift circuit provides a simple and inexpensive means for obtaining high-level plate modulation without transformers and is particularly well adapted for use with low-power rigs. I hope that other experimenters will investigate the possibilities of this circuit; and I enthusiastically welcome correspondence on the subject of variable-plate-current Heising modulation systems.

#### YL MARINE OP'S

[from page 53]

adder. Then she told them to come up one by one into her office and not to be disorderly. The men queued up and everything went smoothly.

At Bombay, India, where the *Union Car*rier had to deliver cargo, Billie met the son of a wealthy Indian chemical manufacturer. He promptly fell in love with Billie and pleaded with her to marry him. Despite the lavish surroundings, which she admits were intriguing, she turned him down.

Billie's last ship was the tanker S.S. Gulf Banker. Billie says it was a good one and she spent four and a half years aboard, plying the blue Caribbean with nothing to worry about but eating, sleeping, and standing a watch.

Billie received permission from the owners, the Gulf and South American S.S. Co., to install her own amateur station on the Gulf Banker. She had a 25-watt mobile rig with a home-built power supply and a fine three-telement rotary beam up on the deck. Everyone traboard ship had a part in building the antenna. She had to turn it by hand, but found it would beam right through the smokestack. An NC-57 receiver completed her station, which she operated under the call W6HBO/MM. Her bulkhead was plastered with QSL cards and thers were much in demand, for Billie apparently is the only American YL ever to have operated maritime mobile!

In the fall of '53 Billie decided to quit the sea when she found her eyes were back to normal. She has always loved animals—she even took a Siamese cat and her three kittens around the world with her on the *Union Carrier*, and sold two of the kittens in Hong Kong. Now Billie is in her second year at the Veterinary School at Alabama Polytechnic Institute and declares she doesn't miss the sea too much—except perhaps at quiz time. Her call now is W4CJV, and she is trustee of the local club station, W4UJJ.

#### YLs on Scandinavian Ships

Currently there appear to be no girls operating on any ships flying the U.S. flag. However, according to the Radiomarine Corporation of America there are some sixty Scandinavian (Norwegian, Swedish, Danish) ships that carry women radio operators and it is believed that there are a number of Russian vessels which also carry women operators.

Due to the manpower shortage in Norway it has long been the practice to train girls as combination radio operators and pursers. W4EWS/MM tells us that these girls do all the

[continued next page]







# COMMUNICATIONS RECEIVER

#### FEATURING:

- Six bands covering .54 to 31 Mc. AM, CW, MCW, and FS with appropriate FS converter.
- Accurately calibrated main tuning dial plus auxiliary dial with full Electrical bandspread.
- A ferrite transformer provides accurate antenna matching for 75 ohm unbal. and/or 300 ohm balanced inputs.
- Sensitivity: 1 (one) microvolt or better for 10-1 signal to noise power ratio, 1.5 to 31 Mc. Less 5 microvolts for .54 to 1.5 Mc.
- Image Ratio: Better than 60 db.
- Selectivity: Variable in 6 steps from 200 cy to 5 KC, 5 crystal and one non-crystal positions.
- Input: 105-125VAC 50/60 cy., approx. 90 Watts 6V.-6A, and 250VDC.-0.1A
- Output: 4, 8, 16, 600 ohms, 2 Watts high quality audio-better than -60 db hum level.
- Highly effective noise limiter Calibrated "S" Meter - Dial locks.
- Specially designed Audio Selectivity control with variable bandwidth.
- Diversity operation is available with the GPR-D. Provisions for external control for HFO, BFO, IFO.
- SSB Coaxial IF output & Audio input.
- Cabinet or rack mounting . . . 52 lbs. . . . 20"w. x 10"h. x 15"d. (Cabinet.)

#### Tube complement:

6AB4 Grounded grid input RF amp. 6CB6 2nd RF 6AU6 1st Converter 6AG5 Oscillator 6BE6 2nd Converter and Oscil. 6BA6 IF Buffer Amp 3-6BA6 IF Amplifiers 6AL5 Det./Noise Itr. 6AG5 BFO 12AX7 Avc and Audio Amp. 5V6 Output 0A2 Regulator 5U4G Rectifier

Complete receiver - Amateur Net \$39500 Matching Speaker \$16.00 extra



IN CANADA:
TMC Canada, LTD.
OTTAWA, ONTARIO

MAMARONECK,

#### GEIGER COUNTER TUBES This is "the heart" of the Geiger counter! Famous 1B85. Brand new and boxed. Terrific buy for you do-it-yourself'ers. Only STROBOSCOPE TUBE SN-4. Brand new. Each \$3.75 \$1.95 \$2.95 Oscillograph!!! Hickok Model RFO-5 This precision instrument originally cost \$400.00! Contains 0-3 MC, vertical amplifier 10-30 and 100-900 Kc. frequency modulated sweep, 0.40 Kc, sawtooth sweep. Demodulator input. Voltage calibrated vertical control. New in original package. Get this high quality lab and service test instrument at fraction of former price! \$59.50 Quantity limited SET OF SPARE TUBES, including scope tube, \$5.95 CHEST MIKE-Used. Ea.

FREE: On request with every purchase of \$3.00 or more, one 1-51 Hand Code Key! AND, with a \$5.00 or more purchase, a free aircraft-type slide rule, on request.

MINIATURE HAND CRANK GENERATOR

49¢

Latest type, light weight. From recent model field phone. Many uses. Brand new. Terrific buy! COMMAND TRANSMITTERS 

CAT. NO. 105 IS OFF THE PRESS! Get yours!
All items F.O.B. L.A. Prices subj. to change without notice. Calif. buyers add tax. Send 25% deposit with C.O.D.

J. J. GLASS ELECTRONICS CO. 1624 S. Main St. Los Angeles 15, Calif.

#### Bound Volumes

CQ in book form for the ham who wants to have a neat and attractive bookshelf. It is always worth a little extra to go first class and do things right. This will make your shack really look like a million dollars, and for only \$7.95, a steal. Loose copies of magazines are OK for the workshop, but if you sport a good looking shack you will want bound volumes.

And don't try to send for one of these next year. We cleverly make up only a few of these volumes and usually run out of them way before the demand dies down. Send for yours right now.

Since we ran out of the bound volumes last year we are binding up a few more of the 1953 and 1954 volumes for those that missed them. There are only a limited number of these available so jump. Foreign purchasers will have to send \$1.00 extra for postage.

CQ MAGAZINE	
67 West 44th St., No	ew York 36, N. Y.
Enclosed \$	ForBound Volumes
YEAR WANTED: [] 1	953; 🗆 1954; 🗀 1 <b>955</b> .
NAME	CALL
ADDRESS	242280
CITY	ZONE

paper work and stand a somewhat haphazard radio watch which usually consists of opening up two or three times a day with a "QRU?" The paper work load is so heavy that many of them do not even get ashore in some ports. Dick adds that without exception the wegian girl operators are generally good looking and have an excellent command of English. Often they wind up married to one of the mates aboard ship and thenceforth sail as a married couple on the same ship. For "safety reasons" and because of the additional secretarial work, amateur radio stations are not permitted to be used by operators on Norwegian merchant ships.

In Norway maritime operators are trained in seven schools of navigation run by the government. Rolf Suleng, chief technical instructor at the Bergen Sjomannsskole reports that every year about 150 candidates from these schools pass their exams for 2nd class radiotelegraph licenses and that some 25% of

the pupils are girls.

One Norwegian (OM) maritime operator says that in his personal opinion the girls are just as good as the men with the key, but when it comes to repairing some broken down equipment "most of them lose their heads." He adds this opinion is common among Norwegian men operators, and that the girls often can't even change a fuse or a tube, and in an emergency there have been cases where some mistakes have been made.

This operator recounts a story he heard from a chief engineer who was telling about one time he was on a ship when a fire broke out and they had to abandon the ship. "I was number two to be in the lifeboat," said the engineer, "and do you know who was first?it was Olge, the woman operator!" In her praise it must be added that after they tried the lifeboat transmitter and it didn't work (supposedly her fault as it was powered by batteries and after four months aboard she had not once looked after them, and didn't even know they were there), she went back on board the ship and stayed at the transmitter as long as possible, calling SOS. A few hours later the crew was all picked up by another vessel.

#### Canadian YL Marine Operators

Besides their own Norwegian girls there have been many Canadian women working as radio operators on Norwegian ships. One girl, from Eastern Canada, made so many crossings of the Atlantic during World War II that she was decorated by the King of Norway and a book written of her experiences, "The Lucky Mossdale," was a best seller in Norway.

Miss Lylie Smith, also a Canadian girl, has been a radio operator on Norwegian ships for ten years, having started early in 1946. (Prior this she was the first girl radio operator to hired by the Hudson's Bay Fur Trade Co. their northern posts.) Since being at sea has spent five years in the far east run—ulippines, Hong Kong, Singapore, Dutch dies and two trips to Shanghai just after the ar. For almost the last five years she's been a run between the United States West Coast deurope—France, Belgium, Holland, Geruny, England and Norway, with one roundendy trip from England through the editerranean to Australia, to Los Angeles de back to Europe. Currently Lylie is aboard Siranger on a run from Los Angeles hich goes around South America and back the West Coast.

#### gulations Do Not Prohibit YL Operators

Though there are at present no girls serving as maritime radio operators aboard U.S.rg ships, Secretary of the Federal Communitions Commission, Mary Jane Morris, rerts there is no law or regulation of the FCC hich would prohibit women from serving as diotelegraph operators on board ships.

Such operators now also are licensed by the S. Coast Guard as radio officers. The Chief the Merchant Vessel Personnel Division, fice of the Commandant U.S. Coast Guard in Washington, D.C., reports: "The Coast uard regulations for licensing and certifi-

In addition to those mentioned in the preceding account, we express our appreciation to the following persons who assisted in providing information for this record of girl marine operators—W7HDS, W6PCN, W3OB, W5CA, K4AJG, W2PFB, W6LYG; Dr. L. S. H. baird, ex-9HO; Y. Kaldal; Fred Howe, ROU; Wm. Simon, VWOA.

ting of merchant marine personnel does not ontain any restrictions prohibiting women om serving as Radiotelegraph Operators on ssels of the United States."

One former woman maritime operator aims the Unions are against the use of girl perators aboard ships and that the shipping ompanies, with rare exceptions, hate to make langes. She feels that women could, and lould be encouraged to enter this phase of dio, and that it's nothing but "inflated ego" the part of the male operators which keeps the YLs from making the \$500 to \$800 per conth paid to maritime operators for handling comparatively light traffic schedule. She adds lat quarters these days are strictly private, and job of radio will never be kicked off a ell-run ship.

[Continued on next page]

# **Cramped For Space?**

NOW...a maximum of signal a minimum of antenna

# WESTERN GEAR'S NEW COAXIAL-TENNA

- · matches 72 ohm coax
- high efficiency, excellent radiation pattern
- expertly machined, strong aluminum construction
- built in brass coaxial connector; Coaxial-Tenna mounts on 34 inch pipe



#### DELTA-TENNA GROUND PLANE



- matches 52 ohm coax
- gold anodized elements
- uniform loading characteristics over an entire amateur band
- meets or exceeds all FCDA specs

Prices (either type) \$19.95 (2 mtr.), \$24.95 (6 mtr.), \$29.95 (10-11 mtr.). Can be supplied for any commercial or amateur frequency from 25-465 megacycles. In stainless steel or brass at extra charge.

Available through any major parts house or send your check or money order direct, allowing 8 lbs. (10-11), 6 lbs. (6), or 2 lbs. (2) for shipping charges.

#### WESTERN GEAR CORPORATION ELECTRO PRODUCTS DIVISION

132 W. Colorado Street . Pasadena 1, California

"The difference is reliability" \* Since 1888





SPECIAL

BC-458, 5.4-7 Mc transmitter, used condition, Perfect for conversion to SSB at an 2 for \$5.00

MODULATION XFORMER, 20 watt, P.O.T.C.S. transceiver, Stancor 95A10, Also used as 1:1 isolation, Boxed \$1.95
FILA XFORMER, 24v, 1.5A, Compact FB all surplus gear \$1.95
FILA. XFORMER, 5v, 13A, new \$2.95
TUBE TYPE 1025 (SSB types)—Dozen \$2.25

2 for \$5.00

88 Cortlandt St. New York 7, N. Y.

[from page 103]

So if any of you YLs are interested, the nothing in the rules and regulations to s you—but you'd better be good at radio, a have a little spark of the pioneer in you, compete in a field that to date has been alm exclusively masculine.

#### A-C GENERATORS

[from page 23]

generator during the hurricane power-outa If a 2,000 volt plate transformer had be available, for example, the same capacitor fect could have been had with a 0.4 μfd pacitor tied across the 2,000-volt winding. course this capacitor would have to be rat at a minimum of 2,000  $\sqrt{2}$  working vo d.c., or 2,820 volts, because it would be su jected to the peak a-c voltage. A  $0.5 \mu$ 3,000 wvdc, capacitor would have done nice

The current drawn by the capacitor shou not exceed the rated current of the tran former secondary. Thus, I = E/X<sub>0</sub> is the ge eral formulation of Ohm's Law with capaciti reactance, where  $X_c = \frac{1}{2} \pi f C$ , where f frequency in cycles per second and C capacitance in Farads. Assuming 60-cyc operation and rearranging the constants, get the pracitcal formula, I<sub>e</sub> = 0.377 V<sub>s</sub> where I<sub>c</sub> is the capacitor current in mil amperes, Vs the transformer secondary vo age, and C the capacitor size in  $\mu$ fd. For t case just mentioned a 0.5 µfd capacit operating at 2,000 volts, 60 cycles, a.c., the current drawn by the capacitor from the tran former secondary will be 377 milliampere

#### **Transformer Sources**

One possible source of a heavy duty, high voltage transformer for this service might b the local power company. These days, almoi every home has lots of electrical appliance with the result that the old transformer mounted on the light-and-power poles are n longer adequate for present-day loads. Nowa days it is rare to see a pole, transformer of less than 10 kva. capacity. Power companie are rapidly replacing the older and smalle equipment and usually this old equipment sold for scrap. These transformers nearly a have a dual voltage secondary rated 115/23 volts, and a primary rated 2,300 volts, wit an internal center tap which is easily ac cessible.

The author once bought a 1 kw and a 3 kw unit at the local power company for very reasonable price. These transformers will be quite adequate for any size induction gen erator likely to be contemplated by any hami Again, caution: DANGER! HIGH VOLT AGE!

Regulation

The problem of voltage adjustment can be attacked from two angles: First, the actual amount of capacitance connected for excita-

REX RADIO SUPPLY

ion may be varied, or: Second, a fixed-excitaion capacitor may be connected but the voltge to it may be varied. Either scheme will ary the excitation, and like any other isoated generator, when the excitation is varied, he output voltage will vary. Figs. 3-b and 3-c llustrate the practical application of these chemes.

#### **Tryout**

Once the generator is mounted and belted of the gasoline engine (the lawnmower engine vill do nicely here, if you can get away with t!) with pulleys arranged so that the generator speed will be in the proper range, and he excitation system is connected, we are eady to fire up the rig. With an a-c voltmeter connected across the terminals, the engine is tarted and slowly the generator is brought up o speed. If all is well, the voltage will quite auddenly build up to considerably more than he full rated voltage (about half again as purch)

This is the tricky phase of the game. If the generator does not build up voltage, keep speeding it up. If it does not build up even let top speed, stop the engine, unbelt the generator, and plug it into house current for a moment. This will reestablish the residual magnetism in the generator iron which causes t to build itself up. Normally, it will build up without difficulty if it is momentarily run up to 300 or 400 rpm above rated speed. Once it has built up, the engine speed is lowered until the voltage is about normal and a 120 volt, 100 watt light bulb is connected to the terminals to furnish a bit of load. This has a stabilizing affect

If you have included a voltage adjusting scheme in your system, you should now bring the engine up to operating speed and set the voltage to its normal value. Otherwise, voltage may be set by adjusting the generator speed. Once these preliminary settings are made, they should be noted for future reference. You will be amazed at the "cleanness" of this a.c., for it will be almost a pure sine wave, depending on the design of your particular motor.


#### Output Frequency

The frequency can be checked with an electric clock—if the clock does an hour in approximately 60 minutes, you're set! While maintaining precisely 60 cycles is not required, it will be desirable to err in the direction of higher frequency, for this will be found to produce less heating effect in the transformers of your radio equipment. In other words, your receiver power transformer will run cooler on 115 volts, 70 cycles than it will on 115 volts, 50 cycles.

The author has operated a standard National NC-183 receiver on a 115 volt, 400

[continued next page]





# Special Redundant Offer

Beautiful full-color maps in great profusion. Important, detailed information, which correctly memorized, will put you one up on even the most eminent geographers. Only \$12.50, wow! Year's subscription to CQ included.

CQ Magazine 67 W. 44 St.,	CQ-6	
New York 36, N. Y.  Gentlemen: Please send me (postpaid) the New dor World Atlas plus a one year extension subscription to CQ. I check money order for \$12.50.	new enclose	
(name)	(call)	
(street address)		
(city) (zone) N.Y.C. residents add 3% sales tax	(state)	

#### [from page 105]

cycle power supply with quite normal and satisfactory results. So, since a-c generator frequency is directly proportional to generate speed, run your unit a little fast if you cannot be sure of the exact frequency.

# An Effective Cure for Gasoline Engine Ignition and Exhaust Noise

Now that we have gone into the power transformer business, we might as well carry it to its logical conclusion. Assuming that All Hands are now possessed of a healthy respect for the dangers of high voltage, the following scheme may be employed to produce excellent reduction of the annoyance caused by the ignition system and exhaust noise of our gasoline engine used to power the generator.

The idea is to use two transformers and step up the voltage at the generator, run it as high voltage over a transmission line to the point of use, and then step it back down to 115 or 120 volts for use, thus physically separating the generator from the operating location by a distance sufficiently large to practically eliminate the effects of ignition and exhaust noise. The principle here is that, for a certain amount of power to be transferred over a transmission line with a given loss, if the voltage be doubled, the size of copper wire may be reduced to ½ the original size.

The Hingham, Mass., Amateur Radio Club has used this scheme for the past two Field Days with very satisfactory results. Last year the generator was located about 500 feet from the nearest operating position. At this distance the exhaust noise of the engine was barely discernible and ignition noise was no problem at all. In fact, the club members were so unaware of the presence of the generator that it ran out of gas several times during the contest for lack of attention! Transmission in this case was at 450 volts along a line strung from tree to tree and hung from glass antenna strain insulators. The average night-time load was approximately 2,500 watts, including the 600-watt electric coffee pot. Due to the dangers and difficulties involved, operation of an amateur power transmission line at voltages in excess of 450 volts is not recommended unless some rather expert advice and guidance can be had.

#### Summary

We hope this article has whetted the "ham ingenuity" of some of the readers and that it will offer a few ideas for further development. We feel that the description of the induciton generator is justified by the fact that while relatively few hams own a real a-c generator of the common variety, many of them can probably locate an induction motor, a suitable transformer and a capacitor. See you this summer, and more power to you.

#### CYCLE 19

[from page 30]

morning and early afternoon hours of the late fall, winter and early 'spring months, and during most of the daylight period of the summer months, minimum skip distances on 20 meters will be as short as a few hundred miles. During such times, relatively near stations will be skipping in with the DX causing considerable QRM. Figures 5-8 show good examples of the typical change in 20 meter propagation conditions expected during the next few years of maximum solar activity. For both circuits shown, note the early morning openings, followed by a higher LUF, and consequently weaker signals, during the late morning and afternoon hours, with band conditions improving again later in the day and during the evening hours. Note also the greater number of hours that the 20 meter band is open on both circuits as compared to the openings during the period of low sunspot activity.

#### Meters:

As the sunspot numbers increase, the 10, 15 and 20 meter bands open to more areas of the world, open more consistently, and remain open for considerably longer periods of time. The improvements in propagation conditions on these bands during the period of sunspot maximum is quite emphatic. Propagation conditions on the 40 meter band also change considerably during this period, but unlike the changes on the higher frequencies, they do not always result in improved conditions. Throughout minimum period of the sunspot cycle intense ionospheric absorption, between the mid-morning and late evening hours, limits 40 meter propagation to one-hop openings usually not exceeding several hundred miles at best. Ionospheric absorption increases as the sunspot numbers rise, and at the peak of the cycle it is approximately 8 DB more intense than during the years of low sunspot activity. This increase in absorption further weakens signals during the midday period, and also adversely



The new James Model C-1450 Fixed Crossed Mobile Power Supply features:

- Operation from 6 or 12 volts d.c. and 117 volts a.c.
- Supplies receiver power up to 250 volts at 100 ma.
- Supplies transmitter high voltage up to 500 volts at 200 ma. and low voltage up to 250 volts.
- Includes receiver muting relay and complete system control circuit.
- All outputs fully filtered.
- Supplies filament power for a.c. operation.

Model C-1450, wired and tested . . . . . \$69.95

For mobile only, see the companion Model C-1050

Model C-1050, wired and tested . . . \$49.95 Model C-1051, kit . . . . . . . \$39.95



4036 N. Rockwell St. . Chicago 18, Ill.



# SINGLE-SIDEBAND CONVERTER-Model 67A

For connection to the IF output of any communications receiver. Provides exalted-carrier detection of single-sideband, double-sideband AM and PM, and CW signals. Product detector in conjunction with mechanical sideband filter together with crystal controlled carrier oscillators. Eliminates carrier fading distortion and provides the optimum reception for single-sideband as well as all other signals.

The ideal attachment to modernize your present receiver.

Ask for Technical Publication #257.



# CROSBY LABORATORIES, Inc.

P. O. Box 233, Robbins Lane, Hicksville, L. I., New York WElls 1-3191

# BACK ISSUES FOR SALE

1946—June, July, Aug., Sept., Oct., Nov., Dec.

1947—All issues, except Nov.

1948—All issues, except June, Oct.

1949—All issues except Feb., June.

1950—All issues, except Aug., Dec.

1951-All issues.

1952—All issues.

1953—All issues, except July.

1954—All issues, except Feb.

1955—All issues, except Nov.

1956—All issues to date.

# 50c per copy

**CQ** Magazine

67 West 44 St.

New York 34, N. Y.

affects long distance transmissi during the early morning, afternoon and early evening p ods as well. From dawn u sunset, during the years of h solar activity, multi-hop, I distance propagation will gener not be possible on 40 meters. example of this affect is shown Figures, 5-8. During the winter 1953-54, the 40 meter band ened between the East Coast Europe as early as 2 PM E while during the winter of 19 57, the LUF is considerably hill er on this circuit, and the ba is not expected to open until at 5 PM EST. The 40 meter circ between the West Coast and A tralasia remained open until 8 AM PST during the winter 1953-54, but because of the hij er LUF during the period maximum sunspot activity, t circuit will fade out by 6:30 A during the winter of 1956-57. the other hand, during the hol of darkness, when ionospheric: sorption is minimum, the i proved ability of the ionosphe to reflect shortwave signals duri the period of peak solar activ is expected to result in an i provement in propagation contions on the 40 meter band. The improvement will be more notice able on transmission paths follow ing an easterly and westerly dire tion and less noticeable on nort south paths. For example, Figure 5 shows that during the winter 1953-54, the MUF dropped b low 7 Mc at 8 PM EST on the East Coast to Europe path, cau ing the circuit to fail. Frc Figure 6 it can be seen that duri the winter of 1956-57, the MU is expected to remain above 7 N throughout the evening hours an the 40 meter band is expected remain open to Europe until at proximately 4 AM. Beginni with September, and at least und the spring of 1958, we can expevery little change in the 40 met band during the daylight hou when propagation is limited one-hop distances of several hu dred miles. Multi-hop, long di tance propagation is expected be somewhat poorer during th dawn and late afternoon hou because of the increase in ion spheric absorption associated wir [continued on page 110]



Q, THE RADIO AMATEURS'
DURNAL

well-known Hams and authors from

w format, new cover, new material, better cicles are the by-words at the CQ Editorial rices. Reacting to the hundreds of letters reived during the past summer on "what want in CQ," the editors put their heads yether and came up the this NEW looking). Regardless of what month you soose out of the next 12 or 24, CQ will ntain first-rate material from the best thors in the Ham game. Your subscription is a guarantee (a money saving one at that) u will be among the first to see these sureres.

## Q YEARLY BINDERS

ondering what to do with your ose copies of CQ? That's easy. et a CQ binder at a ridiculously leap price and have them at your igertips. Why dig around under e desk, or in some old box to led an important CQ schematic? If your CQ issues immediately a steel reinforced red fabricord nder and keep them ordering sure to specify whether your ant yours stamped for a strikelar year, or just pialn.

\$3.50 each

## SINGLE SIDEBAND TECHNIQUES

by Jack N. Brown, W3SHY

This is the latest addition to the "CQ Technical Series," Over 2000 Hams took advantage of our pre-publication offer and are now probably sitting back enjoying Jack's breezy style of telling the full story of SSB. This book is a continuation of Jack's series "Getting Started on Single Sideband." In this book he goes on to describe two different SSB transmitters and several items of useful test equipment, and throws in a good background on how to keep your SSB signal clean. This is the only book of its kind on the market. Some may try last-minute imitations, but they'll never equal it.

112 pages . . . . \$1.50

## Radio Amateurs' MOBILE HANDBOOK

by William I. Orr, W6SAI

Going Mobile? This manual is indispensable. It covers in logical step by step form all facets of Mobile Operation. This book is the only complete source of such information and is not just a collection of reprints of magazine articles. No other book or manual tells you how to adjust your car regulator, information worth many times the price of the book and little known even in automotive circles. Written in the usual Orr style, the book is both thorough and easy to understand. The book is filled with valuable information nowhere else available and is profusely illustrated with photographs and diagrams. Invaluable.

192 pages . . . . \$2.00

CQ Magazine	CQ.
67 West 44th Street, New York 36, N.Y.	
l enclose \$for which please send me:	
copies of your "Mobile Handbook" at \$2.00/ca	ру.
copies of your "SSB Techniques" at \$1.50/copy	<b>/</b> •
CQ Yearly Binders. Years to be stamped	
,, or plain [].	
Add 3% Sales Tax in New York City.	
My correct address is: (Please Print)	
(name) (calf)	
(street or avenue)	

(eltv)

(state)

(2086)

### Really SILENT A-C Relays

By DOW

Model DKC



1000 WATTS Length 41/2", width 3" Silent A-C magnet prevents hum modulation of carrier — A-C types guaranteed as quiet as D-C.

Special connector protects your receiver ←from R.F. during transmission (Optional).

Transmit contact-pressure over 75 grams, making the 1000 w. rating very conservative. Causes negligible change in SWR up to 100 Mc.

DKF rigid adapter for external chassis mounting, \$1.85



See your distributor. If he has not yet stocked Dow Co-axial relays, order from factory. Send check or money order or will ship COD. Prices net FOB Warren, Minn. Shipping Weight 9 oz. Dealers' inquiries invited. Literature on request.

Add \$1 for external switch (Optional)
Add \$1 for special receiver protecting connector (Optional)

### THE DOW-KEY CO., INC.

WARREN, MINNESOTA

Distributed in Canada by Canadian Electrical Supply Co. Ltd. 275 Craig St., W. Montreal, Quebec

#### RTTY TELEWRITER CONVERTER RTTY

To receive amateur or commercial radio teletype messages, you need: 1. Your radio receiver, 2. Telewriter Converter, which plugs into the phone jack. 3. Polar Relay. 4. Teletypewriter (used commercial equipment available at low prices) Telewriter Converter with tubes and power supply, wired and tested. \$89.50. Polar Relay \$8.50. Write or phone: TOM, W-1-AFN.

ALLTRONICS,

BOX 19, BOSTON 1, MASS.

(RICHMOND 2-0048)



## MOVING?

Please Mail Us Your Change of Address

Also be sure to include your old address, and code line from the mailing label. Or, if you prefer, tear off the entire label and send it along with your new address. Duplicate copies cannot be sent.

CQ MAGAZINE 67 West 44 Street New York 36, N.Y.

the rapid rise in sunspot act Somewhat improved propaga conditions are expected di the hours of darkness, and the meter band is expected to more consistently for DX shortly after sundown and dawn than it did during the of lower sunspot activity. will be especially true for cir to Europe and parts of the East. On longer circuits to Af Australasia, Asia and South erica, the improvement will be as noticeable. With a cons able increase expected in auroral activity and in the oc rence of ionospheric disturban transpolar propagation on 40 ters is not expected to be g during the period of peak s activity.

#### 80 Meters:

Intense daytime absorption lil ionospheric propagation on meters to one-hop, high a radiation out to distances of all 250 miles or so between the ha shortly following sunrise and late afternoon period. sunspot cycle reaches its m mum, daytime absorption on meters increases by approximal 10 DB. This results in consid ably weaker daytime signals a reduction in the distance can be covered by one-hop s during the daytime hours. Dur the summer months of this peri when seasonal absorption is m intense, ionospheric propagat during the mid-day period n not be possible at all, except or very short distances. Solar absol tion on 80 meters begins to crease as the sun goes down, a is minimum during the hours darkness. During the years of 1 sunspot activity, multi-hop, lo distance propagation was possi to most areas of the world fre shortly after sundown until t dawn. Because of the increase ionospheric absorption, the greer affects of auroral absorptic and the greater occurrence ionospheric disturbances expect during the next few years, nig time propagation conditions w become somewhat poorer duri the years of peak solar activit but long distance transmissis should still be possible to max areas of the world. For example Figure 6 shows that 80 meters is expected to open between the East Coast and Europe between the hours of 11 PM and 3 AM EST during the winter of 1956-57. Since the band lies so near the LUF during this period, we can expect that the atmospheric noise level will be high, and signals relatively weak. This circuit is rather typical of the 80 meter night time propagation expected during the period of peak solar activity. In general long distance propagation should be possible during the night time hours to many areas of the world, but the band will be noisier and signal levels will at times be weak, especially on the longer circuits to Australasia, Africa and South America. Trans-polar propagation is not expected to occur on 80 meters during the period of maximum sunspot activity. Unlike the higher frequency bands, propagation conditions on 80 meters do not improve as the sunspot numbers rise, and in fact somewhat poorer conditions are expected during this period.


#### 160 Meters:

Because of the extremely intense daytime absorption at these lower frequencies, skywave propagation is not possible on the 160 meter band during the daylight hours. During this period, 160 meter propagation takes place by way of the groundwave component of the radiated signal. Groundwave propagation depends upon the radiated power, conductivity of the earth, and to some extent antenna polarization, but is independent of sunspot activity. Under average conditions of ground conductivity, using the maximum power limit for this band, groundwave propagation rarely is possible beyond 50 miles on 160 meters, and is usually considerably less than this. Since groundwave propagation is independent of sunspot activity, no changes in 160 meter daytime propagation conditions are expected during the next few years and daytime communications will be possible only over very short distances.

From shortly before sunset, until shortly after sunrise, when ionospheric absorption has decreased

[continued on page 113]





## Whose Shack?

#1 of a series: Famous Hams using the CQ World Globe

Are you still Globeless, or are you one of the many hams who read this ad just so they can feel smug about the fact that they have theirs already and are enjoying them more every day.

huh, which are you?

Anyhow, for you pining minority who plead penury (not enough cash) as your excuse for not having the beautiful World Globe (some excuse, when you could easily go without lunch for a few months), here's what you've been waiting for—A Mammoth CQ Guess Whose Shack This Is World Globe Contest. All you have to do is find out by any means available to you, Whose Shack is pictured above? The first 132,000 winners are eligible for the Low Low Contest Winner's Price for the CQ World Globe plus a one-year new or extension subscription to CQ—only \$19.94!

Don't feel too bad if none of your friends know and you can't afford private detectives.

The regular offer on the Globe and subscription still stands. P.S. Picture entries invited.

CQ Magazine 67 W. 44 Street New York 36, N. Y.	
<b>Gentlemen:</b> Enclosed please find \$19.95. This shack belongs right, please refund the difference.	o If I'm
Name	
Street Address	
City Zone Sta	te

considerably, skywave propagation is possible on the 160 meter band. Even under ideal conditions of minimum absorption and low static levels, propagation beyond distances of 2000 miles is extremely difficult. Optimum conditions exist on this band during the period of low sunspot activity, and as ionospheric absorption increases with the rise in sunspot numbers, night time propagation conditions become poorer on 160 meters. Skip, up to distances of a few hundred miles or so. is expected during the night time period of the next few years, but long distance propagation beyond approximately 1500 miles will be extremely poor, with openings possible for only a very small percentage of time. An occasional DX opening to Europe, and possibly other areas of the world, may occur during the late fall, winter and early spring months, but such openings will be fewer, and conditions poorer, than they were during the past few years of lower sunspot activity.

Timmary:

During the coming period of peak solar activity, beginning with September, 1956 and lasting through the spring of 1958, ionospheric propagation conditions are expected to improve considerably on the 10, 15, and 20 meter amateur bands. Somewhat improved conditions are also expected during the night time hours on the 40 meter band. Skywave propagation conditions are expected to be somewhat poorer on the 40 meter band during the daylight hours. Poorer skywave propagation conditions are also expected on the 80 and 160 meter amateur bands.

#### Six Meters

At this point, the hopes of 6 meter enthusits probably have already been aroused conterably, and there's good reason for it. After we years of nothing more than an occasional boradic-E opening of a thousand miles or so, orld-wide DX on 6 meters is now in prospect. With indications that the present sunspot cycle ay be the highest ever recorded, long distance -2 layer propagation conditions on the 6 eter band are expected to be better than ever reginning this fall. Sunspot activity is already ghe nough for 6 meter openings to have taken ace from areas of the world where MUF's e normally somewhat higher than they are



LOS ANGELES 18, CALIFORNIA

## BARGAINS in QUALITY CRYSTALS BY MANUFACTURER

#### AMATEUR BAND CRYSTALS

#### OTHER FREQUENCIES

All in standard FT 243 Holders Your choice of frequencies ± 1 KC 6000 to 7000 KC......7300 to 8000 KC 50¢ ea.

#### SSB FILTER CRYSTALS

New Surplus Plated Type
54th and 72nd harmonic types in FT 241A
Holders
All channels 370 to 534 KC (except 500 KC)

500 KC .....\$1,25 ea.

## FREQUENCY STANDARD CRYSTALS

100 KC or 1000 KC Glass enclosed types. No surplus. Excellent Temp. Coeff. \$4.50 ea. 5 for \$20.00

Every crystal guaranteed Minimum order \$2.00 NO COD's. Add 5¢ postage per crystal


#### CRYSTALS INCORPORATED

ODELL, ILINOIS



on circuits from the United States. From r Mexico City, XE 1 GE reports almost dl openings to Argentina and Chile during Maj 1956. What is believed to be one of the 6 meter DX openings of the present cy from the United States took place during late afternoon of March 28th, when K 6 O worked several Argentine stations. On Ma 24th, 1956, what appears to be a new 6 mm DX record was established when LU 9 1 in Argentina worked JA 6 FR in Japan, proximately 11,000 miles away. But this only the beginning . . . MUF's are expec to rise above 50 Mc. from the United Sta to almost all areas of the world during the of 1956, the winter and spring of 1957, a the fall, winter and spring of 1958, when so activity is expected to be at peak intense Almost daily 6 meter openings are expect to South America between the noon and ea evening hours of the fall and spring mont with somewhat fewer openings during winter months. During the 1947-50 peak the previous sunspot cycle, a definite tender was observed for the 6 meter band to on between the United States and South American following the breakup of severe ionosphe disturbances, or the occurrence of consideraauroral activity. Six meter openings from eastern and southern areas of the United State to Europe and North Africa (see Figure are expected to begin during the late f months, with peak conditions occurring durit the winter months. Some openings should a be possible during the early spring months. these paths the band is expected to open shor after sunrise and remain open until noon tin The 6 meter band is expected to open from the western areas of the United States to Japi and the Far East between noon and the east evening hours. Openings to Australasia (Ref to Figure 8) from all areas of the Unit States should also be possible from shor after noon through the early evening hours the fall, winter and spring months. The anal sis of these few circuits are intended to gill an indication of 6 meter propagation contions during the period of maximum soll activity. The band is expected to open to most all areas of the world during this perid Six meter cross-country openings, via F-2 pro agation, are also expected on paths great than about 2000 miles, from shortly after no through the late afternoon hours on at least half the days during the fall, winter and sprin months. Ionospheric absorption is usually e tremely low on 6 meters and exceptional strong signal strengths should be possible eve for long distance, low power transmissions. Ionization of the F-2 layer is generally strong

Ionization of the F-2 layer is generally strong enough to support 6 meter propagation in the area of the world only when the smoother sunspot numbers rise above 120. Since 193 the sunspot cycles have risen above this figure during only four years, 1937, and the period



#### P-400-GG

Grounded Grid Linear Amplifier





#### Phasemaster -

the ultimate for AM - PM -CW and SSB - 75 W PEP output completely bandswitched 160 thru 10M — wide pi network output — built in 3500 cycle audio filter complete shielding — no critical ex-ternal balance controls — no mixer tuning ELIMINATES OUT Of Band operation - rounded corner black operation — rounded corner black crackle cabinet with gray front panel with white lettering — 91/4" H x 171/4" W x 111/4" D — a complete wired tested and ALIGNED audio thru balanced modulator subassembly furnished with kit allows transmitter to be built as simply as a CW rig.

W and T \$329.50 Kit \$279.50

See Your Dealer or Write for Literature

#### CHECK THESE OPERATING FEATURES:

- V Utilizes 4 6CN6 grounded grid hi-mu tubes. Low cost in replace-
- V Requires less than 20 W PEP driving power.
- V Wide range Pi network output circuit and Bandswitching 80M thru
- Exclusive power switching circuit makes it impossible to apply plate voltage before filaments are turned on.
- V Exclusive metering circuit reads GRID Ma. PLATE Ma. WATTS Input and WATTS Output directly in WATTS on the meter.
- V Complete built in power supply gives 1250 V DC 380 MA with 30 MFD filter capacity for maximum dynamic plate supply regulation.

W and T \$269.50

ne4

Immediate Shipment



#### TREMENDOUS CRYSTAL CLEARANCE

## Save Money — Order in Package Quantities!

All crystals tested and guaranteed to oscillate. Please include 20¢ postage and handling charge for every 10 crystals or less, Minimum order \$2.50, No. C.O.D's.

PACKAGE DEAL No. 1 25 Assorted FT-243 45 Assorted FT-241 A 15 Assorted FT-171B 15 Assorted CR-1A

100 Crystals Choice \$8.95

Assorted......Regular value \$66.00

PACKAGE DEAL No. 2 FT-241A Crystals for Single Sideband 370 KC-538 KC

35 Crystals Choice \$3.49 Assorted......Regular Value \$14.00

PACKAGE DEAL No. 3

HAM BAND CRYSTALS - FT-243 For operating on 80, 40, 20, 15, 10, 6 and meters—on either fundamentals or

25 Crystals Our \$6.95 Assorted......Regular Value \$20.00









INDIVIDUAL CRYSTALS . Indicate 2nd choice—Substitution May Be Necessary Fundamental Frequencies, fractions omitted.

49¢ each - 10 for \$4.00 10 for \$6.50 460 533 534 536 537 440 463 491 444 466 380 381 383 384 385 425 426 427 473 474 475 476 477 479 448 450 451 404 452 453 455 386 407 387 388 408 436 438 481

79¢ eac	:h1	0 for	only	\$6.5	50
CR-1A SCR 522-1/8 Pin, 1/2" SP		Ba	71B — nana 3 <sub>4</sub> ′′ Si		0
5910 7380 6370 7480 6450 7580 6497 7810 6522 7930 6547 6610 7350	2065 2082 2105 2125	2260 2282 2290		3237 3250 3322 3550 3945	3995



79¢ each - 10 for \$6.50

6550 7306 8350 8650 6573 7325 8375 8690 6575 7425 8383 8700 6600 7440 8400 8733 6173 6175 6185 6040 6.200 6606 8000 6040 6200 6606 8000
6042 6404 6625 8050
6050 6450 6640 8125
6073 6473 6650 8173
6100 6500 7025 8200
6106 6506 7075 8225
6125 6525 7125 8275
6140 6540 7150 8280 8450 8475 8500 8575

## For A Complete Line of Ham Equipment

## TECRAFT TRANSMITTERS

didi

righ

**SH** 

## h



ALL PRICES FOB N.Y.C.

## ARROW ELECTRONICS INC

Digby 9-3790 525 Jericho Tpke. Mineolo, L. I., N. Y. Ploneer 6-8686

#### HALLICRAFTERS SX-100



\$295.00 GET IT FROM DOSSETT

LOW DOWN PAYMENTS
EASY TERMS — HIGH TRADE-INS
FAST — PERSONAL SERVICE
WRITE — CALL OR WIRE
M. H. DOSSETT CO. 355 N. COLUMBIA ST.
FRANKFORT, INDIANA

## 2, 6, 10 — Meter MOBILE EQUIPMENT

MOTOROLA, R.C.A., G.E., LINK, etc. 30-50 Mc., 152-172 Mc. Used Commercial F.M. Communications Equipment Bought & Sold. Complete two-way sets meeting F.C.C. Licensing Requirements for taxicabs, Police, Fire, etc. \$169.00 and up.

Motorola F.M. Receivers, Double

Conversion ..... \$55.00 each

Motorola F.M. Transmitters ..... 45.00 each

## COMMUNICATIONS ASSOCIATES 10 Northampton St., Boston, Massachusetts

Telephone: Highland 5-1385

from late 1946 through 1949. On the other hand, during the sixty-five year period betwee 1871 and 1936, the sunspot cycle failed completely to rise above 120, and it is fortunate for the 6 meter enthusiast that amateur radial did not exist during most of this period!!! The world-wide propagation conditions expected on 6 meters during the peak of the present sunspot cycle may truly be of a "once in a litely time" nature. Bearing in mind the vagaries of the various sunspot cycles, it might be anothe sixty-five years before sunspot activity will again permit long distance communication of the 6 meter band!!!

#### VHF


Despite the fact that the peak of the presen sunspot cycle may be the highest ever recorded it is very unlikely that the regular layers of the ionosphere, in this part of the world, will be able to reflect frequencies higher than 60 Mc The VHF region of the spectrum above 60 Mc. is therefore not directly affected by sunspot activity. The rapidly rising curve of solar activity may however have an *indirect* influence on this region of the spectrum, especially in the northern areas of the United States. Auroral activity is expected to increase considerably, both in rate of occurrence and in intensity, as the peak of the cycle is reached. Associated with auroral activity is a type of propagation that can result in radio communication in the VHF range on frequencies as high as, and possibly higher than, 150 Mc. Reflection takes place only when signals are directed at the aurora, preferably at right angles to it, and is believed to be produced by the signal being scattered from the numerous ionized trails and irregularities associated with the visible aurora. Auroral propagation of this nature occurs over distances up to about 1000 miles, and occurs most often in the northern areas of the United States where visible aurora is more likely to be seen. Signals reflected by this mechanism can be identified by the auroral flutter fade superimposed upon the carrier and frequently making radio telephony unintelligible. An example of intense auroral propagation occurred on the 2 meter amateur band during the vivid display of February 25th, 1956. During this period W 1 FZJ in Medford, Mass. worked W 9 GAB, 880 miles away in Beloit, Wis. and W Ø SV, 1200 miles away in St. Cloud, Minn.

Auroral propagation occurs during the late afternoon and evening hours and more frequently during the spring and fall months. It occurs considerably more often during the years of sunspot maximum than during the period of minimum solar activity.

#### DX TV

During the winter months of the peak sunspot period, 1937-39, television signals on 41-46 Mc. originating in London and Berlin were received at Long Island, N. Y. and as far

# HERE





#### MOBILE POWER



NFW SAFETY **FUSING** 

- 500 V.D.C. at 225 MA. Perfectly filtered.
- Instant Start-No Waiting.
- No battery drain when on standby.
- Low current—low voltage switching. Heavy duty components for dependable, long life operation.
- No ventilation problems. Mount on fire-wall

near battery.
MODEL 606-6 V.D.C. Kit \$32.50
MODEL 612-12 V.D.C. Kit \$35.50
FACTORY WIRED, either model \$7.50 extra
Combination 6 and 12 V.D.C115 V. AC
Model also available. We can supply power cables of any required length.
causes of any required length.

The PALCO BANTAM 65 is only 4" high, 8" wide, 8\%" deep—leaves you lots of leg room. The separate modulator section on a 2" x 2\%" x 11" chassis may be mounted in any convenient location. The exclusive new "tune up" meter was designed with highway safety in mind. No more stooping, no more squinting—you'll like this new idea!

- OTHER OUTSTANDING FEATURES Efficient pi-section output.
   Provisions for mounting standard
- Built-in VFO with 2 xtal posi-
- tions.

  Either 6 or 12 volt filament supply plate supply 450-600 volts @ 250 MA.

  Complete bandswitching 10 thru
- 80 meters Gang tuned VFO and exciter stages.

 AB1 modulation employing negative peak clipping. 

For additional information, see your distributor, or write to . . .

PALCO ENGINEERING

#### FRANKFORT, INDIANA

Break-in CW operation.

coax relay.

Separate inputs for high imped-once or carbon mikes.

## Fantastic Offer!!

Join the CQ Subscriber's Club! Obtain CQ at the unbelievably low rate of 29¢ per year. Just think! Only 2.415¢ per issue! Obtain this benefit and many others\* by joining the CQ Subscriber's Club today! Dues only \$4 per year, \$7 for 2 yrs., \$10 for 3 yrs., including CQ subscription!

\*Other benefits include pride of belonging to such an exclusive club with shrewd amateurs who were also wise enough to take advantage of this marvelous opportunity. Also permission to use 1,000 watts on Six Meters (Technician and General Class only). Additionally, unrestricted permission to buy all CQ Handbooks at regular newsstand rates,

Exclusive rates, available to subscribers only:

One year, \$4

Two years, \$7

Three years, \$10

in U.S., Possessions, APO & FPO, Canada & Mexico. Pan-America and all other foreign: 1 yr. \$6; 2 yrs. \$11; 3 yrs. \$16.

CQ Magazine 67 W. 44 St. New York 36, N.Y.	4 - 3 1 4 7 1	CQ-6
Enclosed is \$ for a to be sent to:	year new renew	al subscription to CQ,
Name		
Address		
City	Zone State	

## Shakespeare \_WONDEROD

Pat Applied

#### Fiberglass Whip Antenna

Try one with your present equip--You'll notice first the shorter ment. length for best impedence match.

-Use it and see how it silences road noises and vibrations. Your Wonderod stands up almost straight at any car speed. Light weight reduces sway as car slows or accelerates.

A surface of full length glass fibers surrounds the conductor metal in Shakespeare's exclusive Howald Process to give greater strength to slim diameter. Wonderod withstands sharp impacts, is extremely flexible. Never takes a set . . . cannot rust or corrode.

Prices (—amateur net) for standard whips 54"-60", 5.75; 61"-90", 6.95. For base extensions 18" -.. 350 dia, 3.95; .500 dia, 4.80;—36" —.350 dia, 4.70; .500 dia, 5.82. Fittings are 3/8" 24 thd, chrome plated brass.

Inquire about custom antennas and industrial applications. Look for the spiral markings, trademark of

Shakespeare Howald Process Wonderods. COLUMBIA PRODUCTS Subsidiary of Shakespeare Co. P. O. Box 5207, Columbia, S. C.

d all H III

di M

48

inland as Indiana. During the peak solar period of 1946-1948, the BBC London TV transmissions were again received quite regularly in the eastern United States during the fall, winten and spring months. To actually see and hear the BBC programs required a TV set modified to receive the British 405 line system and AM sound. With the MUF's to most areas of the world expected to rise above 50 Mc. this fall. long distance propagation of television transmissions should again be possible.

Long distance television broadcasts most likely to be received in the United States are those from countries using the American 525 line standard and operating on Channel 2, between 54 and 60 Mc. These would include: transmissions from Brazil, Mexico, Puerto Rico, Canada, Cuba, Alaska and possibly Hawaii. Several European television stations transmit in the frequency range between 41 and 55 Mc., and while these transmissions will probably be propagated across the Atlantic on a number of days during the fall, winter and spring months of peak sunspot activity, they can not be seen on an American TV set, except as interference lines, because of the different technical standards and channel allocations used by the European stations. These would include transmissions from England, Germany, Holland, Switzerland and France. For the most part, the long distance reception of television signals will be more of a nuisance than an oddity, since these transmissions will at times interfere with the reception of local TV stations, especially in fringe areas. This in effect will be a sort of TV TVI, for which no doubt, amateurs will inadvertently receive a share of the blame.

#### 2-METERS—AN/ARC-4

Get on 2 meters the easy way!! 15 watts A.M.—PLUS a built-in receiver!! (See "CQ"—Nov. '55) Used but excellent, less tubes, less dynamotor, with conversion data for complete 110 V.A.C. Rig with xtl. control!!!

\$15.95
Shock mount rack for ARC-4
\$6.95

#### BENDIX DIRECTION FINDER

 
 MN-26-C. 12-tube remote control Navigation Direction
 Finder and communications receiver. 150 to 1500 Kc in 3 bands.

 28 V. DC input. Ideal for commercial navigation on boats and planes.
 \$14.95

 MN26Y, 150 KC—7MC
 \$24.50

 MN28Y Control for MN26Y
 \$ 5.75

 MN28C Control for MN26C
 \$ 3.75
 \$24.50

SCR 522, 100-156 mc, consists of BC625 Xmtr and BC624 Revr unit, with tubes BC 624 Revr unit, with tubes BC 625 Xmtr. unit, with tubes Scnd M.O. or Check. Shipping Chgs. C Shipping Chgs. C.O.D.

COMMUNICATIONS EQUIPMENT CO. 343 Canal St., Dept. Q-6, New York City 13, N. Y.

#### EASY TO LEARN

It is easy and pleasant to learn or increase speed the modern way — with an Instructograph Code Teacher. Excellent for the beginner or advanced student. A quick, practical and dependable method. Available tapes from beginner's alphabet to typical messages on all subjects. Speed range 5 to 40 WPM. Always ready, no QRM, beats having someone send to you.

#### **ENDORSED BY THOUSANDS!**

The Instructograph Code Teacher literally takes the place of an operator-instructor and enables anyone to learn and master code without further assistance. Thousands of successful operators have "acquired the code" with the Instructograph System. Write today for full particulars and convenient rental plans.

#### INSTRUCTOGRAPH COMPANY

Dept. C., 4701 SHERIDAN RD., CHICAGO 40, ILL.

#### **QRM**

The increase in television ORM is not the only type that can be attributed to the increase in sunspot activity. With the sweet must come some bitter. The considerable improvement in propagation conditions on the 40, 20, 15 and 10 meter bands results in optimum propagation conditions existing simultaneously for both DX and short-skip circuits. Under certain conditions on these bands, stations within distances as short as a few hundred miles and as long as several thousand miles will be skipping in together, resulting in a considerable increase of QRM on each band. The QRM problem is, however, considerably worse for the communication stations in the range 30 to 50 Mc. When the radio spectrum was divided up and allocated to various services at the Atlantic City International Radio Conference of 1947, frequencies between 30 and 50 Mc. were allocated to fixed and mobile services of a "local" nature. These services include Police and Fire Department radio systems, taxi-call services, truck and ambulance dispatching services, etc. At the time of the Conference, the full impact of an exceptionally high sunspot cycle was not yet fully realized, and the general belief was

lit frequencies above 30 Mc. would not be pject to any significant degree of ionospheric pagation, and allocations were made on a nred channel basis throughout the world. Ir example, the Police radio system of one y shares a frequency with dozens of other flice radio systems throughout the world. ring low sunspot activity, there isn't any wave propagation in this frequency range And hence there isn't any problem of interence. As the cycle reaches an exceptionally th peak however, the regular layers of the osphere reflect frequencies as high as 50 c. over great distances and the result is that police radio call in a European city is renved in a police car on a highway in the mited States, or a radio equipped taxi in ruth America suddenly hears a call from a ki-dispatcher in Florida. During the past inter months newspapers carried several pries of these and similar experiences as a sult of radio interference. While some cases my result in rather humorous situations, comunication of a vital local nature may be rupted for several hours at a time. The deral Communications Commission has reatly issued a Public Notice warning all users the radio spectrum below 50 Mc. that they 1st expect to have their communications dispted in this way fairly often during the next w years of peak solar activity.

#### Finale

At the present time, sunspot activity, as easured by the Zurich smoothed sunspot mbers, is approaching a higher level than is previously been recorded in over two huned years of observations. In view of the ose correlation between the sunspot activity d the characteristics of shortwave propagan through the ionosphere, very unusual dio propagation conditions can be expected bring the next few years, and, in particular le ionosphere may be expected to support dio transmission on higher frequencies than er before. The period ahead of us may truly one of "once in a lifetime conditions."

73, George, W3ASK

#### Bibliography

The author wishes to give special acknowlgement to the Central Radio Propagation aboratory of the National Bureau of Standds as the source of most of the basic ionoheric data used in the preparation of this ticle. The following texts were also found be of particular assistance as reference urces:

The Upper Atmosphere, Mitra, pub. The Asiatic Geomagnetism, Chapman and Bartels, pub. The Clarendon Press, Oxford, England.

The Polar Aurora. S.örmer, pub. The Clarendon Press, Oxford, England.

Shortwave Radio and the Ionosphere, Bennington, pub. Iliffe & Sons Ltd. London.

Sunspots In Action, Stetson, pub. The Ronald Press, N. Y.

Ionospheric Radio Propagation, NBS Circular 462, pub. Govt. Printing Office, Wash., D. C. Society, Calcutta.

#### THIS MAY BE YOUR LAST CHANCE . . .

to steal the very best, most popular 2 METER RECEIVER ever released by the Armed Forces!! Best for Novice! Best for Generals! Best for C.A.P.! Best for C.J.! Best for VHF air communications! R-28/ARC-5, 100-156 MC., with all 10 tubes, plus schematic and modification instructions to change from 4-channel fixed tuned to continuous tuning. Ask your buddles about this super-sensitive, super-heterodyne receiver. Excellent condition.

#### UHF CAVITY GIVE-AWAY!

\$4.95



## MATCHED

Gorgeous new line—not surplus! Only 1\%" square. 1\%" hole. Handsome black calibration on white face. 2\% accuracy D'Arsonval movements. Guaranteed!

DC Microamperes: 0-50 . . . \$5.95. 0-100 or 100-0-100

\$5.50, 0-200 . \$4.95. 0-500 . . \$4.50. DC

Milliamperes: 0-1, 0-100, 0-200, 0-300, 0-500, any one
. \$3.50. DC Volts: 0-15, 0-30, 0-500, any one
. \$3.50. DC amps: 0-10 . . \$3.95. RF amps: 0-3

\$5.95. AC Volts: 0-15 or 0-150, either one . \$3.95.

#### FOR 80 AND 40!

Famous BC-696 3-4 MC TRANSMITTER & BC-457 4-5.3 MC (modify easily to 40). With schematics, conversion instructions (Xmtrs in repairable condition less tubes \$7.95 and crystal. Both for only......

#### GERMANIUM DIODE

#### MOBILEERS! THIS ONE IS FOR YOU-ALL

DM-35 12 V. DYNAMOTOR: 625 V. 225 ma. Excellent condition, A steal at only..... \$9.95

#### THE BEST PORTABLE MOBILE 10 & 61

The best for back-pack and automobile. 28-80 MC. AM. Modifications necessary for amateur use are easy and explicitly shown in simple instruction sheet furnished with your order. This is the famous Marine Corps' TBY. Original power supply not included, but power supply which you ean use is spelled out in these instructions.

Transceiver Unit only, excellent, used condition, with tubes. Special

New Transceiver with tubes and accessories (antenna, headset, and carrying bag), all new. \$24.95

#### TEST-SCOPE & PAN-ADAPTOR SPECIAL!

115 V. 60 cyc. The famous 1D-60/APA-10.New with schematic. ONLY \$49.50

DESK-TYPE CRYSTAL MIKES: Brand new!

\$2.95

BULLET-TYPE CRYSTAL MIKES: Extra wide \$4.25 range. Only

FREQUENCY METER AND TEST OSCILLATOR! 115 V., 50-800 cy. power supply. In freq. meter section, crystal oscillator beats VFO. Osc. section puts out sine or pulse modulated RF. With tubes, headset, cords, adapters, radiators, etc. and INSTRUCTION BOOK. LU-3, 465-498.5 MC. 17.95

IF YOU DON'T SEND FOR OUR FREE FLYER YOU'LL NEVER KNOW WHAT YOU'RE MISSING! All shpts, FOB whse, Send 25% dep. with all C.Q.D. orders, Item sub. to prior sale & change of price without notice. Min. order \$2.50.


#### ARROW SALES, INC.

Western Mailing Address: BOX 3007-CQ, NORTH HOLLYWOOD, CALIF.

Central Mailing Address & Sales-Showroom: 2441 S. MICHIGAN AVE., Dept. CQ, CHICAGO 16, ILL. California Distributors' Stores

G. L. Electronics Inc., 1632 Venice Blvd., Los Angeles P.A.R.T.S., INC., 2005 Empire Ave., Burbank

#### **GET ON SSB!**



#### HALLICRAFTERS MODEL HT-30

for SSB, 50 db range meter for constant monitoring of r-f output and carrier suppression. Voice control built in and antitrip features.

Highly stable VFO reads directly in kilocycles. Send for complete technical specifications to:

### Selectronic Supplies, Inc.

1320 Madison Ave. Toledo, Ohio

803 So. Adams St. Peoria, Illinois

### **BOX CHASIS** OFFERS FREE inside LMB BOXES

10 tested kit diagram projects for the builder. Each one of these kit diagrams built by a recognized expert. Kit projects are complete in every detail. Circuit diagram, photo of project both front and rear photo. Rear photo shows wiring and parts. Detailed instructions for building, complete parts list and approximate cost. Complete to build except parts and your distributor can supply the parts. Ask your distributor for the list of LMB kit Diagram Projects. If he does not have them, write to

dist.

441

dy.

1011 Venice Blvd. Los Angeles 15, Calif.

#### AMAZINGNEW VIBROPLEX



PRESENTATION MODEL PRESENTATION MODEL

Yibroplex presents the first really speed control key. An adjustable main spring permits operator to send slower or faster as desired. No more muddy signals . . . no sacrifice of signal quality. Suits any hand or any style of sending. Free of arm tension. Sends easily as pressing a button. Praised by operators and beginners alike. Try this new Vibroplex key! You'll be delighted. Other new popular Vibroplex keys from \$15.95 up. At your dealer or THE VIBROPLEX CO., INC. 833 Broadway, N. Y. 3, N. Y.

#### HAMVENTION

[from page 55]

vided while the YL's attended their for headed by Betty, WN8AXA, at which Jeane Ebur, W3QPQ, Ruth Rickett, W8LGY, Helen Smith, W8SPU, were speakers. The tire ladies' program was under the direct of Ruby Rhude, W8MDK.

Examinations in the General and Ex Class grades were a part of the morning p gram, being made possible by special perm sion of the Commission. During the afternor Novice and Technician license examination were conducted by a group of volunteer wol ers, members of the Dayton Club.

Then a break while the banquet ticket ha ers prepared for the closing treat, enhance this year by the fine electric organ music the hams' own Leo, WØGFQ, of WRL far

John Willig, W8ACE, past president DARA and four-time Hamvention gene chairman, was toastmaster for the 1956 be quet, and began the evening affair with invocation.

At the conclusion of the dinner, toastmas W8ACE presented General Chairman Ru Plak, W8ZOF, DARA President A. B. Hend son, W8WYL, and their staffs, together w honor guests and many well-known hams tending the convention.

The award for the outstanding amateur the area serviced by the Hamvention is mal at the dinner session, and this year Edmund Ryan, W8LRR, of Mansfield, O., was present the trophy.

With the introduction of John Reinart K6BJ, came one of the big thrills of the meeting. His talk was punctuated time a again by bursts of applause, and at the concl sion he was given a thrilling standing ovation

And the only thing to properly wind this kind of a meeting came next—of cours the prize drawing, with the major prize going to W8GVE.

To conclude, some interesting facts: 50 prizes with a total value of over \$4,000 we distributed; nearly every major manufactur and distributor of amateur gear was represent ed at this session, many of whom have sign fied they'll return in '57; advance registration for '56 were almost as large as the total ticket buyers in '51; and the dates for '57 an '58 are set. See you then!

#### **OVARA Picnic in Cincy**

Sunday, June 10 will see the annual picnic of the Ola Valley Amateur Radio Association at the Cincinns Police Firing Range, Evandale, Ohio. No police will fired that day, so come and bring the family and a bask lunch. Lots of games and prizes. Adults \$1, children 25

#### SIGNAL SEPARATION

[from page 61]

eceived signal, properly peaked, over the same signal with the multiplier switched off. (This we are at a loss to account for, since the high-Q circuit shunts the normal i.f. primary winding. However, we have demonstrated the phenomenon to our own satisfaction, time after time.)

(3) Its installation does require tearing into he receiver. But, we hasten to add, the "tearng into" is such a simple procedure that the natural respect for and apprehension of a ham or his commercial receiver can be completely gnored. There are two phases of minor surgery required: one to bring out filament and plate supply leads to feed the twin triode in he QF-1; and the other to tie the gadget onto the high side of the input i-f transformer. (We inderstand there are multipliers on the market which come self-powered, requiring no power from the receiver; too, a separate power supply could be built up to feed filament and B voltages, thus eliminating the first phase of surgery. The second phase must be done, however, in any case.)

With the QF-1, the Heath people supply a length of 3-wire cable, an octal socket, and a plug to match. For a good, permanent-yetremovable installation, it is recommended that a hole be punched, drilled, filed, or cut in the back skirt of the receiver chassis, and the octal socket mounted therein, so that appropriate connections can be made between the socket and the filament, B plus, and ground leads of the receiver supply. This constitutes the first

phase of surgery.

The manufacturer also furnishes a length of co-ax cable, together with an RCA type phono plug and jack. The jack should be mounted in a hole drilled in the receiver chassis as close as possible to the plate contact of the mixer tube or the plate terminal of the input i-f transformer, so that a connecting wire may be kept short. After this wire is soldered in place, the input i-f primary should be touched up to bring it back into alignment; the added capacity of the short wire and jack will have detuned it only slightly. This operation completes the second and final phase of the sur-

With the QF-1 plugged into the receiver, there's a little more to be done yet. The reactance of the co-ax cable has to be tuned out, and the high-Q circuit has to be aligned to center at the middle of the receiver's bandpass. But the manufacturer's instructions are clear, no instruments are required, and the whole

job won't take five minutes.

And after that, Voila! Your Peasant's-Special will separate signals like a Super-Meteor, and you won't have to hock the family furniture after all.

Not for a receiver, anyway. . . .



with a

## TELO-PATCH

Clear undistorted speech with perfect intelligibility at 100% modulation



Actual size 4x4x2 inches

## THREE MODELS TO CHOOSE FROM Original

Economy unit adaptable to all types transmitting and receiving equipment.

#### Amateur net \$14.95

### Supreme

A dual purpose unit for use with all types custom and commercial transmitting and receiving equipment featuring one switch operation for Phone-Patching and Transmit-Receiver control.

## Amateur net \$24.95 Regency

For use with 32V-KW1-75A series equipments. Does not require equipment changes or modifications. Ready for use.

#### Amateur net \$24.95

Consult your radio amateur
equipment dealer for
information and literature
You Can Buy For Less Than You Can Build.

#### CONTINENTAL ELECTRONICS

and

SOUND COMPANY

711 Liscum Drive

Dayton 7, Ohio

HO for the 5 TOP NAMES In-

# **BRAND TUBES**

ONLY new, 1st quality, boxed 90 Day RETMA guaranteed tubes shipped. No seconds, private label, or rewashed "bargains". SATISFACTION GUARANTEED!

New handy air-mail order blank fresh off the press! Lists rovg, xmtg, special purpose tubes, diodes, transistors, etc. WRITE FOR YOUR FREE COPY TODAY!

0B3/VR90\$ .85	250TL Surp 14.00	829B 8.56
0C3/VR10575	HK253 6.50	830B
0D3/VR15075	276G 8.50	832 4.00
2C39A 9.00	304TH Surp 8.75	838
2C43 8.50	304TL Surp10.50	866A 1.25
2C5310.25	339A10.00	
2E31 1.90	350A 3.00	872A 1.25
2E35 1.95	412A 3.90	874
3D21A 3.95	GL-575A10.00	918 1.65
3BP1 1.00	717A50	CK-1007
3DP1 3.30	723A/B 9.00	1500T Surp 75.00
4-750A Surp60.00	750TL Surp 50.00	5551/FG271 37.50
4E27 8.50	803 2.00	5641 6.00
4PR60A Surp 50.00	805 5.00	5643 6.00
4X150A Surp 22.50	003 5.00	5647 5.00
4X150G Surp 32.50	807 1.20	5656 6.00
4X500A50.00		5663 1.25
4X500A50.00	807W/5933	5670 1.10
4X500F Surp 65.00 5BP1 2.50		5676 1.25
	\$2.85	5678
5BP4 3.95		5812 1.50
5FP7 1.20		581480
6AK5	809 2.25	581939.00
6C2117.00	811 3.00	5820 (Icon) 185.00
6K4 2.25	811A 3.85	5894/AX9903 19.00
6SN7WGT 1.95	812 3.50	591580
7GP410.00	812A 3.50	6161
RK-65/5D23 7.50	815 1.50	(RCA-JAN) 70.00
1001H Surp 6.50	816 1.00	8008/872A 3.95
203A 2.50	826	8020 Surp 1.25
We stock ove	r 1,000 other types	write.

EXTRA! SPECIALS! EXTRA!

(g)

rati

WEL

ndl

100 lp)

Fight.

Ige

1 the f

5812 Hytron (improved 2E30) singles, \$1.00 By the pair, each 75c 357A W. E. high power final bottle (worth \$50.00). singles, \$10.00 By the pair, each \$7.50

307A highly improved 2E25 (a real buy!) singles, \$1.20 By the pair, each 95c

singles, \$1.20

By the pair, each

(6AK5W) rugged, long-life 6AK5. FB for
mobile. Use in place of 6AK5 directly. Each

The old work horse of mobile radio.

Special each

\$3.20

Tube Cartons • Stackers • 2 Color or White Write for free price list & sample

#### NOW! FOR THE FIRST TIME! A 1000 WATT SSB AMPLIFIER KIT

AT A SENSIBLE PRICE!

A complete set of electronic components including chassis, meter, tubes, chokes, transformers, condensers, etc. Everything you need to build the real FB 1000 wast SBB amplifier described in CQ. February 1956 issue, pages 27 & 29. (Includes two 803 tubes.) All parts, complete, (less hdwr. & plug-in \$85.00 coil). PREPAID IN U.S.A. (No Cod).

\$65.00 Matching Power supply for above (kit) ..... \$139.50 COMBINATION! BOTH ABOVE KITS ....

#### "PERFECT MATCH" PHONE PATCH.

See description in our ad, May CQ Page 122 or write for details. (Postpaid in USA)

#### TUBE CHECKER SPECIALS!

HICKOCK model 550X. Mutual Conductance Type.
Used, worn, but in good operating condition.

Used, worn, but in good operating condition.

Used, brand new cases, in like new condition with the conductance Type.

PRECISION model 820 (Combo. checker & analyzer) used, in good operating condition.

PRECISION model 912 (same as 920 less analyzer) \$29.00 (OTHERS! LISTED ON "GREEN SHEET" — SEE BELOW

#### FILTER CHOKE SPECIAL!

HEAVY DUTY. 10 H. @ 500 Ma. High voltage in-sulation. Wght. 34 lbs. Herm. sealed. NEW...\$5.50 Write for "BARRY's GREEN SHEET!" Bargains galore in Variaes, Relay racks, Xmtrs, Revrs, Tube checkers, Freq. meters, etc., etc., etc. Even some of our office equipment! Write. Free!

TERMS: 25% with order, balance C.O.D. All merchandise guaranteed. F.O.B., N.Y.C.

#### ELECTRONICS CORP. BARRY Dept. 6-C

512 Broadway, N. Y. 12, N. Y. Call us day or night 24-hour telephone service WAlker 5-7000\_

## The Ham Shop

RATES: 25c per word per insertion for commercial business organizations.

5c per word per insertion for individ-uals on a non-commercial basis. MINIMUM CHARGE \$1.00.

CLOSING DATE: 25th of the 2nd month preceding date of issue.

MAIL: Your typewritten copy with full remittance should be sent to CQ Magazine, 67 West 44th St., New York 36, N. Y. Attention: Classified Ad Dept.

NOTE: The products and services advertised in this section are not guaranteed by the publisher of CQ.

Telephone orders not accepted.

#### FOR SALE

FREE LIST! New and reconditioned receivers, transmit ters, etc. One hundred big bargains every month. Highestrade-in allowance. Write today! Dossett, W9BHV, 851 Burlington, Frankfort, Indiana.

CRYSTALS: FT-243's-3500 to 8700 KC  $\pm$  2 KC, \$1.00 each. .01% setting, \$2.00 each. Hundley Crystal Co., 2951 North 36th, Kansas City 4, Kansas.

TWIN SET precision screwdrivers (9 pieces) under-writers laboratory approved, \$1.00 complete. White Com-pany, 1730C Flatbush Avenue, Brooklyn, N. Y.

INTERESTED IN Hi-Fi? First complete book, 160 pages. on why, what and where to buy high fidelity equipment. Fully describes basic elements of a high fidelity system. Only \$1.00 postpaid anywhere. Audio Fair Publishers, Dept. C, 299 Madison Ave., New York 17, N. Y.

FOR SALE: Leece-Neville 6 volt system 100 amp. alternator, rectifier, voltage regulator with mounting brackets, schematic. Excellent condition, \$49.50. Samuel Lieberman, K2IFL, 130-29 228th Street, Laurelton, Queens 13, N. Y. LA 7-1642.

PERSONAL HAM SUPPLIES! Pocket printer—name, call, address (ink pad included)—\$1.00. 500 miniature labels—name, call, address—\$1.00. Lucite desk wedge, name or call, gold on black—\$2.75. All postpaid. Santer, 544 East 6th St., New York 9, N. Y.

MOVING. HAVE bunch of stuff for sale. Tubes, parts, tools, equipment. Write for list, WØDVN, PO Box 5938, Kansas City 11, Mo.

RUBBER STAMP: Call, name and address, with inking pad and plastic case, \$1.00. Richard's, 2029c Bradley, Chicago 18, Illinois.

ATTENTION MOBILEERS: Leece-Neville 6-volt 100 amp system. Alternator Rectifier and Regulator, \$45.00. Also Leece-Neville 12-volt 100 amp system. Alternator, Rectifier and Regulator, \$85.00. Good condition. H. A. Zimmermann, Jr., K2PAT, 570 Jamaica Avenue, Brooklyn 8, N. Y. UL 2-3472.

FOR SALE: Collins KW-1, perfect condition, like new; 110 foot special heavy duty aermotor tower. All offers considered. K2HLB.

PE-103 OWNERS: 8 pin male Cannon plug made for the PE-103, brand new, \$1.50. Postpaid. W2CRJ, 37-20 Gardenview Terrace, Fair Lawn, New Jersey.

DXCC DIRECTORY: \$1.00 postpaid anywhere. W8YHO.

SELL FOR best offer: High power all band rig—PP813s -807-VFX680. Screens and grids electronically regulated; Variac control for 6500V at 700Ma final power supply 10 meters: Par-Metal cabinet; coaxial fittings; spare tubes. W2TAM.

GARDINER AUTOMATIC sender, twelve rolls tape, slightly used. Best offer over \$12; Audio oscillator \$3. extra. Gale, W1BD, Waterford, Conn.

[from page 12]


#### 50 kc We'd Better Grab

Used to be that the high end of Twenty was Il filled up with DX phone. As a matter of act, that was where 90% of the phone DX ould be found. Then came the axe and we all ost the top half of this segment (14350-4400). Somehow or other most of the DX tations have now set up shop in the lower part of the band and the 14300-14350 segment is slowly getting grassy. Apparently acion on this band is imminent, with many people in favor of extending the present U.S. bhone band to 14350.

Whatever you think should be done it would e prudent to get into action. As you know, ou can send in a petition to the FCC and they will give it every consideration.

#### The Winner

A few issues back we announced a contest or the best designed QSL for the CQ staff.



About three dozen good ideas were submitted. The winner was the above, designed by W4RBI, John W. Moore, Decatur, Georgia. His prize vas a Heathkit Signal Generator SG-1.

73 (x 0°), Wayne, W2NSD

#### SCRATCHI

[from page 8]

peres, on acct. I throwing in the sponge.

So you can seeing why Scratchi are a bit sad, Hon. Ed. The good old days of amchoor adio are reely gone. I still think these Yung Fellers could working more stayshuns if they becoming better operators. And, on the other hands, maybe some of the Old Timers could doing the same if they keeping up with all the new fangled ideas.

Anytime your Hon. Mag. starting a mewseum, letting me know, and I'll sending you 1/c xmitter, toob lineup being 53, 76, push-

pull 42's.

Respectively yours, Hashafisti Scratchi

## IN DETROIT IT'S AARON

ZERO DELAY STROBOSCOPIC 100 WATT SECOND



Sh. Wt. 60 Lbs. With Manual Has external connection for shutter cord BRAND NEW—READY TO OPERATE

2 types—6/12 or 12/24 volts DC source. Complete with 200 watt second Sylvania 1073A bulb, similar to Sylv. R 4330, Trigger & Ignition coil, housed in hand ass'y; (adaptable for any reflector) 15 ft. line cable & 20 ft, of cord and Instruction Manual.

THIS ELECTRONIC PHOTO-FLASH

Is designed to deliver 12,000,000 lumens at the rate of one flash per 1½ seconds. (When trigger is held down.) It has a visibility of over 7 miles. Due to the brilliance of intensity, it is extremely visible through Fog, Rain, Snow. or any bad weather.

\*\*IDEAL FOR AUTOMOBILES\*\*

\*\*Ports\*\* Docks\*\* Read stans Picknicking, Small Airports, Camps.

Boats, Docks, Road stops, Picknicking, Small Airports, Camps, Hunting, Fishing, Boy Scouts, Beacons, Lakes, Cabins, Advertising, Warnings, or Signalling for assistance in emergencies—such as, Accidents, Breakdowns, Loss of Direction, or for any other purpose. (It must be good it is.) Cost \$22.50 the Gov't. \$457.00. Sh. Wt. 50 lbs....Our Price

Spare 200 Watt sec. Sylv. 4330 Flash

\$5.95

SPARE PARTS KIT, Includes Case, Vib., Sylv. Flash Bulb, Rectifier Tubes, Etc.

DIAGRAM For converting Photo-Flash to 110 Cycle. With simple step by step

DYNAMIC MUTUAL CONDUCTANCE

@ 15 AMP. OUTPUT-15 VDC \$6.95 @ 7.3 AMP. MALLORY 1536B74

SCR-274 COMMAND EQUIPMENT \$19.95

Bulb

TRANSMITTERS WITH TUBES & CRYSTALS

1.3-2.1 mc-ARC/5. (160 meter mobile).
First time on surplus market. Brand New.
3-4 mc-ARC/5. 80 meter. Like new.
5.3-7 mc BC 458. Brand new.
7-9.1 mc ARC/5. Brand new. \$7.95 .... 7.95 .... 7.95 RECEIVERS-COMPLETE WITH TUBES

3-6 mc BC 454, fair as is.... 6-9.1 mc BC 455, fair as is.... Splined Tuning Knob, for above receivers....



TRIPLETT AC VOLT & OUTPUT METER 150 VAC. 4000 Ohms. res. in 5 ranges 0-150. \$495 0-60. 0-15. 0-6.0-1.5.

701-A TETRODE SIMILAR TO 4—125 A
4—250 A
Diagram and Info. For Amateur Use With Order
A dandy K.W. SSB final—fil: 8 V. @ 7.5 amps. plate: 3000 V.
@ 200 MA, screen: 280 V. @ 50 MA, Just 10 W. to drive
pair 1 K.W. A.M. phone. Max. input 600 W. per tube, class C
ampH. \$2.95 ea. 2 for \$5.00.
Shipped and Gt'd via Railway Express Only
NOTE—Terms: 25% Deposit, Bal. C.O.D.

#### AARON ELECTRONICS

Dept. E, 3830 Chene St., Detroit 7, Michigan

FOR SALE

T-17's \$4.75; 4-wire Kolled Kords \$1.19; BC-454 (80 Meter) Receiver \$6.95; R4/ARR-2 (220 MC) Superhet Receiver with motor and eleven tubes \$8.95; APC-25 996, APC-30 496, APC-50, 596, APC-10 796; Johnson 122-101 socket 796; Power Supply for TBS-50 \$19.95; Mike Buttons 196; Telegraph Keys 996; Radiosonde Transmitters with 3A5 \$1.29; Dynamic Microphones \$3.95; Single Headsets \$1.19; 100 Carbon resistors \$1.49; BC-366 Jack Boxes 696; Tubes: 6AH6, 6AK5, 601-A, 3A5, HY-65, OA3, 9002, 954, 955 956 each, All plus postage.

LAWRENCE, MASS 5 WOLCOTT AVE.

## **AMATEUR** CRYSTAL Headquarters

#### CRYSTAL HOLDER DATA

FT-243 and FT-241-A holders have 1/2" pin spacing (2 of either of these crystals will plug into any standard octal tube socket). DC-34 holders have ¾" pin spacing-sockets available when ordered with crys- 25¢ tals, each at

#### NOVICEBAND

80 meters within 1 kc of specified frequency-3701 to 3749 kc in DC-34 79¢ or FT-243 holders-(specify holder 79¢ wanted)

#### 40 METERS

H

From 7152 to 7198 kc within 1 kc of 79¢ specified frequency in FT-243 holders only

2-6-10-15-20-40-80 Meter Ham Bands in DC-34 or FT-243 holders 79¢ (specify holder wanted)

#### STOCK CRYSTALS

Send postcard for free list of frequencies. FT-241, DC-34, FT-243, 50¢ FT-171, each

#### SPECIAL CRYSTALS

Crystals ground and etched to exact frequency, using electronic counter, in FT-243 holders with  $\frac{1}{2}$ " pin spacing. From 3000 kc to 9000 kc.

.05% tolerence \$1.35 ea. .01% tolerence \$1.50 ea. .005% tolerence \$2.50 ea.

Crystals ground and etched to exact frequencies in DC-34 holders with  $3/4^{\prime\prime}$  pin spacing. From 1691 kc to 4600 kc.

.05% tolerence \$1.35 ea. .01% tolerence \$1.50 ea. .005% tolerence \$2,50 ea.

#### STOCK CRYSTALS

In FT-243 holders - 5675 kc to 50¢

#### FT-241 LATTICE CRYSTALS

In all frequencies from 370 kc to 540 kc-50c 500 kc Crystals - \$1.00 455 kc Crystals - \$1.00

### Texas Crystals

The Biggest Buy in the U.S.

8538 W. GRAND AVENUE . RIVER GROVE, ILL. ALL PHONES - GLADSTONE 3-3555

Terms: All items subject to prior sale and change of price without notice. All crystal orders MUST be accompanied by check, cash or M.O. WITH PAYMENT IN FULL. NO C.O.D.s. Postpaid shipments made in U.S. and possessions only. Add 5¢ per crystal for postage and handling charge.

## CQ Ad Index

Aaron Electronic Sales	127
Allied Radio Corp. Alltronics American Electronics Co.	93
Alltronics	110
American Flectronics Co	126
Arrow Colog Tro	110
Arrow Electronics Arrow Sales, Inc. Band Guard Electronics Barker & Williamson Barry Electronics Corp.	195
Band Guard Electronics	9 07
Barker & Williamson	4, 01
Barry Electronics Corp	122
Bassett, Rex Inc	92
Bassett, Rex Inc. Bud Radio, Inc. Burghardt Radio Supply	14
Burghardt Radio Supply	95
CQ. Handbooks	109
CQ Subscriptions	117
CQ, World Atlas	106
CQ, World Atlas	112
Clegg Laboratories, Inc	100
Claveland Institute of Radio	
Electronics	8
Collins Radio CompanyCov	ver 2
Columbia Electronics Sales	113
Columbia Products Company Communications Associates Communications Equipment Co.	118
Communications Associates	116
Communications Equipment Co	118
Continental Electronics & Sound Co.	121
Crosby Laboratories, Inc	108
Crystals Inc	114
Curlo Padio Supply	196
Davis Floatronics	01
Degreett M H Co	116
Davis Electronics Dossett, M. H. Co. Dow-Key Company Eitel-McCullough, Inc. Electronic Outlet Engineering Associates	110
Dow-Key Company	110
Eitel-McCullough, Inc	11
Electronic Outlet	127
Engineering Associates	126
Glass, J. J. Co	102
Gonset Company	18
Gotham Hobby Corp	91
Hallicrafters Company	7
Harvey Radio Company	104
Heath Company4,	5, 12
Hershel Radio Company	. 98
Instructograph Company	118
Hallicrafters Company Harvey Radio Company Heath Company Hershel Radio Company Instructograph Company International Crystal Mfg. Co.	50
International Crystal Mig. Co	107
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMR Roy Chassis	107
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMR Roy Chassis	107
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMR Roy Chassis	107
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMR Roy Chassis	107
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMR Roy Chassis	107
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMR Roy Chassis	107
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co.	107 124 15 114 120 111 115 126
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co.	107 124 15 114 120 111 115 126
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics. 1	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics  1 National Company, Inc. Co.	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics  1 National Company, Inc. Co.	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics  1 National Company, Inc. Co.	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics 1 National Company, Inc. Cor Palco Palmer, Joe Petersen Radio Company, Inc.	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics  1 National Company, Inc. Palco Palco Palmer, Joe Petersen, Radio Company, Inc. Philoo	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics . 1 National Company, Inc Cov Palmer, Joe Petersen. Radio Company, Inc. Philco Pierson-Holt Electronics Co.	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics . 1 National Company, Inc Cov Palmer, Joe Petersen. Radio Company, Inc. Philco Pierson-Holt Electronics Co.	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics . 1 National Company, Inc Cov Palmer, Joe Petersen. Radio Company, Inc. Philco Pierson-Holt Electronics Co.	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics  1 National Company, Inc. Palco Palmer, Joe Petersen Radio Company, Inc. Philco Pierson-Holt Electronics Co. RCA Tubes Rex Radio Supply Co.	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics  1 National Company, Inc. Palco Palmer, Joe Petersen Radio Company, Inc. Philco Pierson-Holt Electronics Co. RCA Tubes Rex Radio Supply Co.	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics  1 National Company, Inc. Palco Palmer, Joe Petersen Radio Company, Inc. Philco Pierson-Holt Electronics Co. RCA Tubes Rex Radio Supply Co.	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics  1 National Company, Inc. Palco Palmer, Joe Petersen Radio Company, Inc. Philco Pierson-Holt Electronics Co. RCA Tubes Rex Radio Supply Co.	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics 1 National Company, Inc. Palco Palmer, Joe Petersen Radio Company, Inc. Philco Pierson-Holt Electronics Co. RCA Tubes Cox Remington Rand Univac Rex Radio Supply Co. Sam's Surplus Selectronic Supplies, Inc. Sun Parts Distributors, Ltd. Technical Materiel Corp	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics 1 National Company, Inc. Palco Palmer, Joe Petersen Radio Company, Inc. Philco Pierson-Holt Electronics Co. RCA Tubes Cox Remington Rand Univac Rex Radio Supply Co. Sam's Surplus Selectronic Supplies, Inc. Sun Parts Distributors, Ltd. Technical Materiel Corp	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics 1 National Company, Inc. Palco Palmer, Joe Petersen Radio Company, Inc. Philco Pierson-Holt Electronics Co. RCA Tubes Cox Remington Rand Univac Rex Radio Supply Co. Sam's Surplus Selectronic Supplies, Inc. Sun Parts Distributors, Ltd. Technical Materiel Corp	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics  1 National Company, Inc. Cor Palco Palmer, Joe Petersen Radio Company, Inc. Philco Pierson-Holt Electronics Co. RCA Tubes Rex Radio Supply Co. Sam's Surplus Selectronic Supplies, Inc. Sun Parts Distributors, Ltd. Technical Materiel Corp. Tennalab Texas Crystals Truart Products Company	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics . 1 National Company, Inc. Co. Palco Palmer, Joe Petersen Radio Company, Inc. Philco Pierson-Holt Electronics Co. RCA Tubes	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics . 1 National Company, Inc. Co. Palco	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics . 1 National Company, Inc. Co. Palmer, Joe Petersen Radio Company, Inc. Philco Pierson-Holt Electronics Co. RCA Tubes . Co. Remington Rand Univac Rex Radio Supply Co. Sam's Surplus Selectronic Supplies, Inc. Sun Parts Distributors, Ltd. Technical Materiel Corp. Tennalab Texas Crystals Truart Products Company U. S. Crystals Valparaiso Technical Institute Vibroplex Company, Inc. Walsco Electronics Corp.	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics . 1 National Company, Inc. Co. Palmer, Joe Petersen Radio Company, Inc. Philco Pierson-Holt Electronics Co. RCA Tubes . Co. Remington Rand Univac Rex Radio Supply Co. Sam's Surplus Selectronic Supplies, Inc. Sun Parts Distributors, Ltd. Technical Materiel Corp. Tennalab Texas Crystals Truart Products Company U. S. Crystals Valparaiso Technical Institute Vibroplex Company, Inc. Walsco Electronics Corp.	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics . 1 National Company, Inc Co. Palmer, Joe Petersen Radio Company, Inc. Philco Pierson-Holt Electronics Co. RCA Tubes	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics . 1 National Company, Inc. Co. Palco Palmer, Joe Petersen Radio Company, Inc. Philco Pierson-Holt Electronics Co. RCA Tubes . Co. Remington Rand Univac Rex Radio Supply Co. Sam's Surplus Selectronic Supplies, Inc. Sun Parts Distributors, Ltd. Technical Materiel Corp. Tennalab Texas Crystals Truart Products Company U. S. Crystals Valparaiso Technical Institute Vibroplex Company, Inc. Walsco Electronics Corp. Western Gear Corporation Wholesale Supply Co.	
James Vibrapowr Company Jara Sales Company Johnson, E. F. Co. Kaar Engineering Corp. LMB Box Chassis LW Electronic Laboratory Lakeshore Industries Lee Electronic Engineering Co. Lewis, E. B. Co., Inc. Lynch, J. Electronic Co. Millen, James Mfg. Co. Mosley Electronics . 1 National Company, Inc Co. Palmer, Joe Petersen Radio Company, Inc. Philco Pierson-Holt Electronics Co. RCA Tubes	